

Internal File System Errors

1	chNoBuf	no free cache buffers (all in use)
2	chInUse	requested block in use
3	chnotfound	requested block not found
4	chNotInUse	block being released was not in use
16	fxRangeErr	file position beyond mapped range
17	fxOvFIErr	extents file overflow
32	btnotfound	record not found
33	btexists	record already exists
34	btnospace	no available space
35	btnoFit	record doesn't fit in node
36	btbadNode	bad node detected
37	btbadHdr	bad BTree header record detected
48	cmnotfound	CNode not found
49	cmexists	CNode already exists
50	cmnotempty	directory CNode not empty (valence = 0)
51	cmRootCN	invalid reference to root CNode
52	cmbadnews	detected bad catalog structure
53	cmFThdDirErr	thread belongs to a directory not a file
54	cmFThdGone	file thread doesn't exist
64	dsBadRotate	bad BTree rotate

Slot Declaration ROM Manager Errors

1	silnitSDTbErr	slot int dispatch table could not be initialized.
2	silnitVBLQsErr	VBLqueues for all slots could not be initialized.
3	silnitSPTbErr	slot priority table could not be initialized.
10	sdmJTInitErr	SDM Jump Table could not be initialized.
11	sdmInInitErr	SDM could not be initialized.
12	sdmSRTInitErr	Slot Resource Table could not be initialized.
13	sdmPRAMInitErr	Slot PRAM could not be initialized.
14	sdmPrilInitErr	Cards could not be initialized.

HD20 Driver Errors

16	wrtHsLw	HSHK low before starting
17	wrtHSLwTO	Time out waiting for HSHK to go low
19	wrtHSHighTO	Time out waiting for HSHK to go high
32	rdHsHi	HSHK high before starting
33	rdSyncTO	Time out waiting for sync (\$AA) bye
34	rdGroupTO	Time out waiting for group
36	rdHoffSyncTO	Time out waiting for sync after holdoff
37	rdHsHiTO	Time out waiting for HSHK high
38	rdChksumErr	Checksum error on response packet
48	invalidResp	First byte in response packet was wrong
49	sqncNumErr	Sequence number in response packet was wrong
50	dNumberErr	Drive number in response packet was wrong
64	noResp	No response packet ever received

SCSI Manager Errors

2	scCommErr	Communications error (operations timeout)
3	scArbNBErr	Arbitration failed during SCSIGet - Bus busy
4	scBadparmsErr	Bad parameter or TIB opcode
5	scPhaseErr	SCSI bus not in correct phase for operation
6	scCompareErr	SCSI Manager busy with another operation when SCSIGet was called
7	scMgrBusyErr	SCSI Manager busy with another operation when SCSIGet was called
8	scSequenceErr	Attempted operation is out of sequence - e.g., calling SCSISelect before doing SCSIGet
9	scBusTOErr	Bus timeout before data ready on SCsIRBlind and

SCSIWBlind

10 scComplPhaseErr SCSIComplete failed - bus not in Status phase

Serial Driver Error Masks

1 swOverrunErr Serial Driver overrun error
16 parityErr Serial parity error
32 hwOverrunErr Serial hardware overrun
64 framingErr Serial framing error

Miscellaneous Result Code

1 evtNotEnb Event not enabled at PostEvent

CDev Errors

0 cdevMemErr Memory shortfall; alert user please
1 cdevResErr Couldn't get a needed resource; alert
3 cdevUnset cdevValue is initialized to this
-1 cdevGenErr General error; gray cdev w/o alert

Script Manager Errors

0 smNotTruncated No truncation was necessary
1 smTruncated Truncation performed
-1 smTruncErr General error

Communications Toolbox Errors

0 ctbuNoErr ????
-1 ctbuGenericError ????

Communications Resource Manager Errors

0 crmNoErr ????
-1 crmGenericError ????

Connection Manager Errors

0 cmNoErr ????
1 cmRejected ????
2 cmFailed ????
3 cmTimeOut ????
4 cmNotOpen ????
5 cmNotClosed ????
6 cmNoRequestPending ????
7 cmNotSupported ????
8 cmNoTools ????
9 cmUserCancel ????
11 cmUnknownError ????
-1 cmGenericError ????

File Transfer Manager Errors

0 ftNoErr ????
1 ftRejected ????
2 ftFailed ????
3 ftTimeOut ????
4 ftTooManyRetry ????
5 ftNotEnoughDspace ????

6 ftRemoteCancel ????
7 ftWrongFormat ????
8 ftNoTools ????
9 ftUserCancel ????
10 ftNotSupported ????
11 ftUnknownError ????
-1 ftGenericError ????

Midi Manager MIDIPacket Errors

1 midiOverflowErr ????
2 midiSCCErr ????
3 midiPacketErr ????
255 midiMaxErr all command words less than this are errors

Terminal Manager Errors

0 tmNoErr ????
1 tmNotSent ????
2 tmEnvironsChanged ????
7 tmNotSupported ????
8 tmNoTools ????
11 tmUnknownError ????
-1 tmGenericError ????

AppleTalk Errors

-1 overrunErr ???? (returned by ReadPacket & ReadRest routines)
-2 crcErr ????
-3 underrunErr ????
-4 lengthErr ????

System Errors to put up msg dialogs

-10 dsMacBugInstalled say "MacBug Installed"
-11 dsDisassemblerInstalled say "Disassembler Installed"
-12 dsHD20Installed say "HD20 Startup"