

New Technical Notes

Macintosh



®

Developer Support

SCSI Port Q&As

Hardware

M.HW.SCSI.Q&As

Revised by: Developer Support Center

October 1992

Written by: Developer Support Center

October 1990

This Technical Note contains a collection of Q&As relating to a specific topic—questions you've sent the Developer Support Center (DSC) along with answers from the DSC engineers. While DSC engineers have checked the Q&A content for accuracy, the Q&A Technical Notes don't have the editing and organization of other Technical Notes. The Q&A function is to get new technical information and updates to you quickly, saving the polish for when the information migrates into reference manuals.

Q&As are now included with Technical Notes to make access to technical updates easier for you. If you have comments or suggestions about Q&A content or distribution, please let us know by sending an AppleLink to DEVFEEDBACK. Apple Partners may send technical questions about Q&A content to DEVSUPPORT for resolution.

|New Q&As and Q&As revised this month are marked with a bar in the side margin.

SCSI/NuBus card development tools and resources

Written:

Last reviewed:

Are there any new tools or resources for developing a SCSI/NuBus card? None of the slot tools available on AppleLink have been updated since September 1989.

We recommend you look at the application named Slots, on the latest Developer CD Series disc. It allows you to look at declaration ROM sResources and make your own calls to the Slot Manager. It was written in 1990 by an engineer working on the Slot Manager.

SCSI hardware specifications: Where to get docs

Written: 8/30/91

Last reviewed: 2/17/92

SCSI-1 and Common Command Set (CCS) hardware specifications are published by the

American National Standards Institute. You can request specifications (from this organization) by contacting them at:

American National Standards Institute
1430 Broadway
New York, NY 10018

SCSI-1 and CCS specification numbers are as follows:

SCSI-1: ANSI X3.131-1986 / ISO DP 9316 / ECMA-111
CCS: X3T9.2/85-52, 1986 (Revision 4.B)

SCSI-2 and most other SCSI documents are available from:

Global Engineering Documents
2805 McGaw
Irvine, CA 92714
Tel: (800) 854-7179 or (714) 261-1455

The SCSI-2 specification number is:

SCSI-2: ANSI X3.131-1990 (Revision 10c)

SCSI terminator specs

Written: 12/7/90

Last reviewed: 2/20/91

Please provide us with specs on Apple Part No. M0332LL/A, and also information on what type of SCSI terminator can be used for Macintosh IIfx.

Specs for Apple SCSI terminators (the original gray terminator and the special black Macintosh IIfx terminator) can be found in the Macintosh Technical Note “SCSI Termination.” The Macintosh IIfx requires the black terminator for external termination and either a properly terminated internal hard disk or the internal termination block and filter for internal termination. All Macintosh IIfx computers shipped without an internal hard disk include this internal terminator and filter plugged into the SCSI connector on the logic board.

X-Ref:

Macintosh Technical Note “SCSI Termination”

Macintosh/SCSI compatibility

Written: 12/11/90

Last reviewed: 3/13/91

Is there any reason that a SCSI device (scanner) would work on a Macintosh IIfx but not work on a IIci?

Without a bit more information it is difficult to speculate what might be causing the problem. If you access the scanner through the SCSI Manager, there should be no problem. Usually it is the other way around (works on the Macintosh IIci but not on the IIfx). If any part of your driver does access hardware directly on the Macintosh IIci, it would likely have problems on the IIfx because its SCSI hardware is very different. It may simply be related to termination

on the SCSI bus and not driver code on the IICI. The IICI is prone to termination problems if there is no internal HD or if it is not properly terminated externally. Check for that possibility by changing the arrangement of SCSI devices. There are also some specific bugs/quirks in the

SCSI Manager documented in the Macintosh Technical Notes “SCSI Bugs,” “The Joy of Being 32-Bit Clean,” and “Our Checksum Bounced.”

Cannot make SCSI inquiries of CPU

Written: 12/12/90

Last reviewed: 1/16/91

Is there a way to get the SCSI information for the CPU (ID 7) using a SCSI call?

—

No, sorry. The SCSI protocol says that there is a SCSI bus Master and a SCSI target, and that the two will not be the same. Since the Macintosh is always the master, there is no way you can make inquiries of it.

Connecting two Macintosh systems via SCSI

Written: 12/12/90

Last reviewed: 7/26/91

How can I connect two Macintosh systems together using the SCSI port so they can run in parallel?

—

For many reasons, connecting any two systems via SCSI port to SCSI port should not be attempted. The most important reason is that you would then have two devices (the CPUs, and probably the internal drive) on the bus with the same SCSI ID. Further, a straight-through cable would connect outputs to outputs and inputs to inputs, which would bring communications to a halt.

However, a SCSI-to-SCSI connection, like the type mentioned below, is possible between the Macintosh Portable and a desktop Macintosh using LapLink Macintosh III from Traveling Software. It works only on the Macintosh Portable since the SCSI ID of the Macintosh Portable can be changed from 7 to 6, avoiding the ID conflicts. Traveling Software also provides a special SCSI-SCSI cable, which is required for this connection. (This setup cannot connect two desktop Macintosh systems unless the drive ID can be changed. This is not possible with Apple’s internal drives but you may be able to do it with other internals. In any case, this is unsupported, so if you attempt this you do so at your own risk. You probably will void your warranty.)

LapLink Macintosh III
Traveling Software, Inc.
18702 North Creek Parkway
Bothell, WA 98011
206-483-8088

If Macintosh doesn't boot with multiple SCSI devices

Written: 12/17/90

Last reviewed: 7/26/91

What would cause the system to refuse to boot up when I connect a third-party SCSI drive after the Apple CD-ROM drive?

Your problems with the CD SC and a third-party disk are probably related to noise on the SCSI bus. We use CD SCs here with as many as 5 other external SCSI devices without problems. However, any SCSI device's performance can be affected by noise and is exacerbated as more devices are added to the SCSI chain. The most common causes of noise are improper termination, damaged or poor quality cables, and incorrectly designed SCSI devices. Because DTS successfully uses the CD with multiple devices (both Apple and third party), we suspect the third party drive is the source of the noise. If it uses any kind of internal termination, the terminator **MUST** be removed. Apple recommends that all SCSI device manufacturers not use internal termination, relying instead on the external terminators provided by Apple which can easily be rearranged or upgraded (as with the Macintosh IIfx). Also, try a different SCSI peripheral cable in case yours is damaged or not up to par. You may also be having problems if there is no internal hard drive in your system. This leaves the internal end of the SCSI bus unterminated. This is particularly a problem for the fast CPUs such as the Macintosh IIfx and Macintosh IIfx, because they are more sensitive to noise. If this is the case, try installing an internal hard drive, or you can obtain an internal SCSI terminator from MicroNet (see the Macintosh Buyer's Guide for a #/address). For more information, see the Macintosh Technical Note "SCSI Termination."

Using Macintosh SCSI Manager for direct disk access

Written: 5/7/91

Last reviewed: 7/25/91

I would like to read and write sectors directly on a SCSI disk. Do I need to access the SCSI chip directly or can I use the SCSI Manager for this?

The normal way to access a SCSI disk is to use the Macintosh® file system, which calls the SCSI Manager to access the SCSI bus and command the hard disk to read or write data in various blocks. You should be able to directly command the hard disk yourself and directly send and receive the sector buffers by calling the SCSI Manager to perform the SCSI communication for you.

Pseudo code to perform this kind of transaction would be:

- Prepare a command block for read or write, etc.
- Prepare your data buffer and a transfer instruction block (tib) containing instructions for

data transfer. For example, a tib for transferring six 512-byte blocks of data from or to address \$67B50 contains the following:

SCINC	\$67B50	512
SCLOOP	-10	6
SCSTOP		

- Call SCSIGet() to gain control of the buss
- Call SCSISelect(TargetId) to select the target device (your hard drive) and allow the target to command the bus.
- Call SCSICommand(CommandBlock,Length) to give the SCSI Manager the command you want it to transfer when the target requests the command.
- Call SCSIRead(tib) (or SCSIWrite) to tell the SCSI Manager where to put the bytes (or where to get them from on a write) when the target requests them.
- Call SCSIComplete(Status, message) to finish the transaction and receive the (potential) error code.

If what you intended to ask was how to write your own SCSI hardware driver, be aware that this is not an area that DTS normally supports. If you are developing for a unique SCSI device that cannot be interfaced to using the provided SCSI Manager, please let DTS know the details about your device and the problems you are encountering that will not allow its control via the SCSI Manager. Also, please note that the specific SCSI chip used in a specific Macintosh model may change in some future Macintosh model and will break your custom driver, requiring you to rev your driver if you want to continue to be compatible. For this reason we strongly suggest that you use the provided SCSIManager if at all possible.

Transferring data from SCSI device to Macintosh

Written: 8/30/91

Last reviewed: 8/30/91

How can an external SCSI device interrupt the Macintosh system CPU? What's the procedure for transferring data from my external SCSI device's buffer to system RAM?

—

Transferring data from a SCSI device to a Macintosh is not a simple task. The Macintosh SCSI implementation does not support arbitration, so only the Macintosh can start a SCSI transaction. If someone else were to begin transferring data on the bus, and the Macintosh wanted to begin a transfer, it would not know how to deal with the situation.

This rules out your SCSI device being able to decide to send data to the Macintosh. The only way to accomplish what you need to do is to write a VBL or Time Manager task that periodically checks your device to see if it needs to be serviced, and if so, initiates a SCSI transfer to get the data from it. While this approach requires somewhat more care, because of its granularity, it should prove adequate.

Currently A/UX is only OS to use Macintosh IIx SCSI DMA chip

Written: 8/15/91

Last reviewed: 8/15/91

Does System 6.0.7 or 7.0 make use of the DMA portion of the Macintosh IIx hardware?

—

System 7.0, or any version of the Macintosh operating system at this point, does not utilize the SCSI DMA chip in the Macintosh IIx. A/UX is the only operating system on the Macintosh that does use this chip.

Apple SCSI cable information

Written: 9/17/91

Last reviewed: 9/17/91

Where can we get specs for Apple's SCSI cables, similar to Apple's paint and finish standard, which allows us to match our hardware exactly to the Macintosh family? SCSI details we are concerned with are: single versus double shielding, contact types (such as gold), wire gage, and color.

The information you've requested is unavailable for distribution. Apple simply doesn't supply specifications for any of its hardware to outside parties. However, you might try looking at the following SCSI specifications for more information:

Specification:	Available from:
SCSI-1: ANSI X3.131-1986 ISO DP 9316 ECMA-111	American National Standards Institute 1430 Broadway New York, NY 10018
CCS: X359.2/85-52,1986 (Rev 4.B) (Common Command Set)	American National Standards Institute 1430 Broadway New York, NY 10018
SCSI-2: ANSI X3.131-1990 (Revision 10c)	Global Engineering Documents 2805 McGaw Irvine, CA 92714 Tel: (800) 854-7179 or (714) 261-1455

These specifications discuss SCSI interface and, although they don't tell you exactly how to build a SCSI cable, they give you a good benchmark for engineering one. Both of the above specs are available from:

Another alternative is to go out and buy one of Apple's cables and reverse engineer it. Your local dealer might be the best location for this.

Use Macintosh SCSI Manager for SCSI chip compatibility

Written: 10/22/91

Last reviewed: 10/22/91

Our SCSI driver asserts the SCSI bus protocol directly, according to the SCSI bus specs, using the low-memory global SCSIBase as the SCSI base address. Our code works fine on systems using the NCR 5380, but hangs with the new SCSI NCR 53C96. Do I need to add a NOP somewhere because the new chip is faster?

Although SCSIBase is exactly where a SCSI device driver should look to find the base address of a SCSI chip in the Macintosh, the NCR 53C96 is a physically different chip than the NCR 5380. Besides having its registers in different locations of the address map and a slightly different register set, the chip takes on much more of the burden (and control) of accessing the SCSI bus. The major difference is that with the 5380, the chip controller (drvtr) needs to actively respond to the phases of the SCSI bus as the target changes them and to be ready to correctly react to any unexpected changes in state. For continued compatibility with the Macintosh product lines, your driver must use the SCSI Manager rather than to write directly to the chip. With the new chip (5396) the chip controller needs to set up all information for the entire command sequence (Arbitration thru Message In) and then tell the chip to execute it. The “controller” is not in direct control of the SCSI bus. (With the earlier chip, it’s really the Target that’s always in control, not your driver, but the 5380’s interaction model gives the IMPRESSION that your driver is in control.)

Your best course of action is to make sure your SCSI driver uses the SCSI Manager so that you will automatically work on all Macintosh platforms in the event that Apple changes chips in the future. If there is something odd about your SCSI device that it just cannot be accommodated by the SCSI Manager (this is rare!) then you will need to get the documentation for the NCR 5396 (from NCR) and rewrite your driver to use this new “setup and go” interaction model.

gestaltHardwareAttr hasSCSI selector

Written: 1/3/92

Last reviewed: 1/27/92

Why does the gestaltHardwareAttr selector on the Macintosh IIfx return a selector indicating no SCSI available?

—

Labelling bit 7 of the response to the gestaltHardwareAttr selector “hasSCSI” is a bit misleading. gestaltHardwareAttr is supplying information about the very low-level hardware implementation. What bit 7 signifies is the presence of a standard 53C80 SCSI chip (the kind in use from the Macintosh Plus up to the IIfx). The IIfx has a different implementation of the 53C80 that allows for SCSI DMA, hence a different bit is used. The new Quadras have yet another chip, the 53C96, so different bits are used for those, as well.

The reason this is not more clearly documented is that it is very rare for applications to need this level of detail. Depending on such information virtually guarantees your application will be hardware dependent and so, incompatible in the future.

Here are the latest, official gestaltHardwareAttr flags from MPW 3.2.1. Any other flags remain undocumented.

```
gestaltHardwareAttr = 'hdwr';    { hardware attributes }
gestaltHasVIA1 = 0;             { VIA1 exists }
```

gestaltHasVIA2 = 1;	{ VIA2 exists }
gestaltHasASC = 3;	{ Apple Sound Chip exists }
gestaltHasSCC = 4;	{ SCC exists }
gestaltHasSCSIDMA = 6;	{ SCSI on the IIfx }
gestaltHasSCSI = 7;	{ SCSI exists }
gestaltHasSWIMIOP = 8;	{ SWIM IOP on IIfx }
gestaltHasSCCIOP = 9;	{ SCC IOP on IIfx and Quadra 900 }
gestaltHasSCSI961 = 21;	{ 53C96 SCSI controller on internal bus }
gestaltHasSCSI962 = 22;	{ 53C96 SCSI controller on external bus }

```
gestaltHasUniversalROM = 24;      { Do we have a Universal ROM? }
```

You can use the GestaltDA in the Tools&Apps:OS/Toolbox folder on the latest Developer Series CD to see gestaltHardwareAttr and other Gestalt values.

Macintosh Quadra SCSI data transfer

Written: 1/15/92

Last reviewed: 2/6/92

My application has problems with Macintosh Quadra SCSI data transfer. I think it depends on the SCSI-chip installed in the machine. Is there a Gestalt definition for the SCSI-chip installed?

—

You need to examine the 6th, 7th, and 21st bits of the gestaltHardwareAttr selector. To investigate hardware-dependent bit values, use the Gestalt DA, which you'll find on the latest Developer CD Series disc.

Make sure your software doesn't read or write to SCSI hardware directly. For example, the Quadra utilizes the 53C96, so it won't correctly interpret or queue a SCSIstat call. With the 53C96, you don't have access to the state of the SCSI bus lines. In implementation, the 53C96 is more abstract than the 53C80; software no longer has the same access to the physical layers of the chip's instruction set. Your software development should allow the SCSI Manager to handle the 53C96 chip/software interaction.

X-Ref:

“gestaltHardwareAttr hasSCSI selector” Q&A

Macintosh Quadra and SCSI termination

Written: 11/27/91

Last reviewed: 11/27/91

Proper SCSI termination is critical for correct operation of the Macintosh Quadra computers, just as with all Macintosh computers. The Macintosh Quadra computers require external SCSI termination at the end of the device chain, either supplied by the last device in the chain, or using a standard Apple SCSI Cable Terminator (M0332LL/A). Note that this is the standard SCSI terminator, NOT the black terminator required by the Macintosh IIx (although the black IIx terminator may be used as well).

Termination is generally supplied at the factory for use with internal SCSI devices. Some early floppy-only Macintosh Quadra 700 units may not have internal termination, so users who attach external SCSI devices (without having added an internal SCSI device) may need to double terminate their external SCSI chain. Properly terminated floppy-only Macintosh Quadra 700 units will have a terminator inserted into the motherboard internal SCSI cable connector. Users of internal SCSI devices must, of course, remove this terminator before connecting their internal SCSI device.

The Macintosh Quadra 900 is the first Macintosh computer to provide a separate, internal SCSI bus. This bus is physically isolated from the external SCSI bus and must also be properly terminated. The cable provided with the machine includes all the termination necessary, so ALL internal devices must have SCSI termination removed before connecting to the internal

Macintosh Quadra 900 SCSI cable. If extra termination is supplied it may cause intermittent hardware failures as well as physical damage to the device.

Developers who ship terminated SCSI devices for possible internal use in the Macintosh Quadra 900 must provide users with instructions for removing the termination.

Can I have a device powered off and connected to the SCSI bus?

Written: 5/14/90

Last reviewed: 11/19/90

Can I have a device powered off and connected to the SCSI bus?

The SCSI specification does not define how a device is to behave while powered off. The best advice and the official line from Apple is not to have devices on the bus and powered off. It's been found that having devices powered off and on the bus causes degradation to performance and the signals. This is the issue: electrical problems of termination and termination power. Some devices are NOT following the description of how Apple's devices work, and following the guidelines of the Apple cable guide does not apply with non-Apple devices. The termination problem can cause hardware damage. Therefore, the rule is this: Do NOT have devices connected to the bus with their power off. Also, do not power on a device connected to the bus after booting and never connect one while the system is on.

Macintosh IIfx SCSI compatibility

Written: 6/29/90

Last reviewed: 12/17/90

My SCSI product is having problems working on the Macintosh IIfx. What are the differences between the IIfx SCSI and SCSI on all the other SCSI-equipped Macintosh systems?

The SCSI chip on the IIfx is different from any of Apple's previous machines. The new SCSI chip is an Apple ASIC which adds functionality to the 5380. The pinouts are identical, the cables are identical, but the terminator is different.

Every IIfx is shipped with the new terminator, so unless you have internal termination on your external SCSI device, there is no known reason for your product not working. The new terminator is black in color (instead of gray or platinum) and completely replaces the old terminator.

If your SCSI device is directly accessing the SCSI low-memory globals, then this is likely to cause your incompatibility problems, since the globals have changed in the IIfx and could

change again in the future.

As stated in the Technical Note “SCSI Termination.” if you can give DTS detailed information on your compatibility problems with the IIx and your SCSI device, we should be able to provide you with more information about the possible causes.

Macintosh IIci SCSI power connector changes

Written: 1/1/91

Last reviewed: 1/1/91

What changes are there to the Macintosh IIci SCSI power connector?

—

The IIci SCSI power connector is supplied by Molex. It is plug housing part number 39-01-2040 with four crimp pins (part number 39-00-0039) per housing needed. You can contact Molex sales representatives Dave Rios in San Jose, CA (408-946-4700) or Randy Kempf in Lisle, IL (312-969-4550) for these parts.

Figure as seen looking down at the IIci logic board:

