

*---A macro to print only every other specified number of columns. The macro prompts the user for the number of columns to skip. Example:
To print only every 4th column, answer 3 to the "How many columns to skip ? " prompt.

*---Use the /Range Name Label Right {End} {Down} <ENTER> to define the range names in this column (starts with the \Z macro name).

*---Hold the <ALT> key and press <Z> to activate the macro
THIS MACRO AUTOMATICALLY DETECTS THE LOTUS 1-2-3 RELEASE
IT WILL WORK IN LOTUS 2/2.01/2.2/2.3/3/3.1/3.1+/123W

```

\Z                {BREAKON}
PRINTALT          {let rel206,@INFO("release")}~{recalc loc206} {recalc form206}
form206           {let here1206,@cellpointer("&quot;coord&quot;);}~
!                {WINDOWSOFF} {PANELOFF}/RNCRANGE TO PRINT?~/RNDR
!                {panelon} {getlabel "How many columns to skip ? ",skip206}~
!                {LET TEMP1206,@STRING(@MOD(@COLS(RANGE TO PRINT?))
!                {getnumber "No. of copies ? ",copies206}~{paneloff} {recalc colshide2
!                {FOR COUNTER1206,1,(@COLS(RANGE TO PRINT?)-@MOD(@C
!                {FOR COUNTER2206,1,COPIES206,1,PRINTS206} {ESC 10}
!                /WCDRANGE TO PRINT?~{GOTO} {HERE1206}~/RNDRANGE TO
!
colshide206       {RIGHT}/wch.{RIGHT 2}~{ESC 10}{RETURN}
!
prints206         {ONERROR ERR206} {IF @MOD(@COLS(RANGE TO PRINT?),@
!                {IF @MOD(@COLS(RANGE TO PRINT?),@VALUE(SKIP206)+1)=
!
temp1206          0
skip206           3
counter1206       6
counter2206       2
copies206         1
here1206          $B:$A$1
key206            ~
err206           {if @LEFT(REL206,1)<>"@"} {beep} Turn on your printer and/or press
!                {if @LEFT(REL206,1)="@"} {beep} Turn on your printer and/or press
!
rel206           3.00.00
!
loc206           coord

```

RANGE TO PRINT?~/RNC{PANELON}{WINDOWSON}RANGE TO PRINT?~{BS}{BS}

,(@VALUE(SKIP206)+1),0)}~

06}{recalc prints206}

COLS(RANGE TO PRINT?),(@VALUE(SKIP206)+1))/(@VALUE(SKIP206)+1)+1,1,COL

) PRINT?~{esc 10}{CALC}

VALUE(SKIP206)+1)>0}/PPCRRRANGE TO PRINT?~R{LEFT 1}{RIGHT}~AGPQ{esc 1

=0}/PPCRRRANGE TO PRINT?~R{LEFT}{RIGHT}~AGPQ{esc 10}{RETURN}

s any key to continue...{get key206}{ESC}/PRQ/wcda1..iv1~

any key to continue...{get key206}{ESC}/wcda1..iv1~

{?}~{WINDOWSOFF}{PANELOFF}

.SHIDE206}{ESC 10}

10}{RETURN}