

Supported Systems Software: 7.5.3

SCSI: DB-25

Serial Ports: 2

Sound Output: 16-bit stereo 44.1 KHz sample rate

ADB: 1, plus additional port for PS/2 keyboard

Ethernet: Add-in card

Machine Gestalt ID: ???

Minutiae:

Improve performance by installing a Newer Technology level-2 cache DIMM, part # 7CC512C.

StarMax can take only 3.3 volt EDO DIMMs. It does not support interleaved memory. The three DIMM sockets are NOT identical. The first socket can only accept up to 32 MB DIMMs. The other two sockets can accept up to 64 MB DIMMs. The maximum memory is therefore 160 MB.

Manufactured by:

Motorola Computer Group

1-800-759-1107

<http://www.mot.com/computer/starmax>