

Speccylator

COLLABORATORS

	<i>TITLE :</i> Speccylator	
<i>ACTION</i>	<i>NAME</i>	<i>DATE</i>
WRITTEN BY		June 25, 2022
<i>SIGNATURE</i>		

REVISION HISTORY

NUMBER	DATE	DESCRIPTION	NAME

Contents

1	Speccylator	1
1.1	Speccylator.guide	1
1.2	Speccylator.guide/Distribution	2
1.3	Speccylator.guide/Introduction	2
1.4	Speccylator.guide/Usage from Workbench	3
1.5	Speccylator.guide/Tool Types	3
1.6	Speccylator.guide/Default program settings	6
1.7	Speccylator.guide/Project settings	6
1.8	Speccylator.guide/Usage from CLI	6
1.9	Speccylator.guide/Program operation	7
1.10	Speccylator.guide/The Project menu	8
1.11	Speccylator.guide/The Settings menu	9
1.12	Speccylator.guide/The Emulation menu	10
1.13	Speccylator.guide/The Processor menu	11
1.14	Speccylator.guide/Keyboard layout	11
1.15	Speccylator.guide/Snapshot files	12

Chapter 1

Speccylator

1.1 Speccylator.guide

Speccylator Documentation

The Speccylator program emulates a Sinclair ZX Spectrum computer. It is available for Motorola MC680x0-based Amiga computers only and is copyrighted (C) 1993-1997 Richard Carlsson.

Distribution

What you are allowed to do with these files.

Introduction

What the program does (and does not).

Usage from Workbench

Running from the Amiga graphical user interface.

Usage from CLI

Running from the Command Line Interface (shell).

Program operation

Menus, keys, features, etc.

Appendices:

Keyboard layout

Amiga - ZX Spectrum keyboard correspondencies.

Snapshot files

The format of the project files.

1.2 Speccylator.guide/Distribution

Distribution

=====

The Speccylator program itself may be distributed freely under the conditions that no fee is charged above the costs of distribution and media, and that the program is not modified in any way.

The file Spectrum.ROM contains an image of the 16 kByte Sinclair ZX Spectrum ROM and it is copyright (C) Amstrad. Cliff Lawson of Amstrad (CompuServe 75300,1517) has given special permission for emulator authors to use the Spectrum's ROM code. (1)

This documentation (the original Texinfo file, or any representation generated from it) may be reproduced and distributed in any form or processed in any way, provided no literal content, and in particular the above copyright notices and this notice of permission, is lost in the resulting product.

The sample snapshot file demo.sna, and other files included in the original distribution of the Speccylator program which are not covered by the above, have no restrictions whatsoever on distribution or use.

----- Footnotes -----

(1) This paragraph is basically a quote from the documentation of Spectrum Emulator 1.7 by Peter McGavin.

1.3 Speccylator.guide/Introduction

Introduction

=====

The Speccylator is a program that emulates the Sinclair ZX Spectrum computer. It is written for Amiga computers as an application of a generic Z80 emulator core for the Motorola M68000 family of processors. It is fast, completely multitasking and totally system-friendly. It requires at least release 2.0 of the Amiga operating system, and about 435 kByte of available RAM. It requires no particular hardware beyond that of a standard Amiga 500.

At startup, the program attempts to load a file containing an image of the 16 kByte Sinclair ZX Spectrum ROM. (By default, this file is called Spectrum.ROM. See

Tool Types

, the ROMFILE Tool Type.) The file

included in the Speccylator distribution is copyright (C) Amstrad. See

Distribution
, for details.

The current version (1.0) of the program emulates only the 48k model of the ZX Spectrum. It reads and writes so-called "snapshot" project files on the common .sna format (see Snapshot files).

The emulator uses a custom screen for the ZX Spectrum display; nothing else would be practical. The allocated custom screen has a depth of 4 bitplanes and uses Lo-res resolution without interlacing.

The program can allocate up to two audio channels, if available, for its sound generation; at most one left channel and one right channel. Both channels will receive the same output data.

1.4 Speccylator.guide/Usage from Workbench

Usage from Workbench

=====

The Speccylator program can be run from the Amiga Workbench, and may be passed a single snapshot file as argument. (See the 'Amiga User's Manual' for details about passing arguments from the Workbench and setting Tool Type values.) Simplest, this is done by double-clicking on the program's icon, or by similarly activating a project icon that has the Speccylator program as its default tool.

Tool Types

The available options.

Default program settings

Where and how are default settings stored?

Project settings

Settings for individual snapshots.

1.5 Speccylator.guide/Tool Types

Tool Types

The following Tool Types affect the behaviour of the program. (Where

they exist, abbreviations are given in addition to the standard name. However, these can only be used when running the program from the Command Line Interface. See

Usage from CLI

.) Booleans can be specified

as TRUE, YES or ON, and FALSE, NO or OFF respectively; these keywords are not case-dependent. If no valid right-hand value is found for a Tool Type, its original setting is unchanged.

AUDIOCHANS

AC

(String.) BOTH, RIGHT, LEFT, ANY, NONE, or any disjunction of these; e.g., RIGHT|LEFT equals BOTH. BOTH overrides LEFT and RIGHT. BOTH, LEFT and RIGHT override ANY. All of them override NONE. (Default BOTH.)

DEBUG

(Boolean.) Only available if the program was compiled with the compilation option DEBUG (not in the standard distribution), this flag makes the program run in debugging mode, which causes the user interface to be handled by a separately launched process, while the Z80 emulation is done by the original process. (Default FALSE.)

DIRECTORY

DIR

(String.) Specifies the directory in which to look for snapshot files. If not given, the current directory is used.

EMULPRI

PRI

(Integer.) The priority (-128-127) of the task running the Z80 emulation. If not specified, the spawned task runs at the same priority as the original process. (The priority of the latter can be specified from Workbench using the standard TOOLPRI Tool Type, or from CLI with the ChangeTaskPri command.) The recommended value is -1 or lower.

GAMEPORTUNIT

GU

(Integer.) Amiga game port unit number for joystick use; see the JOYSTICK Tool Type. (The default value is 1.)

INTPERIOD

IP

(Integer.) The period (a nonnegative number), in number of vertical blankings (50/s for PAL, 60/s for NTSC), of the maskable interrupt (an INT signal). A zero value turns the periodic interrupt triggering off; even then, single maskable interrupts can still be triggered manually. (The default value is 1.)

JOYSTICK

JOY

(Boolean.) If TRUE, the Amiga game port selected by the GAMEPORTUNIT Tool Type is activated, if it is available. (The default unit is 1, the normal port for joysticks; the system generally uses unit 0 for the mouse.) This only has effect on the

emulation if a ZX Spectrum joystick interface (such as KEMPSTON) is also selected. (Default FALSE.)

KEMPSTON

KI

(Boolean.) If TRUE, a Kempston joystick interface attached to the extension port of the ZX Spectrum is emulated. If a game port on the Amiga is activated by the JOYSTICK Tool Type, a joystick connected to that port will appear to be connected to the emulated interface. (Default FALSE.)

ROMFILE

ROM

(String.) The name (relative to the current directory) of the file containing the 16 kByte ROM image to be read into the the ZX Spectrum memory at address 0 before emulation starts. If not specified, a file Spectrum.ROM is searched for, first in the current directory and then in the directory containing the program.

SAVEICONS

SI

(Boolean.) If TRUE, the current settings are automatically saved as the project's default settings when snapshots are saved, and icons are automatically created where none previously exist. See

Project settings
. (Default TRUE.)

SCREENPERIOD

SP

(Integer.) The period (a nonnegative number), in number of vertical blankings (50/s for PAL, 60/s for NTSC), of the Spectrum screen refresh. A zero value turns the periodic screen updating off. (The default value is 1.)

TITLEBAR

TB

(Boolean.) If TRUE, the title bar of the custom screen will be visible. (Default TRUE.)

VERIFYACTIONS

VA

(Boolean.) If TRUE, selecting any potentially harmful user action, like quitting the program, will first ask for verification before being executed. (Default TRUE.)

VERIFYSIGNALS

VS

(Boolean.) If TRUE, commands to trigger processor signals like RES will first ask the user for verification before being executed. (Default TRUE.)

1.6 Speccylator.guide/Default program settings

Default program settings

Default program settings are saved as Tool Types in the Speccylator program icon (the .info file associated with the program). If no such file exists when defaults are saved, a new .info file will be created, using the built-in image for the program. If the file already existed, only its Tool Types are affected, and of these only the ones pertaining to the Speccylator program (see

Tool Types
) are modified.

1.7 Speccylator.guide/Project settings

Project settings

Settings particular to individual projects override any default settings or settings specified on the command line. They are stored as Tool Types in the project icon (the .info file associated with the project file). If no such file exists when project settings are saved, a new .info file will be created analogously to the case of saving default settings. See

Default program settings
. If the Create Icons

menu option (see

The Settings menu

) is turned on, project settings are automatically saved when saving a snapshot.

1.8 Speccylator.guide/Usage from CLI

Usage from the Command Line Interface

=====

The program has the following CLI template:

```
SNAPSHOT, AC=AUDIOCHANS/K, DEBUG/S, NODEBUG/S, DIR=DIRECTORY/K,
PRI=EMULPRI/N, GU=GAMEPORTUNIT/N, IP=INTPERIOD/N, JOY=JOYSTICK/S,
NJOY=NOJOYSTICK/S, KI=KEMPSTON/S, NKI=NOKEMPSTON/S, ROM=ROMFILE/K,
SI=SAVEICONS/S, NSI=NOSAVEICONS/S, SP=SCREENPERIOD/N, TB=TITLEBAR/S,
NTB=NOTITLEBAR/S, VA=VERIFYACTIONS/S, NVA=NOVERIFYACTIONS/S,
VS=VERIFYSIGNALS/S, NVS=NOVERIFYSIGNALS/S
```

Most options have abbreviations, and every boolean option has a corresponding negated form, whose name is NO (or N for the

abbreviations) appended with the name of the positive form. The negated and abbreviated forms can only be used when running from the CLI. See

```
Tool Types
, for descriptions of the effects of these options.
```

Options specified on the command line override any default settings. For instance, entering:

```
Speccylator JetPac.sna PRI -1 AC ANY JOYSTICK NTB KEMPSTON
```

the Speccylator would attempt to load a snapshot (project) file named JetPac.sna, and execute with Z80 emulation task priority -1, allocating a single audio channel, the joystick enabled (in the default joystick port), the titlebar hidden, and Kempston interface emulated. (This is unless the CLI options are overridden by project settings. See

```
Project settings
.)
```

1.9 Speccylator.guide/Program operation

```
Program operation
```

```
=====
```

The program is controlled via menus or corresponding short-cut keys (where such exist, they are shown in the menus). Keypresses which are not intercepted by the system or the graphical user interface are interpreted by the ZX Spectrum keyboard emulation (see

```
Keyboard layout
).
```

```
The Project menu
```

```
The Settings menu
```

```
The Emulation menu
```

```
The Processor menu
```

```
The menus
```

```
-----
```

```
The Project menu
```

```
Open Snapshot...
```

```
Save Snapshot...
```

```
Reload Project
```

```
Save Screen...
```

```
Save Settings
```

Reload Settings

Save Defaults
Reload Defaults

Quit

The Settings menu

Title Bar

Create Icons
Verifications
Audio
Screen Updating
Task Priority

The Emulation menu

Pause

Joystick
INT Frequency
Interfaces

The Processor menu

Halt

Verifications
INT
NMI
RES

1.10 Speccylator.guide/The Project menu

The Project menu

.....

Open Snapshot...

Opens a file requester for selecting a project snapshot file to be loaded. If the DIRECTORY Tool Type (see

Tool Types
) has been

specified, the requester will show that directory (if it exists); otherwise, the program's current directory is shown.

Save Snapshot...

Like Open Snapshot..., but a Save requester is opened instead. The Z80 emulation is automatically halted during the whole of the operation. If the Create Icons menu option is turned on (see

The Settings menu

), the current settings are automatically saved in the project icon file. See

Project settings

Reload Project

Reloads the current project, without reloading settings.

Save Screen...

Opens a Save requester for writing the current contents of the screen to a file, in IFF ILBM format. The Z80 emulation is automatically halted during the whole of the operation. No icon is created for the image file.

Save Settings

Saves the current settings as the project's default settings. See

Project settings

Reload Settings

Loads settings from the project's icon file (if it exists).

Save Defaults

Saves the current settings as the defaults. See

Default program settings

Reload Defaults

Loads settings from the program's icon file (if it exists).

Quit

Terminates the Speccyclator program.

1.11 Speccyclator.guide/The Settings menu

The Settings menu

.....

Title Bar

If turned on, the title bar of the custom screen is visible. See

Tool Types
, the TITLEBAR Tool Type.

Create Icons

If turned on, the current settings are automatically saved as the project's default settings when a snapshot is saved, and new project icons are created where none already exist. See

Project settings
. Also
Tool Types
, the SAVEICONS Tool Type.

Verifications

If turned on, the program asks for verification before executing any potentially harmful user action. See

Tool Types

, the

VERIFYACTIONS Tool Type.

Audio

Selects the audio channels to be used (if available): Both, Right, Left, Any (a single channel) or No Audio. The No Audio submenu item can be toggled, in which case the setting prior to the first selection is restored. See

Tool Types

, the AUDIOCHANS Tool Type.

Screen Updating

Sets the refresh frequency of the ZX Spectrum screen, in percent of the vertical blanking frequency (50 Hz for PAL, 60 Hz for NTSC), or turns it off completely. The Off submenu item can be toggled, in which case the setting prior to the first selection is restored. Values other than those in the submenu can be set using the SCREENPERIOD Tool Type. See

Tool Types

.

Task Priority

Sets the priority of the task running the Z80 emulation. Values other than those in the submenu can be set using the EMULPRI Tool Type. See

Tool Types

.

1.12 Speccylator.guide/The Emulation menu

The Emulation menu

.....

Pause

When selected, all emulation (processor, interrupts, screen updating, etc.) is halted. When deselected, everything is turned on again. All functions are affected, even if some have been individually enabled or disabled.

Joystick

If turned on, the Amiga game port selected by the GAMEPORTUNIT Tool Type is activated, if it is available. (Default unit is 1, the normal joystick port.) See

Tool Types

, the JOYSTICK Tool Type.

INT Frequency

Sets the frequency of the periodic maskable interrupt signal, in percent of the vertical blanking frequency (50 Hz for PAL, 60 Hz

for NTSC), or turns it off completely. The Off submenu item can be toggled, in which case the setting prior to the first selection is restored. Values other than those in the submenu can be set using the INTPERIOD Tool Type. See

Tool Types

.

Interfaces

Kempston

If turned on, a Kempston joystick interface attached to the extension port of the ZX Spectrum is emulated. If a game port on the Amiga is activated (see the Joystick menu option above), a joystick connected to that port will appear to be connected to the emulated interface. See

Tool Types

, the

KEMPSTON Tool Type.

1.13 Speccylator.guide/The Processor menu

The Processor menu

.....

Halt

If turned on, the Z80 emulation is halted (but other functions of the emulation remain unaffected).

Verifications

If turned on, the program asks for verification before executing any command to trigger a processor signal, like RES.

INT

Triggers the Z80's INT (maskable interrupt) signal.

NMI

Triggers the Z80's NMI (nonmaskable interrupt) signal.

RES

Triggers the Z80's RES (reset) signal.

1.14 Speccylator.guide/Keyboard layout

Keyboard layout

The basic correspondence between the Amiga keyboard and that of the ZX Spectrum is simple: the alphanumerical Amiga keys (A-Z and 0-9) map directly to the same keys on the ZX Spectrum keyboard, and the Space bar to the Spectrum's Space key.

Both Shift keys map to the Spectrum's Caps Shift key, and both Alt keys to the Symbol Shift key. When the Amiga Caps Lock is activated, the effect is that of keeping the Spectrum's Caps Shift key pressed down; when Caps Lock is turned off again, it corresponds to releasing Caps Shift.

The Numeric pad works similarly; Enter maps to the Spectrum's Enter key, and the keys 0-9 map to the corresponding Spectrum keys.

The Help key, the function keys (F1-F10), the Ctrl key and the two Amiga keys have no effect on the ZX Spectrum keyboard emulation.

All remaining keys are mapped to sequences of keypresses on the ZX Spectrum keyboard, rather than to particular keys or symbols. Some of them can be modified by holding down a Shift key, but not all. The keys are interpreted according to the standard American keyboard (since it seems likely that most people are more or less familiar with that layout), and produce keypress sequences that yield the corresponding symbol or effect if initiated in the normal editing mode of the ZX Spectrum BASIC line editor.

In particular, the following keys are of interest:

- * Esc: Go into E-mode.
- * Back Space and Del: Delete (Caps Shift + 0).
- * Left Arrow, Down Arrow, Up Arrow and Right Arrow: Cursor keys (Caps Shift + 5, 6, 7 and 8, respectively).

1.15 Speccylator.guide/Snapshot files

Snapshot files

A snapshot file is a complete machine state dump of a 48 kByte Sinclair ZX Spectrum - the RAM memory contents and the processor state. The format is also called the Mirage Microdrive format, after the piece of hardware from which it originates.

Snapshot file names are usually suffixed with .sna or .snapshot. A publicly available program named spconv, written by Henk de Groot, can be used to convert such files to and from other snapshot formats, such as the common .Z80 format.

The snapshot format

A snapshot reflects the state of the machine after the occurrence of a non-maskable interrupt. Thus, the 2 bytes on top of the stack (the address pointed to by the saved stack pointer, and the next higher address) form the address to which the program counter was pointing when the interrupt occurred - this is always the address of the

instruction which was to be executed next. The lower stack address contains the least significant byte (bits 0-7) of the program counter, and the higher address the most significant byte (bits 8-15); this is how 16-bit words are always handled in the Z80.

The first 27 bytes of the snapshot file hold the saved processor and hardware state, at the following offsets (16-bit registers stored with the least significant byte first; for e.g. the register pair HL, this is the 8-bit register L):

Offset	Name	Comment
0:	I	(8-bit register)
1:	H'L'	(16-bit register pair)
3:	D'E'	(16-bit register pair)
5:	B'C'	(16-bit register pair)
7:	A'F'	(16-bit register pair)
9:	HL	(16-bit register pair)
11:	DE	(16-bit register pair)
13:	BC	(16-bit register pair)
15:	IY	(16-bit register)
17:	IX	(16-bit register)
19:	---	(8 bits): Bit 2 set if maskable interrupts are enabled.
20:	R	(8-bit register)
21:	AF	(16-bit register)
23:	SP	(16-bit register): The stack pointer
25:	---	(8 bits): Interrupt mode: 0, 1 or 2.
26:	---	(8 bits): Border colour (0-7) in bits 0-2.

Directly after this (at offset 27 from the start of the file) follow the contents of the 48 kByte RAM (located at addresses 16384-65535) of the machine at the time the nonmaskable interrupt occurred.