

Installation Notes:

- 1.** If you are installing this package on top of a currently installed SafetyNet, you must remove the old version first. If not, strange things may happen with on-line help as well as other areas of the application.
- 2.** NEXTSTEP/FIP version 3.1 contains a bug in the SCSI Tape driver that does not allow access to the tape drive when a tape is not online and ready. Therefore, with NS 3.1, SafetyNet will fail on any access to the drive if a tape is not already present.
- 3.** WangDAT tape drives ship configured not to physically eject the tape in response to a SCSI UNLOAD command. The drive does, however, go off-line and become inaccessible until put on-line either as a result of a SCSI LOAD command, or by manually ejecting and reinserting the tape cartridge. Normally, SafetyNet will place the drive on-line before attempting any operations. However, since the bug described in (2) above precludes access to a drive that is not loaded and ready, WangDAT drives under 3.1 may be

totally inaccessible if an attempt is made to eject the tape under program control. This "wedged" condition is recoverable if the tape is manually ejected and reinserted. Alternatively, the WangDAT tape drive can be configured to physically eject the tape in response to a SCSI UNLOAD by setting the drive configuration switch number four to on. The SCSI Tape driver bug has been fixed in NS 3.2.