

LaserWriter Driver Errors

-8132 ???? Manual Feed time out
-8133 ???? General PostScript Error
-8150 ???? No LaserWriter chosen
-8151 ???? Version mismatch between LaserPrep dictionaries
-8150 ???? No LaserPrep dictionary installed
-8160 ???? Zoom scale factor out of range

PictInfo Errors

-11000 pictInfoVersionErr Version number not zero
-11001 pictInfoIDErr Invalid PictInfo ID
-11002 pictInfoVerbErr Invalid verb combination specified
-11003 cantLoadPickMethodErr Custom pick method not in resource chain
-11004 colorsRequestedErr Number out of range or greater than passed to NewPictInfo
-11005 pictureDataErr Invalid picture data

Power Manager Errors

-13000 pmBusyErr Power Manager IC stuck busy
-13001 pmReplyTOErr Timed out waiting to begin reply handshake
-13002 pmSendStartErr Power Manager IC did not start handshake
-13003 pmSendEndErr During send, Power Manager did not finish handshake
-13004 pmRecvStartErr During receive, Power Manager did not start handshake
-13005 pmRecvEndErr During receive, Power Manager did not finish handshake

Mac TCP Errors

-23000 ipBadLapErr Bad network configuration
-23001 ipBadCnfgErr Bad IP configuration error
-23002 ipNoCnfgErr Missing IP or LAP configuration error
-23003 ipLoadErr Error in MacTCP load
-23004 ipBadAddr Error in getting address
-23005 connectionClosing Connection in closing
-23006 invalidLength
-23007 connectionExists Request conflicts with existing connection
-23008 connectionDoesntExist Connection does not exist
-23009 insufficientResources Insufficient resources to perform request
-23010 invalidStreamPtr
-23011 streamAlreadyOpen
-23012 connectionTerminated
-23013 invalidBufPtr
-23014 invalidRDS
-23014 invalidWDS
-23015 openFailed
-23016 commandTimeout
-23017 duplicateSocket
-23030 ipOpenProtErr Can't open new protocol, table full
-23031 ipCloseProtErr Can't find protocol to close
-23032 ipDontFragErr Packet too large to send w/o fragmenting
-23033 ipDestDeadErr Destination not responding
-23034 ipBadWDS Error in WDS format
-23035 icmpEchoTimeoutErr ICMP echo timed-out
-23036 ipNoFragMemErr No memory to send fragmented pkt
-23037 ipRouteErr Can't route packet off-net
-23041 nameSyntaxErr
-23042 cacheFault
-23043 noResultProc
-23044 noNameServer
-23045 authNameErr
-23046 noAnsErr

-23047 dnrErr
-23048 outOfMemory

[Primary or Secondary Init Code Errors](#)

-32768 svTempDisable *Temporarily disable card but run primary init*
-32640 svDisabled *Reserve -32640 to -32768 for Apple temp disables*