

USING THE WINDOW MENU

"Close session": Closes a session with a host.

"Re-open session": Allows you to attempt to re-open a session which has failed to open or has been closed. If a connection is made, the session's Connection Macro will be executed.

"Reconfigure session...": Lets you use the "Configure Session" dialog to reconfigure a session after you have created or opened it.

"Scrollbar buffer": Lets you turn scrollbar buffering in the emulator window on and off.

"Toggle .edit Window": Bring the .edit window associated with the topmost emulator session to the front.

"Miniaturize": Shrinks the front window down to an icon. The icon will be inverted if data arrives while the session is iconified. The position of the icon on the screen is saved automatically when the window is closed.

A list of session/window names follows; the first 9 are associated with the Command keys 1-9. Selecting the item brings the window to the front.

Items in the list of sessions may have marks to indicate special conditions. Active Telnet sessions have a bullet; Telnet sessions which have terminated abnormally are marked with a cross. A Serial session which has the Modem Port open is marked with a '+', while a Serial session using the Printer Port is marked with a '-'.