Display modes and control characters-serial mode

Display mode Set at Set after (see Note) Complementary display mode Set at Set after (see Note) Alphanumerics Row start 4/1 4/2 4/3 4/4 4/5 4/6 4/7 Block mosaics _ 5/1 5/2 5/3 5/4 5/5 5/6 5/7 Contiguous Row start 5/9 5/9 Separated 5/10 5/10 Foreground display colour includes red

Row start

4/1 4/3 4/5 4/7 5/1 5/3 5/5 5/7

Foreground display colour includes red

_

4/2	4/4	4/6
5/2	5/4	5/6

includes green

Row start

4/1	4/2	4/3	4/7
5/1	5/2	5/3	5/7

excludes green

-4/1 4/4 4/5 5/1 5/4 5/5

includes blue

Row start

4/4 4/5 4/6 4/7 5/4 5/5 5/6 5/7

excludes blue _

4/1 4/2 4/3 5/1 5/2 5/3

Black background

Row start 5/12

New background colour 5/13

—

Stop conceal

Row start

 $\begin{array}{ccc} 4/1 & 4/2 & 4/3 \\ 4/4 & 4/5 & 4/6 & 4/7 \\ 5/1 & 5/2 & 5/3 \\ 5/4 & 5/5 & 5/6 & 5/7 \end{array}$

Conceal

5/8

—

Steady Row start 4/9

– Flash

-4/8

Unboxed Row start 4/10 4/10 Boxed 4/11 4/11

Normal height Row start 4/12

– Double height

> -4/13

Release Row start 5/15 Hold 5/14 *Note* – All attribute control characters are preceded by Escape ESC.

—