

Sourcecode: ReadArgs.c

COLLABORATORS

	<i>TITLE :</i> Sourcecode: ReadArgs.c		
<i>ACTION</i>	<i>NAME</i>	<i>DATE</i>	<i>SIGNATURE</i>
WRITTEN BY		February 12, 2023	

REVISION HISTORY

NUMBER	DATE	DESCRIPTION	NAME

Contents

1	Sourcecode: ReadArgs.c	1
1.1	ReadArgs.c	1

Chapter 1

Sourcecode: ReadArgs.c

1.1 ReadArgs.c

```
/* ReadArgs.c   V1.0   93-03-09                */
/* ROM library: "dos.library/ReadArgs", (V36+) */
/* Copyright 1993, Anders Bjerin, Amiga C Club */

#include <dos/dos.h>
#include <dos/rdargs.h>

#include <clib/dos_protos.h>
#include <stdio.h>
#include <stdlib.h>

#define MY_COMMAND_LINE_TEMPLATE "SoundFile/A"
#define NUMBER_COMMAND_TEMPLATES 1
#define SOUNDFILE_TEMPLATE      0

UBYTE *version = "$VER: ReadArgs V1.0";

struct RDArgs *my_rdargs;
LONG arg_array[ NUMBER_COMMAND_TEMPLATES ];

int main( int argc, char *argv[] );
int main( int argc, char *argv[] )
{
    /* Parse the command line: */
    my_rdargs = ReadArgs( MY_COMMAND_LINE_TEMPLATE, arg_array, NULL );

    /* OK? */
    if( !my_rdargs )
    {
        printf( "Could not parse the command line!\n" );
        exit( 20 );
    }

    if( arg_array[ SOUNDFILE_TEMPLATE ] )
        printf( "File name: %s\n", arg_array[ SOUNDFILE_TEMPLATE ] );

    /* Free the "argument data": */
}
```

```
FreeArgs ( my_rdargs );  
exit ( 0 );  
}
```
