

Setting Up the Port Trigger List

About the Port Trigger List

Provided is an example of what the Port Trigger List looks like and how to set it up. After you have selected the Port Juggler icon, you will see the "Which port is the Port Juggler connected to?" splash screen. Once you have chosen a port and selected OK you will see a blank Port trigger List on the right side of the Chooser. Select a Port Juggler port from the "Port" menu and then assign your device to it, from the "Devices" menu. Once, you have assigned all your devices you will need to shutdown your Mac and configure your hardware to match the Port Trigger List you just created.

enus

There are two popup menus located on the bottom of the right side of the Chooser. The first menu is the "Port" menu. This port tells the Port Juggler which ports your devices are connected to. You have a choice of "1, 2, 3 or 4".

Port Menu

ports
the
ports when

The phone icons represent the Port Juggler's
when it is configured for the modem port and
printer ports represent the Port Juggler's
it is configured for the printer port.

Devices Menu

menu. This is
program that
When you
get a general
category
device.
categories
"Other..." option.

The second menu is the "Devices"
where you select your actual device or
is attached to your Port Juggler's ports.
first select the "Devices" menu you will
list of categories. Selecting the specific
will allow you to choose your specific
Devices or programs that are not in the
can be manually selected from the

Other...

our
"

For devices or programs that are not in
Devices" menu, selecting "Other..." will

prompt a
window will
drive and
The three
are for
MIDI
in the

are
folders. Below
will appear

dialog window to appear. This dialog
allow you to navigate through your hard
select specific devices or programs.
common uses for the "Other..." option
printers, communication programs and
programs. The printers can be found
Extensions folder of your System folder.
The communication and MIDI programs
usually located in their respective
is an example of the dialog window that
when the "Other..." option is selected.

Editing the Port Trigger List (Remove)

Trigger List

If you need to edit or change your Port

the "Remove" order to remove will need to removed, then go to "Remove" option.

settings, this can be done by selecting option from the "Devices" menu. In an item from the Port Trigger List you first highlight the item you want the "Devices" menu and select the This will remove the item selected.

Localtalk & Networking

you connect Localtalk network.

this Mac is a your Mac on a

Select utilities to configure

Localtalk Games: Select these games if you are playing over a Localtalk network.

Appleshare: Select Appleshare if to another Mac as a client on a

File Sharing: Select File Sharing if server (other Macs connect to Localtalk network).

LaserWriter and LaserJet Utilites: either option if you use these your Localtalk printers.

