

Equipment	DMS-100 Settings **									
	B1	B2	EKTS	Ring Indic.	SPID Suffix	Max Keys	Release Key	*Issue		
								30	31	
NTI M5000TD-1 with Release 2.X								0	0	
Hayes System Adapter	CSV	CSD	Y?	Yes		64		0	0	
Hayes PCTA	CSV	CSD	Y?	Yes		64		0	0	
Combinet	CSD	CSD	No	No	B1 = 01 B2 = 02	3	No	0	1	
Digiboard CSD Products			No	No		3	No	0	1	
Digiboard for B=CSV/D without Centrex Voice Features			No	No		3	No	0	1	
Extension Technology Corp. LD-LAN Adapter	CSD	CSD	Yes	No		10	No			
Network Express	CSD	CSD	No	No		3	No	0	1	
Teleos PCTA	CSV or CSD	CSD	B1=Yes B2=Yes			64				
Fujitsu 1050/2000	CSV	CSV or CSD	B1=Yes B2=Yes	Yes		64				
			(Multipoint or Point to Point)							
Fujitsu SRS 410	CSD	None	Yes	Yes		64				
AT&T 7506/7507										
UDS TA 120	CSV	CSD	Y?	Yes		64				
Gandalf TA-1	CSD	CSD	No	Yes		64				
IBM TA & NTI Voice set	CSV	CSD	B1=Yes B2=No	Yes		64				
Ascend Multiband	CSD	CSD	No	Yes		64				

Cameo application	CSV	CSD	Yes	Yes	64
Northern Telecom M5317/M5209	CSV	CSD	Yes	Yes	64
Ricoh Group IV Fax	CSV	CSD	B1 = N B2 = ?	Yes	64

*** Current BCS in the SRVAC DMS-100 is 34 as of 8/93**

**** All DMS-100 settings are Dynamic TEI and Functional Signaling**

Disclaimer: These lab notes are collected from a variety of sources and are not intended to be used as a reference for configuring lines. All vendor names are the trademarks or registered trademarks of their respective owners, although some names may be shown in shorthand on this list.

				5ESS Settings			Special Notes
(per BCS #)				B1	B2	Terminal Type	
32	33	34	35				
0	0	0	2				
0	0	0	0	CSV/CSD	CSD	A	
0	0	0	0	CSV/CSD	CSD	A	
1		2		CSD	CSD	C, D, OR E	
1	1	1	2			A, B, C, D or E	
1	1	1	2			Any but E	
				CSD	CSD	C or D	
1	1	1	2	CSD	CSD	E	
		1		CSV/CSD	CSD	D	
		1		CSV/CSD	CSD	D	
		1		CSV/CSD	CSD	A	
				CSV/CSD	CSD	D	
		1		CSV/CSD	CSD	A	
		1		CSV/CSD	CSD	D	
		1					
		1		CSD	CSD	A or D	

1 if Apple 2 if Planet	CSV	CSD	D	
1				If EKTS on B1 is set to No then SPM won't work.
1	CSV/CSD	CSD	A	

ng unless notes show otherwise

**rces and are incomplete and unverified. They may be
 id as a substitute for the vendors' documentation when
 stered trademarks of their respective holders,
 This is not a complete list of available ISDN equipment.**