

## What's new in TTRLabel 3.5

- \* Windows 95-style help;
- \* More accurate preview scaling system;
- \* You can choose which label you want to print (by a From-To selection);
- \* Automatic uninstalling feature: now you can delete all the system registry entries made by TTRLabel using the Windows 95 install/uninstall application system;
- \* This version is shareware. Please see the user's license

## Hardware/software requirements

TLabel is a 32 bit Windows program, and it needs Windows 95 or Windows NT 3.51 to run.

Hardware requirements are the same of the operating system ones, plus a printer.

TLabel will NOT work under Windows 3.x, even if you have installed the win32s library, or under Windows NT 3.5.

If executed under Windows NT 3.51, TLabel requires the 32 bit 3D control library, contained in the file `ctl3d32.dll`, which should be placed in the `%systemroot%\system32` directory.

## Label type

TLabel can use both single sheet and continuous paper types. See [Setup](#) for the configuration procedure. Single sheet type has the advantage that you can use all the labels, even if printed in different times. Instead, it is often impossible to reach the first label in continuous paper, so if you print only few labels per session, you will lose a significant amount of them.

TLabel can setup all the physical parameters of the paper (height, width, margins, ...), so you can use all the formats supported by your printer.

## Entering labels

The text has to be inserted in the upper left corner window. While you are entering the characters, they will appear in the upper right corner white rectangle (the preview) in the font and color choosed using the Font button. The selection is always possible, but does not affect the previously inserted labels and the lines with explicitly selected font (see below).

Font and color are stored in the system registry, under the current setup. The first time the program is executed the font is Courier New 10 points, black. If this font is not installed, you have to choose another one before entering the first label.

If you type in a label without pressing the Ok button it will not be added to the database and not be printed.

To select a font for a single line, place the mouse pointer over the choosen line and press the right mouse button, then choose "Font" from the menu. Or you can place the caret (the vertical blinking line) and press Alt-f.

If you want the same text line in more than one label, you can make it fixed by placing the mouse pointer over the line and pressing the right mouse button, then choosing "Fixed" from the menu (or simply placing the caret and pressing Alt-x). This line will be copied into the following labels, and will maintain its font, if explicitly selected. To "de-fix" a line, follow the same procedure. Over the editor there is an indicator that display "fixed" when the caret is in a fixed line. Note that the normal lines will not be copied, but their place still exist and will remain empty.

## Setup

With the Setup button you can open the parameters windows. Here you can enter the physical dimension of paper and labels, including left, right, top and bottom margins. If you use continuous paper, you must set the dimension of each page between two perforation lines.

To save a setup, you have to type its name in the edit line of the list placed in the bottom right corner, then press Save or Ok. To delete a setup, simply select it from the list and press Delete.

While you are selecting the setup from the list, using the mouse or the arrow keys, the parameters will change to display the ones relative to the chosen setup.

All data will be stored in the system registry.

## Printing

The Print button starts printing of the labels choosed by “From” and “To” fields.

After printing, the labels are still in the database: if you enter another one, you will print the old ones again. To avoid this, you can use the last printed label number+1 as “From” field value, and you’ll print only the new labels.

You can choose on what label (on the paper) the print must begin. For example, if you put "2" in the “From pos” field, the first label will be printed in the second position. Positions are numbered from top to bottom and from left to right.

## How to register

The registration price is 10 US\$

To register TTLLabel 3.5, you have two choices:

if you are member of Compuserve, go swreg and use Registration ID 9637

if you are not a member of Compuserve, you can send money directly to:

Andrea Rescigno  
via Antonio Conti 67 L/6  
00123 Roma Italia  
(see User's license for E-Mail addresses)

or

Paul M. Eckett  
10, The Oval,  
Albrighton,  
Wolverhampton,  
West Midlands.  
WV7 3NL.  
United Kingdom.  
E-Mail:- paul\_e@dial.pipex.com

When we receive your payment, we'll send you a code which you should put in the registration form (choose Setup, then Register). After that, the title bar will show "registered to: your\_name" instead of "unregistered".

You have to send us your name, because your registration code will be derived from it.

If you have an E-Mail address, please include it, so we can send you the code more quickly than by ordinary mail.

## User's license

**Copyright © Andrea Rescigno 1995,1996**

TLabel 3.5 is shareware: you can duplicate and distribute it, but, if you find the program useful and continue to use it, you must register. See [How to register](#) for more details.

There is no warranty against possible bugs, malfunctioning, or incompatibility with some hardware, and the author is not responsible for them. You use this program at your own risk.

You can reach the author at the following addresses:

Internet 100105.3355@compuserve.com  
Compuserve 100105,3355  
Fidonet 2:335/373.6

The latest version of TLabel can always be found at:

[http://ourworld.compuserve.com/homepages/A\\_Rescigno](http://ourworld.compuserve.com/homepages/A_Rescigno)

Windows NT, Windows 95 and win32s are trademarks of Microsoft Corporation.



