



Cnd = Condensed	C	J	P	:	:	:	:	g	m	r	w
Dbl = Double width	D	K	Q	:	:	:	:	h	n	s	x
Elt = Elite	E	L	R	:	:	:	:	i	o	t	y
Ita = Italics	F	M	S	V	Y	b	:	j	:	:	:
Subscript	G	N	T	W	Z	c	e	k	p	u	:
Superscript	H	O	U	X	a	d	f	l	q	v	:
Backspace	z	:	:	:	:	:	:	:	:	:	:

For example, style 'g' would produce: **Condensed**

Backspace is not a style, but allows the combination of two or more characters by over-printing them. For example, when in the print formatter, by giving a character the style 'z' will make it overprint the previous character.

!CODES

; The letters refer to the type styles above.  
; Letters [, \, ], ^, \_ , ' are reserved for special use explained below

```

; ON          OFF
A 27,45,1    27,45,0
B 27,71      27,72
C 15         18
D 27,87,1    27,87,0
E 27,77      27,80
F 27,52      27,53
G 27,83,1    27,84
H 27,83,0    27,84
I A,B
J A,C
K A,D
L A,E
M A,F
N A,G
O A,H
P B,C
Q B,D
R B,E
S B,F
T B,G
U B,H
V C,F
W C,G
X C,H
Y D,F
Z D,G
a D,H
b E,F
c E,G
d E,H
e F,G
f F,H
g I,C
h I,D
i I,E
j I,F
k I,G
l I,H

```

```

m M,C
n M,D
o M,E
p M,G
q M,H
r S,C
s S,D
t S,E
u S,G
v S,H
w j,C
x j,D
y j,E
z 8          0
; Since backspace is not 'disabled', this feature is represented by a null
; that is ignored by the printer.

; Character labels ^ [ \ ] _ ' are used for special escape sequences outline
; below.

^ 27,69      27,58,0,0,0,27,37,1,0,27,54;ON = General Printer initialiasation
                                           ;OFF = Downloadable character sets init.
[ 27,38,0          ;ON = Download ONE character (start string)
                       ;OFF= Download ONE character (end string)
\ 2              12      ;ON = No of times to send ASCII code.
                       ;OFF= No of bytes of data to send from file
] 27,82         27,82,0 ;ON = Select character subset n (keyboard translation)
                       ;OFF= Select default character set
_                ;Reserved for future use
`                ;Reserved for future use

;The ^ OFF sequence is used prior to downloading all required characters.
;The [ ON sequence is used prior to downloading a specific character.
;The \ ON sequence indicates how many times to send downloading ASCII code
;The [ OFF sequence is used to finish the [ ON sequence
;The \ OFF sequence indicates the No of byte of data to send from the data file

```