



For example, style 'g' would produce: Bold+Underline+Condensed

Backspace is not a style, but allows the combination of two or more characters by over-printing them. For example, when in the print formatter, by giving a character the style 'z' will make it overprint the previous character.

!CODES

;	ON	OFF
A	27,45,1	27,45,0
B	27,71	27,72
C	15	18
D	27,87,1	27,87,0
E	27,77	27,80
F	27,52	27,53
G	27,83,1	27,84
H	27,83,0	27,84
I	A,B	
J	A,C	
K	A,D	
L	A,E	
M	A,F	
N	A,G	
O	A,H	
P	B,C	
Q	B,D	
R	B,E	
S	B,F	
T	B,G	
U	B,H	
V	C,F	
W	C,G	
X	C,H	
Y	D,F	
Z	D,G	
a	D,H	
b	E,F	
c	E,G	
d	E,H	
e	F,G	
f	F,H	
g	I,C	
h	I,D	
i	I,E	
j	I,F	
k	I,G	
l	I,H	
m	M,C	
n	M,D	
o	M,E	
p	M,G	
q	M,H	
r	S,C	
s	S,D	
t	S,E	
u	S,G	
v	S,H	
w	j,C	

```

x j,D
y j,E
z 8      0
; Since backspace is not 'disabled', this feature is represented by a null
; that is ignored by the printer.

; Character labels ^ [ \ ] _ ' are used for special escape sequences outline
; below.

^ 27,69    27,58,0,0,0,27,37,1,0,27,54;ON = General Printer initialiasation
                                           ;OFF = Downloadable character sets init.
[ 27,38,0          ;ON = Download ONE character (start string)
                       ;OFF= Download ONE character (end string)
\ 2              12    ;ON = No of times to send ASCII code.
                       ;OFF= No of bytes of data to send from file
]                ;Reserved
_ 27,37,1,0    27,37,0,0 ;ON=Select RAM
                       ;OFF=Select ROM characters
`              ;Reserved for future use

```