

# NEXTSTEP for Intel Processors

**Title:** Dell Dimension XPS 450V

**Entry Number:** 1522

**Last Updated:** <<Date June 13 1995>>

## **Product Vendor:**

Dell Computer Corporation

11209 Metric Blvd.  
Austin, Texas 78758  
USA

USA Toll-free Phone: +1 (800) 247 6821

Faxback System: +1 (800) 950 1329

Bulletin Board System: +1 (512) 728 8528

Europe Phone: 011 31 20 684 9291

SE Asia Phone: 011 866 2 391 2100

Japan Phone: 011 81 3 5420 5353

USA Fax: +1 (800) 727 8320

WWW: <http://www.dell.com/>

**Keywords:** Dell, Dimension, XPS, ISA, VESA, LocalBus, S3, #9, GXE, 928

**Disclaimer:**

The information contained herein is provided for informational purposes only, and constitutes neither an endorsement nor a recommendation of the product by NeXT Computer, Inc. All product specifications and descriptions are supplied by the respective vendor. NeXT Computer, Inc. assumes no responsibility with regard to the selection, performance, compatibility, or use of non-certified systems. All understandings, agreements, and warranties take place directly between the system vendor and the prospective user.

## Overview

The Dell Dimension XPS 450V includes a Intel 486 processor at 50Mhz, two VESA Localbus slots, and five ISA slots. It provides up to 1024 x 768 in 16 bit color and 1280 x 1024 in 8 bit grayscale with a #9 GXE graphics adapter.

## System Configuration

### System CPU Board(s)

Dell Dimension XPS 450V

### CPU Type(s) & Speed(s)

50MHz Intel 80486

### System RAM

16MB minimum (color), 8MB minimum (grayscale)

### IDE Controller(s)

Integrated

### SCSI Controller(s)

Adaptec 1542CF

### SCSI CD-ROM Drive(s)

NEC MultiSpin model # CDR-74-1 (External)

### Hard Drive(s)

431MB IDE - Seagate Model ST3550A

### Floppy Drive(s)

Integrated 1.44MB 3.5"

### Graphics Adapter(s)

#9 GXE

**Serial Port(s)**

Integrated, COM1,COM2

**Parallel Port(s)**

Integrated, LPT2

**Keyboard(s)**

Dell, PS/2 interface

**Mice and Other Pointing Devices**

Logitech, PS/2 interface

**LAN Adapter(s)**

Intel EtherExpress 16

**Sound Card(s)**

ProAudio Spectrum 16

**Monitor(s)**

Dell UltraScan 17FS-N model # VC7N

**Tested under NEXTSTEP for Intel Processors Release 3.2****Hardware Configuration Information****Dell Dimension XPS 450V**

Type(s): Desktop

Model Number(s): **Dimension XPS 450V**

**System CPU Board(s)**

Dell Dimension XPS 450V

BIOS Version: PhoenixBIOS

BIOS Revision Number: 0.10 A01

**CPU Type(s) & Speed(s)**

50MHz Intel 80486

**System RAM**

16MB minimum (color), 8MB minimum (grayscale)

**IDE Controller(s)**

Integrated

**SCSI Controller(s)**

Adaptec 1542CF

Interface: ISA adapter

BIOS Revision Number: 1.02

Firmware Revision Number(s):

534001-00 E (slot U5)

534201-00 E (slot U15)

533600-01 F (surface mount U10)

**SCSI CD-ROM Drive(s)**

NEC MultiSpin (External)

Model Number: CDR-74-1

**Hard Drive(s)**

452MB IDE - Seagate model #ST3550A

**Floppy Drive(s)**

Integrated 1.44MB 3.5"

**Graphics Adapter(s)**

#9GXE

Interface: VLB (slot 7)

BIOS Revision Number: 1.13.03S

Chipset: S3 P86C928

RAMDAC: Brooktree Bt948KPJ135

VRAM: 2MB

**Serial Port(s)**

Integrated, COM1,COM2

**Parallel Port(s)**

Integrated, LPT2

**Keyboard(s)**

Dell, PS/2 Interface  
Model Number: SK-1000RS

**Mice and Other Pointing Devices**

Logitech, PS/2 interface  
Model Number: M-SR14-6MD

**LAN Adapter(s)**

Intel EtherExpress 16  
Interface: ISA adapter  
Connectors: BNC, AUI

**Sound Card(s)**

ProAudio Spectrum 16

**Monitor(s)**

Dell UltraScan 17FS-N  
Model Number: VC7N

**Known Problems:****Releases 3.1 and 3.2:**

- The standard mouse that Dell ships with this system is incompatible with the NEXTSTEP mouse driver.  
**Request the optional Microsoft mouse when ordering this system.**
- There is a known incompatibility with the firmware found in Seagate IDE drive model number ST3550a

when used with NEXTSTEP 3.1 and 3.2. This error manifests during installation when a sequence of IDE error messages occur and installation stops. The error "Disk initialization failed" is then reported.

A firmware upgrade to fix this problem is available through Seagate. Call 408-438-8222 to find the location of the nearest sales office. Model ST3550a requires firmware update 9581..

Systems purchased from Dell with these hard drive models are supported directly by Dell. Contact their support organizations for assistance.