

QUICK-CATALOGER (tm) INSTRUCTIONS

Purpose:

To provide a resident disk catalog program that can be run at any time, without destroying the Ex. BASIC program in memory and without using the Disk Manager module.

Equipment required:

1. Disk,
2. Ex. BASIC,
3. 32K RAM.

General information:

QUICK-CATALOGER essentially adds a very powerful new BASIC command, CALL LINK("CAT"), which allows you to get a disk catalog at any time. QUICK-CATALOGER is only loaded once, into the machine language portion of the 32K ram. It remains available for re-use at any time, until a CALL INIT statement clears memory, or until the power to the 32K RAM is turned off. You can type NEW, load and run several BASIC or Extended BASIC programs, change modules, even turn the console off and back on--and QUICK-CATALOGER will still be available for instant use. (The Ex. BASIC module must be plugged in at the time that you run QUICK-CATALOGER.)

To load QUICK-CATALOGER into memory:

Plug in the Extended BASIC module.
Turn on all power switches, console switch last.
Insert QUICK-CATALOGER disk in drive 1.
From Master Title screen: Press any key.
From Master menu: Select Extended BASIC.

QUICK-CATALOGER will automatically load itself. From then on, to get a catalog at any time from DSK1, type, CALL LINK("CAT") Enter. The CALL may also be used as a program statement.

To get a catalog from DSK2, type CALL LINK("CAT",2) Enter.

To get a catalog from DSK3, type CALL LINK("CAT",3) Enter.

To get a catalog on both the screen and printer, type CALL LINK("CAT",1,"PIO") Enter.

Note that if you run an Extended BASIC program that has a CALL INIT statement in it, QUICK-CATALOGER will be cleared from memory and must be re-loaded before it can be used again.

REPLACEMENT POLICY:

If, on arrival, the program fails to perform as specified herein, return it directly to us, within three days, along with proof of purchase, for a free replacement. After three days, you may obtain a replacement by returning the disk directly to us, along with \$7, plus \$3 for shipping and handling (Total = \$10).

To prevent accidentally blowing a disk, we strongly recommend that you put a tape over the write-protect notch BEFORE using the disk. In addition, DO NOT leave the disk in the drive when turning power on or off.

Disks obtained from QUALITY 99 SOFTWARE cannot be cataloged, duplicated, or written on.

WARNING: Any modification to the disk will render it inoperable, and voids the Replacement Policy.

If you feel that it is essential to have a back-up disk on hand, we suggest that you purchase another one, just as you would do for a module.

IMPORTANT: If you did not purchase this program directly from QUALITY 99 SOFTWARE, be sure to send us your name, address, and the name of the program, so that we may send you notification of program updates.

If you have any suggestions for improvement or would like to suggest a new program to be on the market, please feel free to call or write. Thank you for buying from QUALITY 99 SOFTWARE.

Program and Instructions
(C) Copyright 1985
QUALITY 99 SOFTWARE

```
QUICK-CATALOGER (TM)
(C) 1984 QUALITY 99 SOFTWARE
NOW LOADED IN LOW MEMORY
5035 BYTES AVAILABLE
SAMPLE CALLS:
CALL LINK("CAT") [FOR DSK1]
CALL LINK("CAT",2)
CALL LINK("CAT",1,"RS232.BA=
4800.")
ANY KEY FREEZES DISPLAY
FCTN CLEAR ABORTS LISTING
```