

## Release note of the OPL3-SAx software package

Yamaha Corporation  
December 26, 1996

The following are the list of the document and disk included of the OPL3-SAx software package.

### 1. Disks Volume Label

- 1) SaW95 the disk for the installation of Windows 95 driver and a application (Ystation Version 1.21).

### 2. Disk contents

Win95 drivers

Opl3sa.drv, Sacom.???, Saide.???, Sareserv.???, Sasound.???, Vopl3sa.vxd, Vsgm.vxd, Vymixd.vxd and R\_note95.doc.

WINST95.EXE is selfextracting archive. It contains several files shown below.

YSTATION	EX_	110,594	96-12-18	19:28	YSTATION.EX_
MUSCROLL	DL_	32,503	96-11-27	15:55	MUSCROLL.DL_
README	WR_	137,500	96-12-13	21:13	README.WR_
TEST	WAV	55,520	96-09-28	19:04	TEST.WAV
WINSTALL	EXE	182,528	96-12-17	18:34	WINSTALL.EXE
WINSTALL	INF	586	96-12-03	15:05	WINSTALL.INF
SACDROM	SYS	2,143	96-12-13	16:44	SACDROM.SYS
SETUP_Y	EXE	170,960	96-11-29	14:21	SETUP_Y.EXE
INSTALL	INF	1,345	96-12-12	18:15	INSTALL.INF
OPL3SA	INI	682	96-11-29	14:50	OPL3SA.INI
SETUPSA	EXE	152,258	96-12-26	19:06	SETUPSA.EXE
INSTALL	EXE	82,980	96-12-17	13:12	INSTALL.EXE
MESSAGE	TBL	2,773	96-12-18	19:39	MESSAGE.TBL

### 3. Installation

Batch files "WINSTALL.BAT" make temporary directory, copy archive and extract files in the archive. Then execute "EXE" programs for installation. You can delete the temporary directory after the installation.

- 1) for Windows 95

"WINSTALL.BAT" in the disk [SAW95]

Installation of only application (Ystation) for Windows

This batch file executes "WINSTALL.EXE".

Batch Options:

WINSTALL -d: Installation of configuration utility (SETUPSA)

for only DOS environment of Win95

This batch file executes "INSTALL.EXE" with "-s" option.

WINSTALL -a: Installation of application(Ystation) and configuration utility(SETUPSA)for only DOS environment of Win95

This batch file executes "WINSTALL.EXE" and "INSTALL.EXE" with "-s" option.

When using IDE CD-ROM interface of soundcard in DOS-MODE of Windows 95, add the option "-c" also as follows.

"WINSTALL -d -c"

"WINSTALL -a -c"

#### **4.Configuration Utility (SETUPSA.EXE)**

1. Configuration Manager or PnP BIOS is in your system.

1-A. Type "SETUPSA"

Open the dialog box, and display the information of OPL3-SAx I/O address, DMA and IRQ assigned by Configuration Manager or PnP BIOS. Set the value of master volume that is written into OPL3SA.INI.

When you change the master volume and click "OK", the value is set and written into OPL3SA.INI.

1-B. Type "SETUPSA /S"

Do not open the dialog box, but display the configuration of OPL3-SAx on the screen. Set the value of master volume that is written into OPL3SA.INI.

2. Configuration Manger and PnP BIOS are not in your system.

2-A. Type "SETUPSA"

Open the dialog box, and display and set the contents into OPL3SA.INI. When you change the configuration and the master volume and click "OK", they are set and written into OPL3SA.INI.

#### **5.Difference from the previous release**

SETUPSA.EXE(Version 1.01)

Change the default value of "GAMEPORT"(OFF--->201H)