

# Table of Contents

[Overview](#)

[Using Hang-It-Up](#)

[Advanced Features](#)

# Overview

**Hang-It-Up** allows you to schedule the shut down of any Windows 95 dial-up networking session. This allows you to leave Internet software running unattended and know that it will disconnect when the job is done.

You can set **Hang-It-Up** to hang up in 30 minutes, 24 hours, 5 minutes, immediately, or any setting you choose. This will let you walk away from a download and go to a movie, or used in conjunction with other ForeFront programs, set up sophisticated scripts to get your e-mail every night.

# Using Hang-It-Up

**Hang-It-Up** is a simple, and useful program. You can use **Hang-It-Up** in many different ways:

- ◆ **Hang-It-Up** allows a user to schedule the shut down of a Windows 95 dial-up networking session.
- ◆ To have the program shut down immediately, type "hangitup" at a DOS prompt.
- ◆ Use Hang-It-Up with batch files.
- ◆ **Hang-It-Up** can also be used effectively with a scheduling program such as ForeFront's Schedule. Just schedule "hangitup.exe" with no parameters and it will hang up when scheduled.

# Advanced Features



Command Line Options



Hang-It-Up .INI File

# Command Line Options

The Following Command Line Options are available:

/H:1	Hang up in 1 hour
/H:24	Hang up in exactly 24 hours.
/M:24	Hang up in 10 minutes.
/H:1 /M:30 or /M:90	Hang up in 90 minutes



**See Also**

[Hang-It-Up .INI File](#)

# Hang It Up INI File

These are the settings for the HANGITUP.INI file:

## [Settings] Section

TimeTotal=0 ;Default is 0 (Immediate disconnect) -- Number of seconds before hanging up - Can be overridden by command line

ExitWhenDone=1 ;Default is 1 (ON) -- Exits the program after disconnect - Can be overridden by command line

Update=1 ;Default is 1 (One Second) -- Determines how frequently to update the time in the title bar

## [Strings] Section

Connected to=Connected to ;First part of dialog box when connected (minus the Dial-Up name)

Disconnect=Dis&connect ;Text on disconnect button - must have "&" before underlined character on the Disconnect button

