

Contents

The following Help Topics are available:

[Status Page](#)

[Print Quality Page](#)

[Paper Page](#)

[Page Format Page](#)

[Service Page](#)

For Help on Help, Press F1

Status

Status Indicator: *Shows the condition of the printer.*

- **Online:** Ready for printing---icon color is blue.
- **Offline:** Not able to print---icon color is yellow, or red if error is serious.
- Second line: Printer activity or error condition.

Port: Shows/selects which parallel port the printer is connected to.

Display:

- **Always On Top:** When checked, reduced window/icon always visible.
- **Shrink To Icon:**
When not checked, appears as reduced window with status only.
When checked, appears as icon.

Buttons:

- **OK:** Save changes and exit.
- **Cancel:** Discard changes and exit.
- **Help:** Display this Help screen.
- **About:** Display version and copyright information.

Print Quality

Darkness: Adjust print density if print is too light or too dark.

Toner Saving: Use to conserve toner when printing rough drafts:

- *Medium:* Reduces toner use by 30%.
- *Light:* Reduces toner use by 50%.
- *Off:* Normal use.

Power Save: Shuts down heating element to reduce power consumption. The printer must warm up before printing.

- *Disable:* Does not shut down.
- *Immediate:* Shuts down every time a print job is finished.
- *After 8 Minutes:* Shuts down 8 minutes after last print job.

Auto Eject: Prints buffer contents after chosen time without receiving more data.

- *Off:* Waits for print command (Form Feed).

Buttons:

- **OK:** Save changes and exit.
- **Cancel:** Discard changes and exit.
- **Help:** Display this Help screen.

Paper

This page sets paper feeding choices. The settings on this page apply to HP emulation only.

Source: Where the paper is fed from:

- **Tray 1:** Built-in tray, takes standard paper sizes, no envelopes or heavy weight paper.
- **Manual:** For individual hand-feeding, takes standard & non-standard paper sizes, envelopes, heavy weight paper.
- **Feeder:** Optional multipurpose feeder, takes standard paper and envelope sizes.
- **Tray 2:** Optional second tray, takes standard paper sizes, no envelopes or heavy weight paper.

Size: Paper size for each available source.

Thickness: Approximate paper thickness for each available source---optimizes print quality for the paper being used.

Orientation: Direction of printing on the paper:

- **Portrait:** Normal upright orientation.
- **Landscape:** Prints along the width of the page.

Auto Tray Switch: With second tray installed, click here to automatically switch to second tray when first tray is empty.

Copies: Select number of each page to print---up to 99. This can also be controlled by software.

Buttons:

- **OK:** Save changes and exit.
- **Cancel:** Discard changes and exit.
- **Help:** Display this Help screen.

Page Format

This page sets page format and font choices. The settings on this page apply to HP emulation only.

Font Source: Shows/selects source of default font.

- Resident: Font built into the printer.
- DLL: Soft font, permanently downloaded to the printer.

Default Font: Shows/selects font used if your software does not change the font. Listing includes font ID number, name, and size. This control is only visible if the Font Source is Resident.

DLL Font: Shows/selects the DLL softfont ID number used if your software does not change the font. This control is only visible if the Font Source is DLL.

Symbol Set: Shows/selects symbol set used. HP standard is Roman-8; others provide special characters for some foreign languages.

Cartridge: For HP LaserJet II emulations, shows/selects Tms Roman cartridge B or F for compatibility.

A4 Width: Shows/selects how a line of 80 10-pitch characters prints on A4 paper, which is slightly narrower than the US standard.

- **78 Columns:** Normal spacing.
- **80 Columns:** Condenses spacing to fit 80 characters on the line.

Skip Blank Pages: Printer does not print pages that are completely blank.

Lines Per Page: Shows/selects how many lines print on the page (5 - 128).

Page Protect: Reserves printer memory for chosen page size to reduce print overruns.

Buttons:

- **OK:** Save changes and exit.
- **Cancel:** Discard changes and exit.
- **Help:** Display this Help screen.

Service

Print Page: Prints the selected type of page.

- **Demo:** Sample of printer features.
- **Menu:** Operator Panel settings.
- **Fonts:** Samples of all available resident and downloaded fonts.
- **Cleaning:** A page that removes impurities from cleaning surfaces. Manually feed a blank sheet of paper when prompted.

Reset:

- **Drum Count:** Resets drum count to zero. Reset the drum count only when you install a new drum!
- **Menu:** Resets all Operator Panel settings to the factory defaults.

X-Pos/Y-Pos Adjust: Fine-tunes the horizontal/vertical print position up to 2 mm plus or minus, in 0.25-mm increments.

Buttons:

- **OK:** Save changes and exit.
- **Cancel:** Discard changes and exit.
- **Help:** Display this Help screen.

