



### **For 16-bit Intel processors Extender DLL Name**

AddExtender("wilx16i.dll")  
Additional Dlls required: NONE

### **For 32-bit Intel processors Extender DLL Name**

AddExtender("wilx32i.dll")  
Additional Dlls required: NONE

This extender provides additional capability to the Windows Interface Language and is a good example of the useful things you as a developer can create using the Extender SDK.

Third party developers can customize and develop their own function libraries with by making their own extenders. Custom extender Dlls may add nearly any sort of function to the WIL language, from the mundane network, math or database extensions, to items that can control fancy peripherals, including laboratory or manufacturing equipment. The source code for the 32-bit WILX extender is included on the WinBatch+Compiler CD-ROM. Technical support for the SDK is not included in the price of the WinBatch+Compiler product, although most experienced developers will find that support is not needed.

To use WILX extender source code you will need appropriate programming tools, such as Microsoft Visual C++ , and a good deal of experience using Visual C++ to develop Windows programs and DLLs.

## **Table of Contents**

### **Functions**

#### xBaseConvert(value, from-base, to-base)

Performs base conversions

#### xCursorSet(setting)

Shows/hides/changes cursor.

#### xDiskLabelGet(drive)

Returns volume label of specified drive.

#### xDriveReady(drive)

Checks whether the drive is ready.

#### xExtenderInfo(request #)

Returns information on this extender.

#### xGetChildHwnd(parent-hwnd, child-text, child-seq)

Gets the handle of a child window belong to the specified parent.

#### xGetElapsed(time1, time2)

Calculates difference between two values obtained with ExactTime().

xHex(hex-val)

Converts from hex to decimal.

xMemCompact(type)

Compacts Global or Local memory.

xMessageBox(title, text, style)

The "real" MessageBox function.

xSendMessage(hWnd, msg, wParam, lParam)

xVerifyCCard(cardnum)

Verifies the validity of a credit card number.

xEjectMedia(Drive)

The real "SendMessage".

Returns information on this extender.

**Syntax:**

xExtenderInfo(request #)

**Parameters:**

- (i) request #    0 = version
- 1 = total functions
- 2 = total constants

This function returns information on this extender. Version number, number of functions and number of constants.

**Example:**

```
ver = xExtenderInfo(0)
ftot = xExtenderInfo(1)
ctot = xExtenderInfo(2)
Message("WILX version %ver%", "Total functions: %ftot% %CRLF% Total
constants: %ctot%")
```



Converts from hex to decimal.

**Syntax:**

xHex(hex-val)

**Parameters:**

- (i) hex-val      hex number to convert (must be delimited if it contains letters)

Like xBaseConvert, but is a simpler way to perform the most useful conversion.

**Example:**

```
hex = AskLine("Hex to decimal conversion", "Enter a hex value", "FF")
dec = xHex(hex)
Message("Hex to decimal conversion", "Hex: %@TAB% %hex% %@CRLF% Decimal: %@TAB%
%dec%")
```

Shows/hides/changes cursor.

**Syntax:**

xCursorSet(setting)

**Parameters:**

- (i) setting      1 = show  
                  2 = hide,  
                  any other number is treated as a cursor

Resource identifier to be loaded (the API documentation helps).

**Note:** This function is not supported in 32 bit versions of the extender.

**Example:**

```
arrowcur = 32512
hglascur = 32514
varowcur = 32516

Message("Cursor tests", "Move the cursor to somewhere you can see it")

Display(1, "Next", "Cursor will change to an hourglass")
xCursorSet(hglascur)
Delay(2)

Display(1, "Next", "Cursor will change to a vertical arrow")
xCursorSet(varowcur)
Delay(2)

;Display(1, "Next", "Cursor will change to a normal arrow")
;xCursorSet(arrowcur)
;Delay(2)

scr = IniReadPvt("Boot", "scrnsave.exe", "", "system.ini")
scr = StrReplace(StrUpper(scr), ".SCR", "*SCR")
Display(2, "Cursor test", "Press any key after screen saver activates")
xCursorSet(@OFF)
RunWait(scr, "/s")
xCursorSet(@ON)
```

Calculates difference between two values obtained with ExactTime().

**Syntax:**

```
xGetElapsed(time1, time2)
```

**Parameters:**

- (i) time1        ending time
- (i) time2        start time

**Example:**

```
time1 = GetExactTime()  
Display(1, "Elapsed time test", "Delaying for 1 second")  
time2 = GetExactTime()  
rc = xGetElapsed(time2, time1)  
Message("Elapsed time", rc)
```



The "real" MessageBox function.

**Syntax:**

```
xMessageBox(title, text, style)
```

**Parameters:**

- (s) title           title of message box
- (s) text:           text to go in message box
- (s) style           type of icon and/or button(s) to use (the API documentation helps)

Returns the value assigned to the button that was pressed.

**Style Parameter / Predefined Integer Constants**

- @MBOKCANCEL (= 1)
- @MBYESNO (= 4)

**Example:**

```
mbstop            = xHex(10)
mbquestion        = xHex(20)
mbexclaim         = xHex(30)
mbinfo            = xHex(40)
idyces            = xHex(6)
idno              = xHex(7)

rc = xMessageBox("MessageBox test", "Are you having fun?", @MBYESNO | mbquestion)

Switch rc
  case idyces
    xMessageBox("Good", "I'm glad to hear it", mbexclaim)
    break
  case idno
    xMessageBox("Sorry", "That's too bad", mbinfo)
    break
  case rc
    xMessageBox("Hey!", "We shouldn't be here!", mbstop)
    break
EndSwitch
```

Returns volume label of specified drive.

**Syntax:**

```
xDiskLabelGet(drive)
```

**Parameters:**

(s) drive            drive letter

Returns volume label of specified drive.

**Example:**

```
drives = DiskScan(6)
tot = ItemCount(drives, " ")
msg = ""

For i = 1 To tot
    drive = ItemExtract(i, drives, " ")
    label = xDiskLabelGet(drive)
    msg = StrCat(msg, "%drive%%@TAB%%label%%@CRLF%")
Next

Message("Volume labels", msg)
```

Ejects media from removable drives.

**Syntax:**

```
xEjectMedia(drive)
```

**Parameters:**

(s) drive          drive letter

Sends a request to the hardware to eject the media cartridge. This function was designed for drives that can automatically unload the media cartridge, such as most CD-ROM and JAZ drives.

**Example:**

```
AddExtender("wilx32i.dll")
drive = "s:"
rc = xEjectMedia(drive)
Message("xEjectMedia", rc)
```

Verifies the validity of a credit card number.

**Syntax:**

xVerifyCCard(cardnum)

**Parameters:**

(i) cardnum credit card number, can include spaces or hyphens

**Returns**

1 if card number is valid, 0 if it isn't

This function verifies whether it is possible for a number to be a valid credit card number. It doesn't verify that the number is real, working credit card number. It only verifies that the number could be a valid credit card number.

**Example:**

```
card = AskLine("Credit card validation", "Enter a credit card number", "")
rc = xVerifyCCard(card)
If rc == 1 Then Message("Credit card number", "Is valid")
Else Message("Credit card number", "Is NOT valid")
```

Compacts Global or Local memory.

**Syntax:**

```
xMemCompact(type)
```

**Parameters:**

(i) type            0 = Global,  
                     1 = Local

Returns number of bytes in the largest free (Global or Local) memory object.

In Windows 95, this function is not supported and will return 0.

In Windows NT, this function has been fixed to use the appropriate Win32 system calls. Since there's no distinction between local and global memory in NT, it doesn't make any difference whether you specify a 'type' of 0 or 1.

**Example:**

```
gfree = xMemCompact(0)
lfree = xMemCompact(1)
Message("Largest free memory objects", "Global: @@TAB% %gfree% @@CRLF% Local: @@TAB
% %lfree%")
```

Checks whether the drive is ready.

**Syntax:**

xDriveReady(drive)

**Parameters:**

(s) drive      drive letter

Checks whether the drive is ready indicating that there is a disk in the drive. This is mainly useful for floppy and CD-ROM drives.

**Example:**

```
Pause("DriveReady test", "Put a floppy disk in Drive A:")
ready = xDriveReady("a:")
If ready Then Message("Drive A:", "Is ready")
Else Message("Drive A:", "Is NOT ready")

Pause("DriveReady test", "Now take the disk out of Drive A:")
ready = xDriveReady("a:")
If ready Then Message("Drive A:", "Is ready")
Else Message("Drive A:", "Is NOT ready")

Message("WILX", "The end")
```

Gets the handle of a child window belong to the specified parent.

**Syntax:**

```
xGetChildHwnd(parent-hwnd, child-text, child-seq)
```

**Parameters:**

- (s) parent-hwnd      handle of the parent window
- (s) child-text        text string of the child window (may be blank)
- (i) child-seq         position sequence of the child window (may be 0)

**Returns:**

- (i)                    the child handle or 0 if child window is not found.

Either child-text or child-seq, or both, must be specified.

If only the text is specified, it will be compared to all children until a match is found; if not, 0 is returned.

If only the sequence is specified, it will be assumed to be correct; if there are less than 'seq' children, 0 is returned.

If both text and sequence are specified, the text is compared to only that one specific child; if they don't match, 0 is returned.

Text comparisons are case-insensitive, the '&' in the control string (if any) is stripped out, but leading and trailing spaces are not stripped.

**Example:**

```
; Determine whether 'Fast "Alt+Tab" Switching' checkbox in Control Panel  
; "Desktop" dialog is checked, and then press the Cancel button
```

```
BMGETCHECK        = 1024  
WMLBUTTONDOWN    = 513  
WMLBUTTONUP      = 514
```

```
If WinExist("Control Panel") == @FALSE Then Run("control.exe", "")  
Then runpanel = 1  
SendMenusTo("Control Panel", "Settings | Desktop")
```

```
hWnd = DllHwnd("Desktop")  
Terminate(hWnd == 0, "Error", "Parent window not found")
```

```
; we know from experience that this control is sequence #6  
hWndChild = xGetChildHwnd(hWnd, 'Fast "Alt+Tab" Switching', 6)  
Terminate(hWndChild == 0, "Error", "Check box not found")  
checked = xSendMessage(hWndChild, BMGETCHECK, 0, 0)
```

```
; on the other hand, we don't know the sequence # for the Cancel button  
hWndChild = xGetChildHwnd(hWnd, "Cancel", 0)  
Terminate(hWndChild == 0, "Error", "Cancel button not found")  
xSendMessage(hWndChild, WMLBUTTONDOWN, 0, 0)
```

```
xSendMessage(hWndChild, WMLBUTTONUP, 0, 0)
```

```
If checked == 1 Then Message('Fast "Alt+Tab" Switching', "Box is checked")  
Else Message('Fast "Alt+Tab" Switching', "Box is NOT checked")
```

```
If IsDefined(runpanel) Then WinClose("Control Panel")
```

```
:cancel
```





