

*Supported System Software: 7.5.2, 7.5.3*

*SCSI: DB-25*

*Serial Ports: 2*

*Sound Output: stereo 16 bit.*

*ADB: 1*

*Ethernet: AAUI, 10baseT built-in or upgrade to Newer Technology 7ET-PCI10/100*

*Machine Gestalt ID: 69*

*Minutiae:*

*Upgraded with one DIMM at a time.*

*Can be accelerated with Newer Technology's Eddy Award winning "PowerClip 604™", part # 7MC604-B. The PowerClip has over 100 different speed settings up to 165MHz. Typically the 8515/120 is set to something between 150MHz and 164MHz. The PowerClip is slotless.*

*It is important to note that some Apple 256KB Cache DIMMs will prevent the PowerClip 604 from accelerating the 8515/120 beyond 130MHz. There are three solutions to this problem:*

*A. Most desirable, use Newer Technology's high-speed 256KB Cache DIMM, part # 7CC256B.*

*B. Remove the Apple Cache DIMM and simply run the computer without it.*

*C. Least desirable, return the PowerClip.*

*Can interleave memory for approximately 10-30% faster RAM access. For the fastest speed, sockets A1 & B1, A2 & B2...A4 & B4 should contain identical capacity DIMMs.*

*Original enabler: 701 v1.2*

*Serial Port with the phone icon supports synchronous modems, with handshaking on both output and input supported.*

*Has 4MB ROM and a 1.44MB SuperDrive.*