



Help for JoyStk

[Properties](#)

[Events](#)

Registration Information

Order Form

Getting Custom Controls Written

Description

JoyStk is a Visual Basic custom control that sends joystick information to your VB program.

File Name

JOYSTK1.VBX

Object Type

Joystick

Distribution Note When you develop and distribute an application that uses JoyStk, you should install the file JOYSTK1.VBX into the users Windows SYSTEM directory. JoyStk has version information built into it. So, during installation, you should ensure that you are not overwriting a newer version of JoyStk.

Properties

All of the properties that apply to this control are in this table.

Properties that have special meaning for this control or that only apply to this control are marked with an asterisk (*).

<u>Align</u>	<u>Left</u>	<u>Top</u>
<u>*Button1</u>	<u>*Manufacturer</u>	<u>*XMax</u>
<u>*Button2</u>	<u>Name</u>	<u>*XMin</u>
<u>*Button3</u>	<u>*Period</u>	<u>*XPos</u>
<u>*Button4</u>	<u>*PeriodMax</u>	<u>*YMax</u>
<u>*Buttons</u>	<u>*PeriodMin</u>	<u>*YMin</u>
<u>*Devices</u>	<u>*Port</u>	<u>*YPos</u>
<u>Enabled</u>	<u>*Product</u>	<u>*ZMax</u>
<u>HelpContextID</u>	<u>*ProductName</u>	<u>*ZMin</u>
<u>hWnd</u>	<u>Tag</u>	<u>*ZPos</u>
<u>Index</u>	<u>*Threshold</u>	

Button1, Button2, Button3, and Button4 Properties

[See Also](#)

Description

Returns the current state of the joystick's buttons.

Usage

*[form.]***Button1**

*[form.]***Button2**

*[form.]***Button3**

*[form.]***Button4**

Remarks

These properties tell you which button(s) were pressed at the last time it was polled (see [Period](#)). They are read-only at run-time only. They are only valid after the joystick has been enabled.

Data Type

Integer (boolean)

See Also

Events:

[ButtonDown](#)

[ButtonUp](#)

Properties:

[Buttons](#)

[Period](#)

Buttons Property

[See Also](#)

[Example](#)

Description

Returns the number of buttons on the joystick.

Usage

*[form.]***Buttons**

Remarks

This property returns the number of buttons on the joystick.

This property is read-only at run-time only. It is only valid after the joystick has been enabled.

Data Type

Integer

See Also

Events:

[ButtonDown](#)

[ButtonUp](#)

Properties:

[Button1](#)

[Devices](#)

[Manufacturer](#)

[PeriodMax](#)

[PeriodMin](#)

[Port](#)

[Product](#)

[ProductName](#)

Devices Property

[See Also](#)

[Example](#)

Description

Returns the number of joysticks supported by the current driver.

Usage

*[form.]***Devices**

Remarks

This property tells you how many joysticks are supported in the system.

This property is read-only at run-time only. It is only valid after the joystick has been enabled.

Data Type

Integer

See Also

Properties:

[Buttons](#)

[Manufacturer](#)

[PeriodMax](#)

[PeriodMin](#)

[Port](#)

[Product](#)

[ProductName](#)

Manufacturer Property

[See Also](#)

[Example](#)

Description

Returns the manufacturer's ID of the joystick.

Usage

*[form.]***Manufacturer**

Remarks

This represents the manufacturer of the driver. The values returned are:

Value	Description
1	Microsoft

This property is read-only at run-time only. It is only valid after the joystick has been enabled.

Data Type

Integer

See Also

Properties:

[Buttons](#)

[Devices](#)

[PeriodMax](#)

[PeriodMin](#)

[Port](#)

[Product](#)

[ProductName](#)



Information Properties Example

In this example, the program will show the informational properties. To try this example, paste the code into the Declarations section of a form that contains seven labels, and a JoyStk control. Make sure that the Port property of the JoyStk control is set properly. Press F5. You'll see the settings of all of the informational properties.

```
Sub Form_Load ()
    Joystick1.Enabled = True

    Label1.Caption = "Buttons: " & Joystick1.Buttons
    Label2.Caption = "Devices: " & Joystick1.Devices
    Label3.Caption = "Manufacturer: " & Joystick1.Manufacturer
    Label4.Caption = "PeriodMin: " & Joystick1.PeriodMin
    Label5.Caption = "PeriodMax: " & Joystick1.PeriodMax
    Label6.Caption = "Product: " & Joystick1.Product
    Label7.Caption = "ProductName: " & Joystick1.ProductName

    Joystick1.Enabled = False
End Sub
```

Period Property

[See Also](#)

[Example](#)

Description

Sets the polling interval for the joystick.

Usage

`[form.][control.]Period[= integer]`

Remarks

This property determines the polling rate (in milliseconds) of the joystick.

When changing this property at run-time, the control should be disabled prior to changing it, then re-enabled afterwards.

Data Type

Integer

See Also

Properties:

[PeriodMax](#)

[PeriodMin](#)



Period Property Example

In this example, the program will show the effects of different settings for the Period property. To try this example, paste the code into the Declarations section of a form that contains a horizontal scroll bar, two labels, and a JoyStk control. Press F5. Play with the horizontal scroll bar, then try the joystick, then the scroll bar again, etc.

```
Sub Form_Load ()
    Joystick1.Enabled = True

    HScroll1.Min = Joystick1.PeriodMin
    HScroll1.Max = Joystick1.PeriodMax
    HScroll1.Value = (Joystick1.PeriodMax + Joystick1.PeriodMin) / 2

    Call HScroll1_Change
End Sub

Sub Form_Unload (Cancel As Integer)
    Joystick1.Enabled = False
End Sub

Sub HScroll1_Change ()
    Label1.Caption = "Period: " & HScroll1.Value & " milliseconds"

    ' need to disable the joystick while doing this
    Joystick1.Enabled = False
    Joystick1.Period = HScroll1.Value
    Joystick1.Enabled = True
End Sub

Sub HScroll1_Scroll ()
    Call HScroll1_Change
End Sub

Sub Joystick1_Move (X As Integer, Y As Integer, Z As Integer)
    Label2.Caption = "Position: " & X & ", " & Y
End Sub
```

PeriodMin and PeriodMax Properties

[See Also](#)

[Example](#)

Description

Returns the minimum and maximum times between polling that this joystick supports.

Usage

*[form.]***PeriodMax**

*[form.]***PeriodMin**

Remarks

These properties specify the minimum and maximum times between polling that the joystick driver supports (see [Period](#)).

This property is read-only at run-time only. It is only valid after the joystick has been enabled.

Data Type

Integer

See Also

Properties:

[Buttons](#)

[Devices](#)

[Manufacturer](#)

[Port](#)

[Product](#)

[ProductName](#)

Port Property

Description

Determines which joystick port to use.

Usage

[*form.*][*control.*]**Port**[= *integer*]

Remarks

This property determines which joystick to use. The allowable values are:

Value	Description
1	Joystick 1, 3-D joystick, or 4-button joystick
2	Joystick 2

This property must be set at design-time.

Data Type

Integer

Product Property

[See Also](#)

[Example](#)

Description

Returns the product ID fo the joystick driver.

Usage

[*form.*][*control.*]**Product**

Remarks

This represents the product ID of the driver. The values returned are:

Value	Description
1	Microsoft MIDI Mapper
2	Microsoft Wave Mapper
3	Sound Blaster MIDI output port
4	Sound Blaster MIDI input port
5	Sound Blaster internal synthesizer
6	Sound Blaster waveform output port
7	Sound Blaster waveform input port
9	AdLib-compatible synthesizer
10	MPU401 MIDI output port
11	MPU401 MIDI input port
12	IBM Game Control Adapter

This property is read-only at run-time only. It is only valid after the joystick has been enabled.

Data Type

Integer

See Also

Properties:

[Buttons](#)

[Devices](#)

[Manufacturer](#)

[PeriodMax](#)

[PeriodMin](#)

[Port](#)

[ProductName](#)

ProductName Property

[See Also](#)

[Example](#)

Description

Returns the product name of the joystick driver.

Usage

*[form.]***ProductName**

Remarks

This property specifies the product name of the joystick driver.

This property is read-only at run-time only. It is only valid after the joystick has been enabled.

Data Type

String

See Also

Properties:

[Buttons](#)

[Devices](#)

[Manufacturer](#)

[PeriodMax](#)

[PeriodMin](#)

[Port](#)

[Product](#)

Threshold Property

[See Also](#)

[Example](#)

Description

Determines the amount the joystick must move for an event to be fired.

Usage

*[form.]***Threshold** [= *integer*]

Remarks

This property determines the amount the joystick must move for a Move eventMove event to be fired.

When changing this property at run-time, the control should be disabled prior to changing it, then re-enabled afterwards.

Data Type

Integer

See Also

Events:

[Move](#)

Properties:

[Port](#)



Threshold Property Example

In this example, the program will show the effects of different settings for the Threshold property. To try this example, paste the code into the Declarations section of a form that contains a horizontal scroll bar, two labels, and a JoyStk control. Press F5. Play with the horizontal scroll bar, then try the joystick, then the scroll bar again, etc.

```
Sub Form_Load ()
    Joystick1.Enabled = True

    HScroll1.Min = 1
    HScroll1.Max = 32000
    HScroll1.Value = 100

    Call HScroll1_Change
End Sub

Sub Form_Unload (Cancel As Integer)
    Joystick1.Enabled = False
End Sub

Sub HScroll1_Change ()
    Label1.Caption = "Threshold: " & HScroll1.Value & " units"

    ' need to disable the joystick while doing this
    Joystick1.Enabled = False
    Joystick1.Threshold = HScroll1.Value
    Joystick1.Enabled = True
End Sub

Sub HScroll1_Scroll ()
    Call HScroll1_Change
End Sub

Sub Joystick1_Move (X As Integer, Y As Integer, Z As Integer)
    Label2.Caption = "Position: " & X & ", " & Y
End Sub
```

XMin, XMax, YMin, YMax, ZMin, and ZMax Properties

[See Also](#)

[Example](#)

Description

Returns the full range of the joystick's position.

Usage

*[form.]**[control.]***XMin**

*[form.]**[control.]***XMax**

*[form.]**[control.]***YMin**

*[form.]**[control.]***YMax**

*[form.]**[control.]***ZMin**

*[form.]**[control.]***ZMax**

Remarks

These properties tell you the full range of the joystick's position. They are read-only at run-time only. They are only valid after the joystick has been enabled.

Data Type

Integer (long)

See Also

Properties:

Period

Port

XPos

YPos

ZPos

XPos, YPos, and ZPos Properties

[See Also](#)

[Example](#)

Description

Returns the current position of the joystick.

Usage

*[form.]**[control.]***XPos**

*[form.]**[control.]***YPos**

*[form.]**[control.]***ZPos**

Remarks

These properties tell you where the joystick was at the last time it was polled (see [Period](#)). They are read-only at run-time only. They are only valid after the joystick has been enabled.

Data Type

Integer (long)

See Also

Events:

[Move](#)

Properties:

[Period](#)

[Port](#)

[XMax](#)

[XMin](#)

[YMax](#)

[YMin](#)

[ZMax](#)

[ZMin](#)



Positional Properties Example

In this example, the program will show the changes in the position of the joystick when run. It will also show the relative amount (as compared to XMin, XMax, YMin, and YMax). To try this example, paste the code into the Declarations section of a form that contains two labels and a JoyStk control. Press F5. Then, play with the joystick.

```
Sub Form_Load ()
    Joystick1.Enabled = True
End Sub

Sub Form_Unload (Cancel As Integer)
    Joystick1.Enabled = False
End Sub

Sub Joystick1_Move (X As Integer, Y As Integer, Z As Integer)
    Dim XP As Integer
    Dim YP As Integer

    Label1.Caption = "Position: " & X & ", " & Y

    XP = (100 * (X - Joystick1.XMin)) / (Joystick1.XMax - Joystick1.XMin)
    YP = (100 * (Y - Joystick1.YMin)) / (Joystick1.YMax - Joystick1.YMin)
    Label2.Caption = "Relative: X " & XP & "% Y " & YP & "% "
End Sub
```

Events

All of the events that apply to this control are in this table. Events that have special meaning for this control or that only apply to this control are marked with an asterisk (*).

*ButtonDown

*ButtonUp

*Move

ButtonDown Event

[See Also](#)

[Example](#)

Description

Occurs when the user pushes on one or more of the joystick's buttons.

Syntax

Sub *ctlname*_**ButtonDown** (*Button As Integer*)

Remarks

This event only occurs when a button is pressed. The joystick must be enabled for this event to happen.

Button represents the button pressed.

See Also

Events:

[ButtonUp](#)

Properties:

[Button1](#)

[Button2](#)

[Button3](#)

[Button4](#)

[Buttons](#)

ButtonUp Event

[See Also](#)

[Example](#)

Description

Occurs when the user releases one or more of the joystick's buttons.

Syntax

Sub *ctlname*_**ButtonUp** (*Button As Integer*)

Remarks

This event only occurs when a button is released. The joystick must be enabled for this event to happen.

Button represents the button pressed.

See Also

Events:

[ButtonDown](#)

Properties:

[Button1](#)

[Button2](#)

[Button3](#)

[Button4](#)

[Buttons](#)



Button Event Example

In this example, the labels show which buttons are down and which are up. To try this example, paste the code into the Declarations section of a form that contains two labels and a JoyStk control. Press F5.

```
Sub Form_Load ()
    Joystick1.Enabled = True

    Call JoystickCheck
End Sub

Sub Form_Unload (Cancel As Integer)
    Joystick1.Enabled = False
End Sub

Sub Joystick1_ButtonDown (Button As Integer)
    Call JoystickCheck
End Sub

Sub Joystick1_ButtonUp (Button As Integer)
    Call JoystickCheck
End Sub

Sub JoystickCheck ()
    Dim Up As String
    Dim Down As String

    If Not Joystick1.Button1 Then Up = Up + "1" Else
        Down = Down + "1"
    If Joystick1.Buttons >= 2 Then If Not Joystick1.Button2 Then Up = Up +
        "2" Else Down = Down + "2"
    If Joystick1.Buttons >= 3 Then If Not Joystick1.Button3 Then Up = Up +
        "3" Else Down = Down + "3"
    If Joystick1.Buttons >= 4 Then If Not Joystick1.Button4 Then Up = Up +
        "4" Else Down = Down + "4"

    Label1.Caption = "Up: " & Up
    Label2.Caption = "Down: " & Down
End Sub
```

Move Event

[See Also](#)

[Example](#)

Description

Occurs when the user moves the joystick.

Syntax

Sub *ctlname_Move* (*X As Integer*, *Y As Integer*, *Z As Integer*)

Remarks

This event occurs when the joystick's position changes. The change must be larger than the current setting of the [Threshold](#) property. The joystick must be enabled for this event to happen.

X, Y, and Z represent the joystick's new position (Z is only valid for 3-D joysticks).

See Also

Properties:

Threshold

XPos

YPos

ZPos

Registration Information

Credits

JoyStk was written by Zane Thomas. He can be reached on CompuServe at 72060,3327 or on Internet at 72060.3327@compuserve.com. His mailing address is:

Zane Thomas
Post Office Box 300
Indianola, WA 98342

Inquiries, tech support, comments should be sent to James Shields. His address is 71231,2066 on CompuServe, or mabry@halcyon.com on Internet. If you must send something via U.S. Mail, the address is:

Mabry Software
Post Office Box 31926
Seattle, WA 98103-1926

Registration

You can register this program by sending \$15 (\$17 for international orders) and your address. CompuServe members may register by sending \$10 and their account number (the registered version will be E-mailed to you). CompuServe members may also register this package by going to the SWREG forum. JoyStk is registered there. JoyStk's registration ID number is 1340.

For your convenience, an [order form](#) has been provided that you can print out directly from help.

Source Code and Registration

Source code (which includes a registered copy) to this control is available for \$35 (\$40 for international orders). With source code you get a registered version of the control. If you are a CompuServe member, you may get the source code in the Software Registration forum (GO SWREG) for \$30. Its registration number is 1341.

Credit Card Orders

You can order this program with Mastercard, Visa, American Express, or Discover from Public (software) Library by calling 800-2422-PsL or 713-524-6394 or by FAX to 713-524-6398 or by CompuServe E-mail to 71355,470. You can also mail credit card orders to PsL at Post Office Box 35705; Houston, TX 77235-5705. THESE NUMBERS ARE FOR CREDIT CARDS ONLY.

JoyStk's ID number for this service is 11097. This is good for both the normal registered version, and the source code version.

Any questions about the status of the shipment of the order, refunds, registration options, product details, technical support, volume discounts, dealer pricing, site licenses, etc., must be directed to Mabry Software at 206-634-1443 or FAX at 206-632-0272.

To ensure that you get the latest version, PsL will notify us the day of your order and we will ship the product directly to you.

© Copyright 1993-1994 by James Shields





JoyStk Order Form

Use the Print Topic.. command from the File menu to print this order form.

Mail this form to: Mabry Software
 Post Office Box 31926
 Seattle, WA 98103-1926
 Phone: 206-634-1443
 Fax: 206-632-0272
 BBS: WinDev BBS 206-634-0783
 CompuServe: 71231,2066
 Internet: mabry@halcyon.com

Where did you get this copy of JoyStk?

Ship to:

Phone:

Fax:

E-Mail:

Disk Size: (circle one) 3½ 5¼

qty ordered _____ REGISTRATION
 \$15 each, postpaid (check or money order in hard currency). Foreign
 addresses add \$2.00 shipping. No additional shipping charges to Canada or
 Mexico.

qty ordered _____ SOURCE CODE AND REGISTRATION
 \$35 each, postpaid (check or money order in hard currency). Foreign
 addresses add \$5.00 shipping. No additional shipping charges to Canada or
 Mexico.

Getting Custom Controls Written

If you or your organization would like to have custom controls written, you can contact me at the following:

James Shields
Mabry Software
Post Office Box 31926
Seattle, WA 98103-1926
Phone: 206-634-1443
Fax: 206-632-0272
BBS: WinDev BBS 206-634-0783 (9600 baud, 8,N,1, 24 hours)
CompuServe: 71231,2066
Internet: mabry@halcyon.com

