

*

* Dire Straits Table...

*

1	dsBusError	Bus error
2	dsAddressErr	Address error
3	dsIllInstErr	illegal instruction error
4	dsZeroDivErr	Zero divide error
5	dsChkErr	Check trap error
6	dsOvflowErr	Overflow trap error
7	dsPrivErr	Privilege violation error
8	dsTraceErr	Trace mode error
9	dsLineAErr	Line 1010 trap error
10	dsLineFErr	Line 1111 trap error
11	dsMiscErr	Miscellaneous hardware exception error
12	dsCoreErr	Unimplemented core routine error
13	dsIrqErr	Uninstalled interrupt error
14	dsIOCoreErr	i/o Core Error
15	dsLoadErr	Segment Loader Error
16	dsFPerr	Floating point error
17	dsNoPackErr	Package 0 not present [List Manager]
18	dsNoPk1	Package 1 not present [Reserved by Apple]
19	dsNoPk2	Package 2 not present [Disk Initialization]
20	dsNoPk3	Package 3 not present [Standard File]
21	dsNoPk4	Package 4 not present [Floating-Point Arithmetic]
22	dsNoPk5	Package 5 not present [Transcendental Functions]
23	dsNoPk6	Package 6 not present [International Utilities]
24	dsNoPk7	Package 7 not present [Binary/Decimal Conversion]
25	dsMemFullErr	Out of memory!
26	dsBadLaunch	Can't launch file
27	dsFSerr	File system map has been trashed
28	dsStknHeap	Stack has moved into application heap
30	dsReinsert	Request user to reinsert off-line volume
31	dsNotThe1	Not the disk I wanted (obsolete)
33	negZcbFreeErr	ZcbFree has gone negative
40	dsGreeting	Welcome to Macintosh greeting
41	dsFinderErr	Can't load the Finder error
42	dsBadStartupDisk	Unable to mount boot volume (obsolete)
43	dsSystemFileErr	Can't find System file to open (obsolete)
51	dsBadSlotInt	Unserviceable slot interrupt
81	dsBadSANEopcode	Bad opcode given to SANE Pack4
83	dsBadPatchHeader	SetTrapAddress saw the "come-from" header
84	menuPrgErr	Happens when a menu is purged
85	dsMBarNFnd	SysErr -- cannot find MBDF
86	dsHMenuFindErr	SysErr -- recursively defined HMenus
87	dsWDEFnFnd	Could not load WDEF
88	dsCDEFnFnd	Could not load CDEF
89	dsMDEFnFnd	Could not load MDEF
90	dsNoFPU	FPU instruction executed, but machine has no FPU
98	dsNoPatch	Can't patch for particular Model Mac
99	dsBadPatch	Can't load patch resource
101	dsParityErr	Memory parity error
102	dsOldSystem	System is too old for this ROM
103	ds32BitMode	Booting in 32-bit on a 24-bit sys
104	dsNeedToWriteBootBlocks	Need to write new boot blocks
105	dsNotEnoughRAMToBoot	Need at least 1.5MB of RAM to boot 7.0
20000	dsShutDownOrRestart	User choice between ShutDown and Restart
20001	dsSwitchOffOrRestart	User choice between Switch off or Restart
20002	dsForcedQuit	Allow the user to ExitToShell, return if Cancel
32767	dsSysErr	General system error (catch-all used in DSAT)

-1 smTruncErr/qErr

the truncation indicator alone is wider than the specified width / not in queue

-2 vTypErr
the QType field of an entry in vertical retrace queue isn't vType

-17 controlErr
this driver can't respond to this control call

-18 statusErr
this driver can't respond to this status call

-19 readErr
this driver can't respond to read calls

-20 writeErr
this driver can't respond to write calls

-21 badUnitErr
the driver reference number doesn't match any found in the unit table

-22 unitEmptyErr
the driver reference number specifies NIL handle in unit table

-23 openErr
the requested read/write permission doesn't match driver's open permission or an attempt to open RAM serial driver failed

-24 closeErr
permission to close .MPP driver was denied

-25 dRemovErr
an attempted was made to remove an open driver

-26 dInstErr
the driver could not be found in resource file

-27 abortErr
the I/O request was aborted by KillIO

-28 notOpenErr
the driver isn't open

-33 dirFullErr
the directory is full

-34 dskFullErr
the disk is full

-35 nsvErr
no such volume exists

-36 ioErr
an I/O error occurred

-37 bdNamErr
the specified filename was invalid

-38 fnOpnErr
the specified file is not open

-39 eofErr
the logical end-of-file was reached while reading

-40 posErr
an attempt was made to position before the start of the file

-42 tmfoErr
there are too many files open

-43 fnfErr
the specified file was not found

-44 wPrErr
of a hardware write protect

-45 fLckdErr
of a software file lock

-46 vLckdErr
of a software volume lock

-47 fBsyErr
the file is busy

-48 dupFNErr
a file with the specified name and version already exists

-49 opWrErr
the file is already open for writing via another access path

-50 paramErr
there was an error in the parameter list

-51 rfNumErr

the path reference number specifies a nonexistent access path

-52 gfpErr

there was an error during GetFPos

-53 volOffLinErr

the specified volume is not online

-54 permErr

an attempt was made to open locked file for writing

-55 volOnLinErr

the specified volume is already mounted

-56 nsDrvErr

the specified drive does not exist

-57 noMacDskErr

the disk in the drive is not a Macintosh disk

-58 extFSErr

there was an external file system error

-59 fsRnErr

there was a problem during rename

-60 badMDBErr

the master directory block is corrupted: must reinitialize volume

-61 wrPermErr

the read/write permission doesn't allow writing

-64 noDriveErr

the drive isn't connected

-65 offLinErr

there is no disk in the drive

-66 noNybErr

this disk is probably blank

-67 noAdrMkErr

an address mark could not be found

-68 dataVerErr

read-verify failed

-69 badCksmErr

a bad address mark was encountered

-70 badBtSlpErr

a bad address mark was encountered

-71 noDtaMkErr

a data mark could not be found

-72 badDCksum

a data mark was encountered on the disk

-73 badDBtSlp

a data mark was encountered on the disk

-74 wrUnderrun

a write underrun occurred

-75 cantStepErr

the drive can't step (Sounds bad)

-76 tk0BadErr

track zero could not be found on the disk (Sounds very bad)

-77 initlWMErr

the disk controller chip could not be initialized

-78 twoSideErr

someone tried to read side two of a disk in a single-sided drive

-79 spdAdjErr

the disk speed could not be adjusted correctly

-80 seekErr

Drive error

-81 sectNFErr

the sector could not be found

-85 clkRdErr

the clock could not be read

-86 clkWrErr

the time written to the clock chip did not verify

-87 prWrErr

parameter RAM written did not verify
-88 printErr
the validity status was not \$A8
-89 rcvrErr user aborted serial transfer
-90 TransTimeout Transputer communications timeout
-91 ddpSktErr
there was an error opening socket
-91 eMultiErr
an address was invalid or the table was full
-92 eLenErr
the packet is too large or the first entry of the write-data structure did not contain the full 14-byte header
-93 noBridgeErr
no router is available
-94 LAPPotErr
a protocol handler is already attached, a node's protocol table is full, no protocol is attached, or protocol handler
pointer was not NIL
-95 excessCollsns
there was a hardware error
-100 noScrapErr
the desk scrap is not initialized
-102 noTypeErr
there is no data of the requested type
-108 memFullErr
there is insufficient memory left in the heap zone
-109 nilHandleErr
a master pointer was NIL
-110 nilPtrErr
a pointer was NIL (returned by FailNil)
-111 memWZErr
an attempt was made to operate on a free block
-112 memPruErr
an attempt was made to purge a locked block
-117 memLockedErr
the block is locked
-120 dirNFEr
the directory was not found
-123 wrgVolTypeErr
this volume is not an HFS volume
-128 userCanceledErr
the operation was aborted
-147 regionTooBigError
the region is too large or complex
-148 pixmapTooDeepErr
the pixel map record is deeper than 1 bit per pixel
-149 mfStackErr
there is insufficient stack space
-157 cDepthErr
the requested pixel depth is invalid
-188 resourceInMemory
the resource is already in memory
-189 writingPastEnd
the program tried to write past the end of the file
-190 inputOutOfBounds
the offset or count was out of bounds
-192 resNotFound
a resource was not found
-193 resFNotFound
the resource file was not found
-194 addResFailed
AddResource failed
-196 rmvResFailed
RmveResource failed

- 199 mapReadErr
the map is inconsistent with operation
- 200 noHardwareErr
the required hardware is not available
- 201 notEnoughHardwareErr
insufficient hardware is available
- 203 queueFull
there is no room in the queue
- 204 resProblem
there was a problem loading a resource
- 205 badChannel
the sound channel is corrupt or unusable
- 206 badFormat
the resource is corrupt or unusable
- 207 notEnoughBufferSpace
there is insufficient memory available
- 208 badFileFormat
the file is corrupt or unusable, or not AIFF or AIFF-C
- 209 channelBusy
the sound channel is busy
- 210 buffersTooSmall
the buffer is too small
- 211 channelNotBusy
the sound channel not currently used
- 212 noMoreRealTime
not enough CPU time available to process the command in real time
- 213 badParam
a parameter is incorrect
- 220 siNoSoundInHardware
there is no sound input hardware available
- 221 siBadSoundInDevice
the sound input device requested was invalid
- 222 siNoBufferSpecified
no buffer was specified
- 223 siInvalidCompression
the compression type is invalid
- 224 siHardDiskTooSlow
the hard drive is too slow to record
- 225 siInvalidSampleRate
the requested sample rate is invalid
- 226 siInvalidSampleSize
the requested sample size is invalid
- 227 siDeviceBusyErr
the sound input device is busy
- 228 siBadDeviceName
the sound input device name was invalid
- 229 siBadRefNum
the sound input device reference number was invalid
- 230 siInputDeviceErr
a sound input device hardware error
- *
- * Speech Manager...
- *
- 231 siUnknownInfoType
an unknown type of information was requested
- 232 siUnknownQuality
an unknown recording quality was requested
- 240 noSynthFound Could not find the specified speech synthesizer
- 241 synthOpenFailed Could not open another speech synthesizer channel - Try increasing the application memory
- 242 synthNotReady Speech synthesizer is still busy speaking
- 243 bufTooSmall Output buffer is too small to hold result
- 244 voiceNotFound Voice resource not found

- 245 incompatibleVoice Specified voice cannot be used with synthesizer
- 246 badDictFormat Format problem with pronunciation dictionary
- 247 badInputText Raw phoneme text contains invalid characters

- 299 nmTypErr
qType was something other than nmType
- 308 smUnExBusErr
of an unexpected bus error
- 330 smBadRefId
the reference ID was not found in list
- 331 smBadsList
the sResource structure was bad; ID1 < ID2 < ID3...
- 332 smReservedErr
a reserved field not zero
- 338 smSelOOBErr
the selector was out of bounds; function not implemented
- 344 smNoMoresResources
the specified sResource data structure was not found
- 346 smBadsPtrErr
an invalid pointer was passed to sCaldSPointer function
- 347 smByteLanesErr
the ByteLanes field in card's format block was zero
- 450 editionMgrInitErr
the Edition Manager is not initialized or could not be loaded
- 451 badSectionErr
the section type was invalid
- 452 notRegisteredSectionErr
this section is not registered
- 454 badSubPartErr
the edition container spec or the edition container was invalid
- 460 multiplePublisherWrn
another publisher is already registered to this edition
- 461 containerNotFoundWrn
the alias was not resolved
- 463 notThePublisherWrn
another publisher wrote this edition
- 500 rgnTooBigErr
the bitmap would convert into a region larger than 64KB
- 600 procNotFound
there is no eligible process with the specified process serial number
- 601 memFragErr
there is not enough room to launch application with special requirements
- 602 appModeErr
the memory mode is 32-bit, but the application being launched is not 32-bit clean
- 605 appMemFullErr
the partition size specified in 'SIZE' resource is not big enough for launch
- 606 AppIsDaemon
this application is background-only
- 607 bufferIsSmall
the buffer is too small
- 608 noOutstandingHLE
there is no outstanding high-level event
- 609 connectionInvalid
the connection is invalid
- 610 noUserInteractionAllowed
no session is established, and there was an attempt to PostHighLevelEvent from an application in the background
- 620 notEnoughMemoryErr
there is insufficient physical memory
- 621 notHeldErr
the specified memory range is not held
- 622 cannotMakeContiguousErr
the specified memory range could not be made contiguous

-623 notLockedErr
the specified range of memory is not locked

-624 interruptsMaskedErr
a Virtual Memory function was called with interrupts masked

-625 cannotDeferErr
additional user functions cannot be deferred

-800 rcDBNull
the data item was NULL

-801 rcDBValue
the data was available or successfully retrieved

-802 rcDBError
there was an error executing the function

-803 rcDBBadType
the next data item not of requested data type

-804 rcDBBreak
the function timed out

-805 rcDBExec
the query is currently executing

-806 rcDBBadSessID
the session ID is invalid

-807 rcDBBadSessNum
the session number is invalid

-808 rcDBBadDDev
the specified database extension could not be found, or error occurred while opening database extension

-809 rcDBAsyncNotSupp
the database extension does not support asynchronous calls

-810 rcDBBadAsyncPB
the specified parameter block was invalid

-811 rcDBNoHandler
there is no handler for this data type installed for the current application

-812 rcDBWrongVersion
the version number is incorrect

-813 rcDBPackNotInited
the InitDBPack function has not yet been called

-850 hmHelpDisabled
Help balloons are not enabled

-853 hmBalloonAborted
constant cursor movement prevented the help balloon from being displayed

-854 hmSameAsLastBalloon
the Menu and item are same as previous menu and item

-855 hmHelpManagerNotInited
the Help menu is not set up

-857 hmSkippedBalloon
there is no balloon content to fill in

-858 hmWrongVersion
the version of Help Manager resource is incorrect

-859 hmUnknownHelpType
the Help message record contained a bad type

-861 hmOperationUnsupported
the Help Manager method parameter is invalid

-862 hmNoBalloonUp
no balloon is showing

-863 hmCloseViewActive
"Close View" is active and preventing the removal of the Help Balloon

-900 notInitErr
the PPC Toolbox has not been initialized yet

-902 nameTypeErr
the locationKindSelector in location name was invalid or inappropriate

-903 noPortErr
the port name was invalid; unable to open port or bad port reference number

-904 noGlobalsErr
the System was unable to allocate memory—critical error

-905 localOnlyErr
network activity is currently disabled

-906 destPortErr
the specified port does not exist on the destination machine

-907 sessTableErr
the PPC Toolbox was unable to create a session

-908 noSessionErr
the session reference number was invalid

-909 badReqErr
of a bad parameter or invalid state

-910 portNameExistsErr
another port is already open with this name

-911 noUserNameErr
the destination machine did not recognize the User name

-912 userRejectErr
the destination rejected the session request

-915 noResponseErr
the application could not be contacted

-916 portClosedErr
the port was closed

-917 sessClosedErr
the session has closed

-919 badPortNameErr
the PPC port record is invalid

-922 noDefaultUserErr
the owner name in the "Sharing Setup" control panel has not been specified yet

-923 notLoggedInErr
the default user reference number does not yet exist

-924 noUserRefErr
a new user reference number could not be created

-925 networkErr
an error occurred in the network

-926 noInformErr
the target application did not have an inform pending

-927 authFailErr
the password entered was incorrect

-928 noUserRecErr
the user reference number was invalid

-930 badServiceMethodErr
the service method is something other than ppcServiceRealTime

-931 badLocNameErr
the location name is invalid

-932 guestNotAllowedErr
the destination port does not allow guest access; authentication is required

-1027 nbpDuplicate
the NBP name exists already

-1096 reqFailed
the request to contact router failed (retry count exceeded)

-1102 cbNotFound
the control block was not found (there were no pending asynchronous calls)

-1105 reqAborted
this ERead was aborted by the ERdCancel function

-1273 errOpenDenied
the open request was denied by recipient

-1274 errDSPQueueSize
the send or receive queue is too small

-1275 errFwdReset
read was terminated by forward reset

-1276 errAttention
the attention message was too long

-1277 errOpening
the attempt to open the connection failed

-1278 errState
the connection state for this operation is invalid

-1279 errAborted
the request was aborted by the dspRemove or dspClose function

-1280 errRefNum
the connection reference number was invalid

-1300 fidNotFoundErr
the file ID was not found

-1302 notAFileErr
the specified file is actually a directory

-1303 diffVolErr
the files are on different volumes

-1304 catalogChangedErr
the catalog has changed and CatPosition may be invalid

-1305 desktopDamagedErr
the desktop database has become corrupted

-1700 errAEC coercionFail
the AppleEvent data could not be coerced to the requested descriptor type

-1701 errAEDescNotFound
the descriptor record was not found

-1702 errAECorruptData
the data in an AppleEvent could not be read

-1703 errAEWrongDataType
the wrong descriptor data type was requested

-1704 errAENotAEDesc
the descriptor record is invalid

-1705 errAEBadListItem
the list item was invalid

-1706 errAENewerVersion
a newer version of the AppleEvent manager is required

-1707 errAENotAppleEvent
the event is not an AppleEvent

-1708 errAEEventNotHandled
the event wasn't handled by any AppleEvent handler

-1709 errAEReplyNotValid
AEResetTimer was passed an invalid reply

-1710 errAEUnknownSendMode
an invalid sending mode was requested

-1711 errAEWaitCanceled
the wait loop for reply or receipt was canceled

-1712 errAETimeOut
the AppleEvent timed out (YOU should be using the Futures package!)

-1713 errAENoUserInteraction
no user interaction is allowed

-1714 errAENotASpecialFunction
the wrong keyword for a special function was specified

-1715 errAEParamMissed
the AppleEvent handler did not get all of the required parameters

-1716 errAEUnknownAddressType
the AppleEvent address type is unknown

-1717 errAEHandlerNotFound
no handler was found for an AppleEvent or a coercion handler

-1718 errAEReplyNotArrived
the AppleEvent reply has not yet arrived (YOU should be using the Futures package!)

-1719 errAEIllegalIndex
the list index was invalid

-2700 threadsNotInitErr
the Threads package has not been initialized

-2701 badThreadErr
the ThreadHandle was invalid

-2702 threadsNotAvailableErr
the Threads package is not available

-2703 wrongThreadsVersErr
the Threads package that is installed is incompatible with the threads Glue being used
-3000 ??? Invalid SpeechChannel parameter
-3101 buf2SmallErr
the packet was too large for buffer; partial data was returned

*

* Print Manager w/LaserWriter

*

-4096 ??? No free Connect Control Blocks available
-4097 ??? Bad connection reference number
-4098 ??? Request already active
-4099 ??? Write request too big
-4100 ??? Connection just closed
-4101 ??? Printer not found, or closed

-5012 afpItemNotFound
AFP information not found
-5030 afpIconTypeError
the size of new icon and one it replaces don't match
-5550 gestaltUnknownErr
the Gestalt response could not be obtained
-5551 gestaltUndefSelectorErr
the Gestalt selector requested was undefined
-5552 gestaltDupSelectorErr
the Gestalt selector already exists
-5553 gestaltLocationErr
the Gestalt selector function is not in the system heap
-11000 pictInfoVersionErr
the PICT version number is not zero
-11001 pictInfoIDErr
the PictInfo ID is invalid
-11002 pictInfoVerbErr
an invalid verb combination was specified in the PICT
-11003 cantLoadPickMethodErr
the custom pick method is not in the resource chain
-11004 colorsRequestedErr
the number of colors requested is out of range or greater than passed to NewPictInfo
-11005 pictureDataErr
the picture data is invalid
-13000 pmBusyErr
the Power Manager IC is stuck busy
-13001 pmReplyTOErr
of a timeout waiting to begin reply handshake
-13002 pmSendStartErr
the Power Manager IC did not start handshake
-13003 pmSendEndErr
the Power Manager did not finish handshake during send
-13004 pmRecvStartErr
the Power Manager did not start handshake during receive
-13005 pmRecvEndErr
the Power Manager did not finish handshake during receive

*

* Following line is the end of the table...

*

-32767 generalErr
End of table marker (not a real error)