

Negative I.D. Codes

SysEnvirons Errors

-5500

envNotPresent

SysEnvirons trap not present - returned by

glue.
-5501

envBadVers

Version non-positive
-5502

envVersTooBig

Version bigger than call can handle

Gestalt Errors

-5550

gestaltUnknownErr Could not obtain the response
-5551

gestaltUndefSelectorErr Undefined selector
-5552

gestaltDupSelectorErr Selector already exists
-5553

gestaltLocationErr Function not in system heap

LaserWriter Driver Errors

-8132

????

Manual Feed time out
-8133

????

General PostScript Error
-8150

????

No LaserWriter chosen
-8151

????

Version mismatch between LaserPrep

dictionaries
-8150

????

No LaserPrep dictionary installed
-8160

????

Zoom scale factor out of range

PictInfo Errors

-11000

pictInfoVersionErr Version number not zero
-11001

pictInfoIDErr Invalid PictInfo ID
-11002

pictInfoVerbErr Invalid verb combination specified
-11003

cantLoadPickMethodErr Custom pick method not in resource

chain
-11004

colorsRequestedErr Number out of range or greater than

passed to NewPictInfo
-11005

pictureDataErr Invalid picture data

Power Manager Errors

-13000

pmBusyErr

Power Manager IC stuck busy
-13001

pmReplyTOErr

Timed out waiting to begin reply

handshake
-13002

pmSendStartErr

Power Manager IC did not start handshake
-13003

pmSendEndErr

During send, Power Manager did not finish

handshake
-13004

pmRecvStartErr

During receive, Power Manager did not

start handshake
-13005

pmRecvEndErr

During receive, Power Manager did not

finish handshake

MacTCP Errors

-23000

ipBadLapErr	Bad network configuration
-23001	

ipBadCnfgErr	Bad IP configuration error
-23002	

ipNoCnfgErr	Missing IP or LAP configuration error
-23003	

ipLoadErr	Error in MacTCP load
-23004	

ipBadAddr	Error in getting address
-23005	

connectionClosing	Connection in closing
-23006	

invalidLength	
-23007	

connectionExists	Request conflicts with existing
------------------	---------------------------------

connection
-23008

connectionDoesntExist Connection does not exist
-23009

insufficientResources Insufficient resources to perform

request
-23010

invalidStreamPtr
-23011

streamAlreadyOpen
-23012

connectionTerminated
-23013

invalidBufPtr
-23014

invalidRDS
-23014

invalidWDS
-23015

openFailed
-23016

commandTimeout
-23017

duplicateSocket
-23030

ipOpenProtErr Can't open new protocol, table full
-23031

ipCloseProtErr Can't find protocol to close
-23032

ipDontFragErr Packet too large to send w/o fragmenting
-23033

ipDestDeadErr Destination not responding
-23034

ipBadWDSerr Error in WDS format
-23035

icmpEchoTimeoutErr ICMP echo timed-out
-23036

ipNoFragMemErr No memory to send fragmented pkt
-23037

ipRouteErr Can't route packet off-net
-23041

nameSyntaxErr
-23042

cacheFault
-23043

noResultProc
-23044

noNameServer
-23045

authNameErr

-23046

noAnsErr
-23047

dnrErr
-23048

outOfMemory

Slot Manager Primary or Secondary Init Code Errors
-32768

svTempDisable

Temporarily disable card but run primary

init
-32640

svDisabled

Reserve -32640 to -32768 for Apple temp

disablesInternal

Didn't know the error codes went down that low, did you?