

# NEXTSTEP for Intel Processors Release 3.3

## Display Driver Overview

**Driver:** Number Nine GXE Family

**Driver Overview:** NeXTanswer #1796

**Last Update:** April 23, 1997

## Availability Information

**A version of this driver is on the CDROM**

**Newer Released Driver in NeXTanswers\*:** No, Version 0.00, as NeXTanswer #

**Newer Beta Driver in NeXTanswers\*:** No, Version 0.00, as NeXTanswer #

**Driver Name / Installer .pkg:** Number9

**Driver Type:** Display

**Driver Scope:** Product Family

**Supported Components:** AT&T ATT20C505 RAMDAC, Brooktree Bt484 RAMDAC, Brooktree Bt485 RAMDAC, Brooktree Bt485A RAMDAC, S3 928, S3 928P, TI TVP3020 RAMDAC

**PC Bus / Interface Supported by Driver\*\*:** PCI, VL-Bus

**General Overview notes:** This driver is obsolete, and has been replaced by the S3GenericDisplay Driver. See NeXTanswer #1737\_S3\_Generic\_Driver\_Overview.rtf

This new Number 9 GXE graphics driver is designed to support a variety of VL-Bus and PCI graphics adapters from Number 9. These cards use the S3-928 graphics controller and support 1MB, 2MB or 4MB of video frame buffer. Some versions of these adapters also support an optional additional 1MB of off screen memory, not required by NEXTSTEP. This version of the driver only supports 1MB, 2MB or 4MB of VRAM.

**Supported Products / Add-on Adapters:**

#9GXE-VL Level 10 (VL-Bus, 1MB VRAM) - not tested, but should work

#9GXE-VL Level 11 (VL-Bus, 2MB VRAM)

#9GXE-VL Level 12 (VL-Bus, 2MB VRAM) - not tested, but should work

#9GXE-VL Level 14 (VL-Bus, 4MB VRAM) - not tested, but should work  
#9GXE-VL Level 16 (VL-Bus, 4MB VRAM) - not tested, but should work  
#9GXE-PCI Level 10 (PCI, 1MB VRAM) - not tested, but should work  
#9GXE-PCI Level 12 (PCI, 2MB VRAM)

**Supported Products / Systems (ie integrated into PC System):**

**Special Features of Driver / Driver Notes:**

# Display Driver Details

**Supported Connectors:** 15-pin High Density (VGA)  
**Access Mode:** Linear Framebuffer  
**Adapter Memory:** 1MB VRAM, 2MB VRAM, 4MB VRAM

**Display Modes (Number in () after resolution indicates frame buffer size required)**

**32 Bit Color Modes\*\*:**  
1024x768 (4MB+), 640x480 (2MB+), 800x600 (2MB+)

**16 Bit Color Modes\*\*:**  
1024x768 (2MB+), 1152X819 (4MB+), 1280x1024 (4MB+), 640x480 (1MB+), 800x600 (1MB+)

**8 Bit Color / Greyscale Modes\*\*:**  
1024x768 (1MB+), 1152X819 (1MB+), 1280x1024 (2MB+), 1600x1200 (4MB+), 800x600 (1MB+)

# Known Problems

# Driver Version Notes

## Future Planning

**Future / Update Planning:**   Obsolete  
**Reason for New Driver / Update:**  
**New Driver / Update Timeframe:**

**New Driver / Update Description:**

**Note:** Information contained in the "Future Planning" section of this document does not constitute a commitment on the part of NeXT to complete the planned development work.

- \* - Any NeXTanswer number that is blank indicates that a driver will not be released for this version of NEXTSTEP.
- \*\* - Indicates information that is inclusive of the entire capability of this driver. Not all devices supported by this driver may include all features listed. Check any available NeXTanswers and the hardware manual for the device for additional information.

## Product Vendor

Number Nine Visual Technology  
18 Hartwell Avenue  
Lexington, MA 02173-3103  
  
Voice: (617) 674-0009  
FAX: (617) 674-2919  
BBS: (617) 862-7502 (8/1/N, up to 28kbps)  
URL: <http://www.nine.com>