# Windows NT 4.0 Off-Campus Connection

Version 1.0
James Madison University


Figure 1

**Figure 1. The Desktop Window**

Double-click the *My Computer* icon on the desktop


Figure 2

**Figure 2.  The My Computer Window**

Double-click *Dial-Up Networking*.  Proceed to **Step 5** if you already have your modem installed or Remote Access software installed.


Figure 3

**Figure 3. The Dial-Up Networking Window**

You will need your Windows NT CD-ROM to install the dial-up networking software.  Click **Install.**

**Files Needed**

Some files on (Unknown) are needed.

OK

Cancel

Insert (Unknown) into the drive selected below, and then click OK.

Skip File

Copy files from:

D:\I386\

Browse...

Figure 3a

**Figure 3a.  Location of files**

Enter the location of your CD-ROM drive and the directory 'I386'. For example if your CD-ROM drive is D, you would enter 'd:\i386'

---

**Remote Access Setup**

There are no RAS capable devices to Add. Do you want RAS setup to invoke the Modem installer to enable you to add a modem?

Yes    No

Figure 3b

**Figure 3b.  Modem Setup**

You will only get this message if a modem has not been setup on your computer.  Click *Yes*

---

**Install New Modem**

Windows NT will now try to detect your modem.  Before continuing, you should:

1. If the modem is attached to your computer, make sure it is turned on.

2. Quit any programs that may be using the modem.

Click Next when you are ready to continue.

☐ Don't detect my modem; I will select it from a list.

< Back    Next >    Cancel

Figure 3c

**Figure 3c. Choosing a new modem**

Leave the box *"Don't detect my modem; I will select from a list"* unchecked and click **Next** to let Windows NT to search for your modem.  If you have a driver disk for your modem or want to select from a list then go to the **Troubleshooting section**

Figure 3d

**Figure 3d.  Installing the modem**

The following window should display your modem.
Click **Next**.

Click *Change* if you modem listed is incorrect and
go to the **Troubleshooting Section**.



Figure 3e

**Figure 3e.  Save modem settings**

Your modem has been successfully setup.  Click
**Finish** to complete the modem installation



Figure 3f

**Figure 3f. Adding a RAS device**
Select your modem  and click *OK*

Figure 3g

**Figure 3g.  Selecting a Modem**
Select your modem and click *Continue*

Figure 3h

**Figure 3h.  Restarting the computer**
Remote Access and Dial-Up Networking has now been successfully installed.  Click *Restart*.  Redo Step 1 and 2, then skip to Step 5.

Figure 5

**Figure 5.** Click **New**

Figure 5a

**Figure 5a. New Phonebook entry**
Type 'CampusNet' in the field provided. Click *Next*

Figure 5b

**Figure 5b. Server Settings**

Check *"I am calling the Internet",* and *"Send plain text password if that's the only way to connect"* by clicking on the boxes.

 **Make sure that the third option remains unchecked**.

Click *Next*

Figure 5c

**Figure 5c. Setup the Phone number**

The dial-up number for CampusLink is 574-9600. Enter this into the field provided. Click *Next*

Figure 5d

**Figure 5d.  Save Phonebook Entry**
Click *Finish* to save your new Phonebook entry.



Figure 6

**Figure 6. Dial-Up**
The standard Dial-Up Networking dialog box will come up.  This is the window that will appear each time you open *Dial-Up Networking* from now on

Click *Dial*



Figure 7

**Figure 7.  Connecting to CampusNet**
Enter your *userid* and *password* in the corresponding fields.  You do not need to enter anything into the *Domain* field.  Click *OK* to establish your connection.