

Dear *READER*

These are the configuration details to connect to **SERVELAN**, for your 30 day trial.

Please read them carefully.

The software you will be using is **NETMANAGE'S SAMPLER CHAMELEON**.

You will only have to make two changes within the CUSTOM utility.

- 1) The PHONE NUMBER of the Point Of Presence, (see the readme for a list.)
 - 2) Possibly your default modem settings.
- There is a DEFAULT modem setting, which works with MOST HAYES compatible modems.
- Unfortunately Leaf Distribution cannot help you with your modem settings.
- There is NO E-MAIL or NEWS GROUP access with this offer, access is allowed to SERVELAN SUBSCRIBERS ONLY.

CHAMELEON SAMPLER is **SHAREWARE** and is **NOT** supported by Leaf Distribution, we will however help you to CONNECT to SERVELAN.
See the file readme file for info on **UPGRADE** paths to a fully supported Chameleon package.

Before you install the software, please read the SERVELAN.WRI on the CD-ROM for some helpful hints and tips.

Should you require assistance during your **CONNECTION**, please contact Leaf Distribution technical support on 01256 707777, where our support professionals are on hand to help you.

Leaf Distribution is an Authorised **NETMANAGE** Distributor.
SERVELAN IS A SERVICE OF LEAF DISTRIBUTION LIMITED.

CUSTOM

CUSTOM, SETUP, PORT

(This is a default setting for a normal 14.400 modem on com port 2, this may need changing, please consult your modem manual)

CUSTOM, SETUP, MODEM

(This is the default settings for a HAYES compatible modem, to change or add more settings, please consult your modem manual.)

-- Dial Settings

Dial :

Timeout if Not Connected in seconds

☐ Redial After Timing Out ☐ Signal When Connected

☐ Redial After Carrier Is Lost ☒ Open Log When Connecting

OK CANCEL

CUSTOM, SETUP, DIAL

(Please select your P.O.P. (point of presence) from the list in the readme, and enter the number here.)

****IMPORTANT**** Please SAVE the configuration and EXIT, then close any other Netmanage applications that are running.

When you now select the CUSTOM application, the word "connect" is now available, please follow these next few steps, to connect to the Internet.

Select the CUSTOM application, and the select "setup" and then select "log" (You will now see an additional "window" appear, move it out of the way.)

Select the word "connect" in the Custom application.

In your "log window", you should see something SIMILAR to the following.....

ATQ0V1E0M1 <=== This is the modem string that was configured
OK <=== This is you modem responding with OK
ATS0=0 <=== This is the other modem string that was configured
OK <=== This is your modem responding with OK
ATDT01223258026 <=== This should be the phone number you put in.

CONNECT 14400 <=== This is your modem connecting to the INTERNET

login:lfdpcplus <=== This is the login and the login name
lfdpcplus <=== This is an echo of the login name
Password:**** <=== This is the encrypted password

Protocol:PPP
PPP
Enabled IPCP address negotiation for lfdpcplus-lfdp <=== This is the Internet talking to your modem
Packet mode enabled <=== This means you are connected.
~_}#+!}!} } }8}

After a few seconds, the word "connect" should change to "disconnect".
When it does, you are connected and ready to discover the INTERNET.

MINIMISE the "custom" application, DO NOT CLOSE IT DOWN.

Select the "ping" application, and select the word "settings"
Select the word "preferences"
Click in the blank box "continuous" (an X will appear)
Click in the box "Interval (sec)" and change this from 1 to 100)
Click in the box "Timeout (sec)" and change this from 6 to 15)
Select "OK"
Select the word "Start"
You will see a blank box named "host".
In the blank box, type in, ftp.pipex.net
Select OK.
You should see something SIMILAR to the following...

Look at the bottom right and it will tell you the percentage of loss. (0 is no loss)

You are now communicating on the INTERNET.
MINIMISE the ping application.

If you wish to pick up a Web Browser like NetScape, you will have to use the FTP application.

**Follow these steps to use the FTP application.
Select the FTP application.**

**Select the "binary" option.
Select the word "settings".
Select the word "log". (A window will appear as it did with custom, move it out of the way)
Select the word "connect".
You will now see the following...**

**In the blank box "host", type in the site of your choice, from the readme.
In the blank box "user" ALWAYS type in anonymous.
In the blank box marked "password" ALWAYS type in pcplus@
Then select OK.
The log will then tell you what is happening.
NOTE: Not all sites are available all the time, so pay close attention to the log.**

When connected you should see four filled boxes, and the word "connect" changes to "disconnect".

The two boxes on the left (top and bottom) is your local drive.
The two boxes on the right (top and bottom) is the remote site.
The "directories" are in the top two boxes.
The "files" are in the bottom two boxes.
You can change remote directories by double clicking on the directory you want to go into.
When you see a file that you want on the remote site, click once on it to highlight it.
Click on the arrow pointing LEFT of the word "copy".
Another box will open, showing you the progress of you copy.
When finished, you will see the file on the left, bottom box, thus indicating that the file was copied to your local drive.

This is what I would do if I were to pick up the NetScape file, from the site "ftp.mcom.com".

```
"host",          ftp.mcom.com
"user"           anonymous
"password" pcplus@
Then select OK.
```

When connected double click on the top right box on the directory named "netscape"
Then double click on the top right box on the directory named "windows"
Then single click on the bottom right box and highlight the file named "n16e11n.exe"
Then click the arrow to the left of the word "copy"
Wait until the file has been transferred.
Select the "disconnect" button in the FTP application.

To END your session on the INTERNET...

Close down the FTP application and save the changes.

Close down the PING application and save the changes

Maximise "custom" and select the word "disconnect" (after a few seconds the word "disconnect" will change to "connect")

Close down the CUSTOM application and save the changes.

**Enjoy your 30 day connection to the Internet, brought to you by
*SERVELAN and LEAF DISTRIBUTION LIMITED.***