

Error Message Explanations

This lists all error messages originating in the Windows NetWare Administrator that are prefixed by NWDxxx.

Many of these errors are caused by [insufficient workstation memory](#).

Select the error number below to see an explanation of the error and action you can take to correct the error.

If you know the error number, you can also choose the Search button in the Help window to search for that error.

[97](#)

[98](#)

[102](#)

[106](#)

[112](#)

[119](#)

[511](#)

[512](#)

[513](#)

[514](#)

[515](#)

[516](#)

[517](#)

[518](#)

[519](#)

[520](#)

[521](#)

[522](#)

[523](#)

[524](#)

[525](#)

[526](#)

[527](#)

[528](#)

[539](#)

[540](#)

[551](#)

[552](#)

[553](#)

[554](#)

[556](#)

[560](#)

[561](#)

[772](#)

[783](#)

[784](#)

[785](#)

[786](#)

[787](#)

[788](#)

[1006](#)

[1007](#)

[1009](#)

[1010](#)

[1011](#)

[1012](#)

1013
1014
1015
1018
1019
1021
1022
1023
1024
1049
1051
1079
1084
1085
1086
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178

1250
1251
1322
1329
1350
1351
1352
1353
1356
1361
1362
1363
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1458
1459
1460
1461
1463
1464
1469
1470
1471
1472
1473
1479
1480
1481
1482
1483
1484
1485
1489
1490

1491
1492
1493
1494
1495
1496
1499
1500
1501
1675
1676
1677
1678
1679
1685
1686
1687
1688
1689
1690
1691
1692
1694
1695
1696
1697
1705
1706
1710
1711
1712
1713
1714
1715
1716
1720
1721
1732
1733
1736
1737
1741
1742
1743
1752
1850
1851
1852
1853
1854
1855
1856
1857
1858
1980
1981

1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
16385
16386
16387
16388
16389
16390
16391
16392
16395
16396
16397
16398
16400
16405
16408
16410
16411
16412
16413
16414
16417
16418
16419
16420
16421
16423
16440

Insufficient Workstation Memory

To resolve an insufficient workstation memory error, you should add more memory by installing a larger memory board. To temporarily free memory, do one or more of the following:

- * Close some browser windows and other open MS Windows applications.
- * Unload any unneeded TSR (terminate-and-stay-resident) programs.
- * Modify CONFIG.SYS to reduce the number of files that can be open at the same time, the number of buffers allocated for disk drives, and the memory size allocated by the shell for your DOS environment (the /E option). The following settings are sufficient for normal workstation operation, but the values can be reduced further until problems occur:

```
FILES=20
```

```
BUFFERS=20
```

```
SHELL=C:\COMMAND.COM /E:640 /P
```

You must reboot your machine after modifying the CONFIG.SYS file.

You may need to close the NetWare Administrator and reopen it to continue.

97: The menu being duplicated has become corrupt. Exit this application and start over.

Explanation

While preparing menus for display, part of the screen data was corrupted. The data is probably intact, but you may not be able to see it.

Action

Exit the utility as soon as possible and restart it.

98: The system does not have enough memory to duplicate a menu.

Explanation

The utility has run out of memory while preparing menus for display. Data may display improperly, though it is not corrupted.

Action

See Resolving Workstation Memory Problems in *Supervising the Network*.

102: The NetWare Administrator and its views are out of memory.

Explanation

The utility has run out of memory and may not be able to continue.

Action

See Resolving Workstation Memory Problems in *Supervising the Network*.

106: The new procedure <name> cannot be located in the <filename> file. Your Path variable is invalid or your DLLs are corrupted.

Explanation

A procedure that was needed to complete a requested action is not available to the utility. The utility attempted to load the procedure from another file, and that file was not available. Some of the NetWare Administrator's files are missing or corrupted.

Action

Make sure that the files are available on search drives. Recopy the NetWare Administrator and its associated files to your work area (probably the PUBLIC directory) from the original NetWare CD-ROM or diskettes.

112: The dynamic link library <filename> cannot be located. Your Path variable is invalid or your DLLs were not installed correctly.

Explanation

A file that was needed to complete a requested action is not available to the utility. One of the NetWare Administrator's files is missing or corrupted.

Action

Make sure that the files are available on search drives. Recopy the NetWare Administrator and its associated files to your work area (probably the PUBLIC directory) from the original NetWare CD-ROM or diskettes.

119: The NetWare Administrator has run out of memory. Terminate some applications, free some space on your swap disk, or run NetWare Administrator on a computer with more memory.

Explanation

The utility has run out of memory and may not be able to continue.

Action

See Resolving Workstation Memory Problems in *Supervising the Network*. You may need to close the utility and reopen it to continue.

511: An error occurred during an attempt to initialize the Trustees dialog.

Explanation

The Trustee List dialog cannot be opened. There may not be enough memory.

Action

Close and reopen the current dialog. Increase the available memory. See Resolving Workstation Memory Problems in *Supervising the Network*. If the problem persists, contact your Novell Authorized Reseller.

512: An error occurred during an attempt to write changes to the trustee list.

Explanation

Changes to the trustee list or to trustee's rights could not be saved to the Directory database. NetWare Directory Services may not allow access at the moment, or the new data may be corrupted.

Action

Close and reopen the dialog before reentering the information.

513: An error occurred during an attempt to delete the trustees.

Explanation

The selected trustee cannot be deleted. One of the following may have occurred:

- * NetWare Directory Services received a command it did not understand.
- * The object has subordinates.
- * The name of the object is invalid for NetWare Directory Services.
- * The request was corrupted.

Action

Check each of the above problems; then do the operation again.

514: An error occurred during an attempt to delete a trustee's rights.

Explanation

The rights granted to the selected trustee could not be deleted. Either NetWare Directory Services did not understand the request because it was corrupted, or the trustee information has been stored incorrectly.

Action

Close and reopen the dialog. You may also do the operation from another workstation.

515: An error occurred during an attempt to add trustees.

Explanation

New trustees could not be added to the trustee list. One of the following may have occurred:

- * The workstation may not have enough available memory for MS Windows to add to the list.
- * The trustee list may be corrupted.
- * The names of the new trustees returned by NetWare Directory Services may not be accurate.

Action

See Resolving Workstation Memory Problems in *Supervising the Network*. Do the operation again. If the problem persists, contact your Novell Authorized Reseller.

516: An error occurred during an attempt to get trustee rights data.

Explanation

The rights granted to the selected trustee could not be found. NetWare Directory Services may have returned incorrect information, or the name of the trustee may be corrupted in memory.

Action

Close and reopen the current dialog.

517: An error occurred during an attempt to set trustee rights data.

Explanation

New rights for the trustee could not be set. MS Windows may be unable to allocate enough memory to save the information, or the trustee or request to change rights may be corrupted and unreadable.

Action

See Resolving Workstation Memory Problems in *Supervising the Network*. Do the operation again. If the problem persists, contact your Novell Authorized Reseller.

518: An error occurred during an attempt to read the object's effective rights.

Explanation

The effective rights of the requested object cannot be found. NetWare Directory Services may not have responded to a request, or the name of the object may be corrupted.

Action

Close and reopen the current dialog.

519: You must be logged in to Directory Services to use the Trustees dialog.

Explanation

The Trustees dialog is only available to authenticated NetWare Directory Services users. The User object must have rights to read the trustees to open the dialog.

Action

Log in to NetWare Directory Services using a valid username and password (if required). Then open the Trustees dialog.

520: An error occurred during an attempt to open the Effective Rights dialog.

Explanation

The Effective Rights dialog cannot be opened. There may not be enough memory.

Action

Close and reopen the current dialog. If the problem persists, see Resolving Workstation Memory Problems in *Supervising the Network*, then open the dialog

521: An error occurred during an attempt to build the list of properties for an object.

Explanation

The list of properties could not be assembled. Either NetWare Directory Services did not respond to the request, or the object name or property data was corrupted.

Action

Close and reopen the current dialog.

522: An error occurred during an attempt to free the trustee rights data.

Explanation

The rights granted to the selected trustee could not be freed.

Action

Close and reopen the current dialog.

523: An error occurred during an attempt to build the list of an object's trustees.

Explanation

The list of trustees could not be assembled. Either NetWare Directory Services did not respond to the request, or the object name or trustee data was corrupted. MS Windows may not have sufficient memory to build the list.

Action

Close and reopen the current dialog. If the problem persists, see Resolving Workstation Memory Problems in *Supervising the Network*..

524: A string resource (message) could not be read from Windows.

Explanation

A message that should be displayed cannot be found in MS Windows.

Action

Do the operation again. If this does not work, exit and reenter the current dialog.

525: An error occurred during an attempt to get the Inherited Rights Filter data.

Explanation

The rights that make up the Inherited Rights Filter for this object cannot be found. NetWare Directory Services may have returned incorrect information, or the request may be corrupted in memory.

Action

Close and reopen the current dialog.

526: An error occurred during an attempt to set the Inherited Rights Filter data.

Explanation

New rights for the Inherited Rights Filter could not be set. MS Windows may be unable to allocate enough memory to save the information, or the request to change rights may be corrupted and unreadable.

Action

Close and reopen the current dialog. Correct the memory problem. If the problem persists, notify your Novell Authorized Reseller.

527: An error occurred during an attempt to restore the original check box value.

Explanation

When you tried to reset a gray checkbox to its original (gray) setting, the utility could not determine the original setting. A gray checkbox affects all selected objects or properties. The information from those objects or properties was not available or was corrupted.

Action

Close the dialog and reopen it. Make sure the information that was selected is not corrupted.

528: An error occurred during an attempt to get the selected object's effective rights.

Explanation

The effective rights of the requested object cannot be found. NetWare Directory Services may not have responded to a request, or the name of the object may be corrupted.

Action

Close and reopen the current dialog.

539: An error occurred during an attempt to build the list of this object's trustee assignments.

Explanation

The list of trustees could not be assembled. Either NetWare Directory Services did not respond to the request, or the object name or property data was corrupted.

Action

Close and reopen the current dialog.

540: An error occurred during an attempt to initialize the Rights to Other Objects dialog.

Explanation

The Rights to Other Objects dialog cannot be opened. NetWare Directory Services may not have responded to the request for trustees, or there may not be enough memory.

Action

Close and reopen the current dialog. This dialog may take a long time to open if the Directory tree is large and this object has many trustee assignments. If the problem persists, see Resolving Workstation Memory Problems in *Supervising the Network*.

551: An error has occurred in Directory Services.

Explanation

A problem has occurred that prevented NetWare Directory Services from responding to a request from the utility.

Action

Make sure the workstation is connected to the network. Make sure a server containing a replica of the partition you are working in is available.

552: Out of memory.

Explanation

The utility is out of memory and may be unable to continue.

Action

Close the utility and reopen it to continue. If the problem persists, see Resolving Workstation Memory Problems in *Supervising the Network*.

553: An error occurred during an attempt to build the list of subordinate objects.

Explanation

The subordinates of an object could not be found for the selected object. There may not be enough memory, or NetWare Directory Services may not have responded to the request for information.

Action

Do the operation again. Make sure the workstation is connected to the network. Make sure the workstation is authenticated to an NDS Server. Increase the available memory. See Resolving Workstation Memory Problems in *Supervising the Network*.

554: An error occurred during an attempt to return the selected items.

Explanation

Information on the selected items could not be received from NetWare Directory Services. NetWare Directory Services may not be available at the moment, or the object name or information has been corrupted on the network or in memory.

Action

Exit the utility. Make sure the work station is connected to the network. If necessary, do the operation again.

556: An error occurred during an attempt to get a connection ID to <string>.

Explanation

A connection is required to complete the current operation; however, the connection could not be established. NetWare Directory Services may not be available, or the request may have been corrupted during transmission.

Action

Make sure the workstation has enough connections to the network. Do the operation again.

560: An error occurred during an attempt to move a Directory Services object.

Explanation

The request to move a NetWare Directory Services object cannot be completed. Another move or delete operation may be in progress, or the name of the object that you want to move may have been corrupted when it was sent to NetWare Directory Services.

Action

Wait a moment for NetWare Directory Services to complete any operations in progress. Do the operation again, closing and reopening the current dialog if necessary.

561: An error occurred during an attempt to get the logged-in object's effective rights to the selected object.

Explanation

The effective rights of the requested object cannot be found. NetWare Directory Services may not have responded to a request, or the name of the object may be corrupted.

Action

Close and reopen the current dialog.

772: Objects could not be created in this context.

Explanation

The utility could not create the requested object in this context. The User object may not have rights, or the object may not be allowed within this container object class. NetWare Directory Services may also be processing partition updates and is not allowing updates to the database at the moment.

Action

Make sure your effective rights in the container include the Create Object right. Check to see if the object you want to create can be created in this container. If the problem persists, wait for NetWare Directory Services to resynchronize the Directory database and attempt the operation again.

783: You cannot open a new browser window with only a leaf object.

Explanation

The top or root object of a new browser window must be a Container object or a Volume object.

Action

Select a Country, Organization, Organizational Unit, or Volume object and do the operation again.

784: The program was not able to obtain the vis object.

Explanation

A record for displaying an object in a browser window was not available when needed.

Action

Close the browser windows and reopen them. If the problem persists, exit and restart the utility.

785: The program was not able to obtain the model object.

Explanation

The record of the object could not be found to display it. A problem may exist getting information from NetWare Directory Services.

Action

Close the browser windows and reopen them. If the problem persists, exit and restart the utility. Make sure the workstation is connected to NetWare Directory Services. Log in again if necessary.

786: The program was not able to obtain the list node.

Explanation

The position of an object within the current browser window is not available or is corrupted. The objects may not display correctly.

Action

Close the browser windows and reopen them. If the problem persists, exit and restart the utility. Make sure the workstation is connected to NetWare Directory Services. Log in again if necessary.

787: No object is selected, or too many objects are selected.

Explanation

The operation requested requires a certain number of selected objects in order to be completed. The number of objects selected was not within the acceptable range.

Action

Do the operation again, selecting the correct number of objects. If you are not sure how many the operation requires, start by selecting one object.

788: The program was not able to obtain the list.

Explanation

The list of objects within the current browser window is not available or is corrupted. The objects may not display correctly.

Action

Close the browser windows and reopen them. If the problem persists, exit and restart the utility. Make sure the workstation is connected to NetWare Directory Services. Log in again if necessary.

1006: The NetWare Administrator is out of memory.

Explanation

The utility has run out of memory and may not be able to continue.

Action

Close browser windows or other applications to increase the available memory. You may need to close the utility and reopen it to continue. If the problem persists, see Resolving Workstation Memory Problems in *Supervising the Network*.

1007: An error occurred during an attempt to save this object's rights to the file system.

Explanation

A trustee assignment to a file or directory cannot be saved to the file or directory's trustee list. The object selected as a trustee may be invalid. The connection to the volume containing the file or directory may be unavailable now, even if it was available moments ago. This made it impossible to write the new trustee assignment to the file or directory.

Action

Wait a while, make sure the workstation is connected to the network, and do the operation again.

1009: An error occurred during an attempt to delete a file or directory from the list of trustee assignments.

Explanation

A trustee assignment to a file or directory could not be deleted from the file or directory's trustee list. The object selected as a trustee may be invalid. The connection to the volume containing the file or directory may be unavailable now, even if it was available moments ago. This made it impossible to write the new trustee assignment to the file or directory.

Action

Wait a while, make sure the workstation is connected to the network, and do the operation again.

1010: An error occurred during an attempt to get the Volumes list.

Explanation

The list of volumes associated with this dialog for listing trustee assignments is not available, because NetWare Directory Services cannot return it or it has become corrupted.

Action

Close the dialog and do the operation again. If necessary, exit MS Windows and make sure the workstation is connected to the network.

1011: An error occurred during an attempt to add an item to the list.

Explanation

The list of objects within the current dialog or browser window is not available or is corrupted. Objects could not be added to the list, and they may not display correctly.

Action

Close the browser windows and reopen them. If the problem persists, exit and restart the utility. Make sure the workstation is connected to NetWare Directory Services. Log in again if necessary.

1012: An error occurred during an attempt to remove a volume from the Volumes list.

Explanation

The list of volumes associated with this dialog for listing trustee assignments is not available. This is most likely because NetWare Directory Services cannot return it or it has become corrupted. Because the list is not accessible, a volume cannot be removed from it. Another possible explanation is that the request to remove a volume from the list may be corrupted.

Action

Close the dialog and do the operation again. If necessary, exit MS Windows and make sure the workstation is connected to the network.

1013: An error occurred during an attempt to gray the dialog buttons.

Explanation

The utility needed to shade parts of this dialog, because access is not allowed or is inappropriate, but the dialog could not be changed.

Action

Close the dialog and reopen it.

1014: An error occurred during an attempt to display this object's trustee rights to a file or directory.

Explanation

A trustee assignment to a file or directory cannot be displayed because the file or directory is not accessible at the moment. The address of the volume may be unavailable, or NetWare Directory Services may not have found another piece of needed information. The object selected as a trustee may be invalid.

Action

Wait a while, make sure the workstation is connected to the network, and do the operation again.

1015: An error occurred during an attempt to set this object's trustee rights to a file or directory.

Explanation

A trustee assignment to a file or directory could not be set because the file or directory is not accessible at the moment. The address of the volume may be unavailable, or NetWare Directory Services may not have found another piece of needed information. The object you selected as a trustee may be invalid.

Action

Wait a while, make sure the workstation is connected to the network, and do the operation again.

1018: An error occurred during an attempt to get this trustee's effective rights.

Explanation

The effective rights of the requested object could not be found. NetWare Directory Services may not have responded to a request, or the name of the object may be corrupted.

Action

Close and reopen the current dialog.

1019: An error occurred during an attempt to get a server connection ID.

Explanation

The utility needed to identify the server that it is receiving information from, but it was not able to identify the server's connection ID.

Action

Make sure the workstation is connected to the network. Make sure the needed NetWare Directory Services server is functioning properly. Do the operation again; exit and restart the utility if necessary.

1021: An error occurred during an attempt to open the Effective Rights dialog.

Explanation

The Effective Rights dialog could not be opened. MS Windows may not have enough available memory.

Action

Close and reopen the current dialog. If the problem persists, see Resolving Workstation Memory Problems in *Supervising the Network*.

1022: An error occurred during an attempt to get the Directory Services context.

Explanation

The context of an object was needed to complete an operation, but the context could not be determined. An incorrect context may have been entered, or rights may not be appropriate to work in the context that was entered.

Action

Do the operation again. Close and reopen the current dialog if necessary.

1023: An error occurred during an attempt to get the trustee list of the selected object.

Explanation

The trustee list could not be assembled. Either NetWare Directory Services did not respond to the request, or the object name or trustee data was corrupted.

Action

Close and reopen the dialog.

1024: An error occurred during an attempt to get the trustee's object ID.

Explanation

A code that identifies a trustee of this object was needed to complete this operation, but it could not be determined. Either NetWare Directory Services did not respond to the request, or the object name or trustee data was corrupted.

Action

Close and reopen the dialog.

1049: An error occurred during an attempt to get a connection ID.

Explanation

A connection to the requested server could not be established, because a connection ID number was not available for this user.

Action

Do the operation again. Make sure the workstation is connected to the network. Make sure the user has appropriate user access rights to the server.

1051: An error occurred during an attempt to retrieve entry information.

Explanation

The entry information was not returned as requested. The User object may not have appropriate rights to the server, or the server cannot be located on the network, either because the Server object is in a different context, or because the physical volume's host server address is not available or is invalid.

Action

Make sure the user has appropriate user access rights to the server. Make sure the server is operating. Make sure the context of the Server object and the volume's host server network address are correct.

1079: A network error has occurred. Please note the following numbers.

Explanation

An unexplained error with the network connection caused this operation to fail.

Action

Record the numbers displayed and contact your Novell Authorized Reseller.

1084: <Object name> could not be found. Please check that it still exists and that you still have rights to see it.

Explanation

The User object may not have appropriate rights to the server, directory, or file, or the server could not be located on the network.

Action

Make sure the user has appropriate user access rights in both the source and destination directories.
Make sure the workstation is connected to the network. Make sure the server is operating.

1085: <Object> is of an object class that cannot be contained by the destination object.

Explanation

The selected object cannot be contained by the destination object.

Action

Select an object class that can contain the type of object you are trying to use.

1086: No more server connection slots are available. Log out of a server that you are not using, or increase the maximum number of connections.

Explanation

To complete this operation, the workstation must attach to a server, but no slots are available for the new connection.

Action

Detach the workstation from a server that is not being used, or increase the maximum number of slots that can be used.

1088: Login has failed. You have no account balance.

Explanation

The user cannot log in because accounting has been set and the user does not have a balance.

Action

Set up an account for the user.

1089 Login has failed. You have no credit in your account balance.

Explanation

The user cannot log in because accounting has been set and the user does not have a balance.

Action

Set up an account for the user.

1090: Login has failed. Your account has been locked because an intruder was detected.

Explanation

The user's account has been locked because an intruder was detected. Either the user typed the wrong name or password, or someone tried to log in as that user.

Action

Make sure that an intruder is not trying to access the system. Then unlock the user's account.

1091: Login has failed. You do not have a valid connection to this server.

Explanation

The login request has failed because the workstation does not have a valid connection to the server.

Action

Log in again, using the correct login name and password. If the request still fails, make sure the server is operating. Make sure the workstation has a physical connection to the server.

1092: Login has failed. You have exceeded your maximum concurrent logins.

Explanation

The user has exceeded the allowed number of concurrent logins for that account.

Action

If the user needs additional concurrent logins, change the user restrictions.

1093: Login has failed. You are not authorized to log in on this day at this time.

Explanation

The account has specific times set when it can log in. Now is not one of those times.

Action

If the user needs modified login authorization, change the user restrictions.

1094: Login has failed. You are not authorized to log in from this workstation.

Explanation

The User object has specific workstation addresses set that must be used to log in. This workstation is not one of those workstations.

Action

If the user needs to log in from this workstation, change the user restrictions.

1095: Login has failed. Your account has been disabled.

Explanation

The account has a date set when it will be disabled. That date arrived.

Action

Reestablish the user's account, if appropriate.

1096: Login has failed. Your password has expired and your grace logins have been used.

Explanation

The account has been set so that the password must be changed regularly. The password expired and the grace logins allowed have also been used.

Action

Reestablish the user's account and assign a temporary password so the user can access the account.

1097: Your password has expired. Please change your password immediately.

Explanation

The account has been set so that the password must be changed regularly. The password has expired.

Action

Change the User object's password.

1098: Login has failed. Please make sure you have correctly entered your name and password and that the server is functional.

Explanation

Either the login name or the password was typed incorrectly, or the server is not functioning properly. The User object may not have appropriate rights to the server, or the server could not be located on the network.

Action

Make sure the user has appropriate user access rights. Type the login name and password correctly. Make sure the workstation is connected to the network. Make sure the server is operating.

1099: The selected server cannot be found.

Explanation

The request for the selected server could not be completed. The User object may not have appropriate rights to the server, or the server could not be located on the network, either because

- The server object is in a different context, or
- The physical volume's host server address is not available or is invalid.

Action

Make sure the user has appropriate user access rights. Make sure the workstation is connected to the network. Make sure the server is operating.

1250: The selected directory's existence cannot be confirmed.

Explanation

This directory was located when first displayed, but it can no longer be found. The directory may still exist, but not be available to this dialog because of partition or network connections that have changed since you first saw the directory listed in the dialog.

Action

Close and reopen the current dialog. If the directory is still not visible to NetWare Directory Services, find out if partitions or network connections have been changed recently.

1251: The selected file's existence cannot be confirmed.

Explanation

This file was located when first displayed, but it can no longer be found. The file may still exist, but not be available to this dialog because of partition or network connections that have changed since you first saw the file listed in the dialog.

Action

Close and reopen the current dialog. If the file is still visible to NetWare Directory Services, find out if partitions or network connections have been changed recently.

1980: NWDSSetContext problem.

Explanation

The function could not complete its execution properly.

Action

Close the current dialog and do the operation again, making sure that you are working with the correct object and context. If the problem persists, contact your Novell Authorized Reseller.

1981: NWDSFreeContext problem.

Explanation

The function could not complete its execution properly.

Action

Close the current dialog and do the operation again, making sure that you are working with the correct object and context. If the problem persists, contact your Novell Authorized Reseller.

1982: NWSPdfAddForm problem.

Explanation

The function could not complete its execution properly.

Action

Close the current dialog and do the operation again, making sure that you are working with the correct object and context. If the problem persists, contact your Novell Authorized Reseller.

1983: NWPSdfUpdateForm problem.

Explanation

The function could not complete its execution properly.

Action

Close the current dialog and do the operation again, making sure that you are working with the correct object and context. If the problem persists, contact your Novell Authorized Reseller.

1984: NWSPdfDeleteForm problem.

Explanation

The function could not complete its execution properly.

Action

Close the current dialog and do the operation again, making sure that you are working with the correct object and context. If the problem persists, contact your Novell Authorized Reseller.

1985: NWSPdfAddDevice problem.

Explanation

The function could not complete its execution properly.

Action

Close the current dialog and do the operation again, making sure that you are working with the correct object and context. If the problem persists, contact your Novell Authorized Reseller.

1986: NWPSdfUpdateDevice problem.

Explanation

The function could not complete its execution properly.

Action

Close the current dialog and do the operation again, making sure that you are working with the correct object and context. If the problem persists, contact your Novell Authorized Reseller.

1987: NWPSdfDeleteDevice problem.

Explanation

The function could not complete its execution properly.

Action

Close the current dialog and do the operation again, making sure that you are working with the correct object and context. If the problem persists, contact your Novell Authorized Reseller.

1988: NWPSdfAddFunction problem.

Explanation

The function could not complete its execution properly.

Action

Close the current dialog and do the operation again, making sure that you are working with the correct object and context. If the problem persists, contact your Novell Authorized Reseller.

1989: NWSPdfUpdateFunction problem.

Explanation

The function could not complete its execution properly.

Action

Close the current dialog and do the operation again, making sure that you are working with the correct object and context. If the problem persists, contact your Novell Authorized Reseller.

1990: NWSPdfDeleteFunction problem.

Explanation

The function could not complete its execution properly.

Action

Close the current dialog and do the operation again, making sure that you are working with the correct object and context. If the problem persists, contact your Novell Authorized Reseller.

1991: NWPSdfAddModeFunction problem.

Explanation

The function could not complete its execution properly.

Action

Close the current dialog and do the operation again, making sure that you are working with the correct object and context. If the problem persists, contact your Novell Authorized Reseller.

1992: NWPSpdfDeleteMode problem.

Explanation

The function could not complete its execution properly.

Action

Close the current dialog and do the operation again, making sure that you are working with the correct object and context. If the problem persists, contact your Novell Authorized Reseller.

1150: The NetWare Administrator has run out of memory.

Explanation

The utility has run out of memory and may not be able to continue.

Action

See Resolving Workstation Memory Problems in *Supervising the Network*.

1151: An error occurred during an attempt to add new trustees.

Explanation

New trustees could not be added to the trustee list. The trustee list may be corrupted, MS Windows may not be able to access enough memory to add to the list, or the names of the new trustees returned by NetWare Directory Services may not be accurate.

Action

See Resolving Workstation Memory Problems in *Supervising the Network*.

1152: A string resource (message) could not be loaded.

Explanation

A message that would have been displayed cannot be found within MS Windows.

Action

Do the operation again. If it fails, exit and reenter the current dialog.

1153 An error occurred during an attempt to build the list of trustees.

Explanation

The list of trustees could not be assembled. Either NetWare Directory Services did not respond to the request, or the object name or trustee data was corrupted.

Action

Close and reopen the current dialog.

1154: An error occurred during an attempt to get trustee rights.

Explanation

The rights granted to the selected trustee could not be found. NetWare Directory Services may have returned incorrect information, or the name of the trustee may be corrupted in memory.

Action

Close and reopen the current dialog.

1155: An error occurred during an attempt to open the Effective Rights dialog.

Explanation

The Effective Rights dialog could not be opened. There may not be enough memory.

Action

Close and reopen the current dialog. If the problem persists, see Resolving Workstation Memory Problems in *Supervising the Network*.

1156: An error occurred during an attempt to get the effective rights.

Explanation

The effective rights of the requested object could not be found. NetWare Directory Services may not have responded to a request, or the name of the object may be corrupted.

Action

Close and reopen the current dialog.

1157: An error occurred during an attempt to save Directory Facts changes.

Explanation

Changes made in the Directory Facts page could not be saved. The directory may be unavailable, or the new information may be corrupted.

Action

Close and reopen the current dialog; and then reenter the information.

1158: An error occurred during an attempt to save Directory Identification changes.

Explanation

Changes made in the Directory Identification page could not be saved. The directory may be unavailable, or the new information may be corrupted.

Action

Close and reopen the current dialog; and then reenter the information.

1159: An error occurred during an attempt to save Trustee changes.

Explanation

Changes to the trustee list or to trustee's rights could not be saved. NetWare Directory Services may not be allowing access momentarily, or the new data may be corrupted.

Action

Close and reopen the current dialog; and then reenter the information.

1160: An error occurred during an attempt to initialize the Directory Facts dialog.

Explanation

The Directory Facts information cannot be opened. There may not be enough memory.

Action

Close and reopen the current dialog. If the problem persists, see Resolving Workstation Memory Problems in *Supervising the Network*.

1161: An error occurred during an attempt to get the object's effective rights.

Explanation

The effective rights of the requested object cannot be found. NetWare Directory Services may not have responded to a request, or the name of the object may be corrupted.

Action

Close and reopen the current dialog.

1162: An error occurred during an attempt to initialize the Directory Identification dialog.

Explanation

The Directory Identification information cannot be opened. There may not be enough memory.

Action

Close and reopen the current dialog. See Resolving Workstation Memory Problems in *Supervising the Network*.

1163: An error occurred during an attempt to return the list of bindery users and groups.

Explanation

When using bindery services or a NetWare 3 server, the list of users and groups from the bindery could not be completed. The request may be corrupted.

Explanation

Close and reopen the current dialog.

1164: An error occurred during an attempt to rename the file or directory.

Explanation

The object could not be renamed. The old name may be corrupted and therefore cannot be found, or the new name may be unacceptable. NetWare Directory Services may not be accepting the request to update the Directory Database.

Action

Close and reopen the current dialog.

1165: An error occurred during an attempt to delete a trustee.

Explanation

The selected trustee could not be deleted. One of the following happened:

- NetWare Directory Services received a command it did not understand
- The object has subordinates
- The name of the object is not acceptable to NetWare Directory Services
- The request was corrupted

Action

Close and reopen the current dialog.

1166: An error occurred during an attempt to set the trustee rights.

Explanation

New rights for the trustee could not be set. MS Windows may be unable to allocate enough memory to save the information, or the trustee or request to change rights may be corrupted and unreadable.

Action

See Resolving Workstation Memory Problems in *Supervising the Network*.

1167: An error occurred during an attempt to save changes to the directory attributes.

Explanation

Changes made to the Directory Attributes could not be saved. The directory may be unavailable, or the new information may be corrupted.

Action

Close and reopen the dialog; then reenter the information.

1168: An error occurred during an attempt to get the trustee rights.

Explanation

The rights granted to the selected trustee cannot be found. NetWare Directory Services may have returned incorrect information, or the name of the trustee may be corrupted in memory.

Action

Close and reopen the current dialog.

1169: An error occurred during an attempt to save File Facts changes.

Explanation

Changes made in the File Facts page could not be saved. The file may be unavailable, or the new information may be corrupted.

Action

Close and reopen the current dialog; then reenter the information.

1170: An error occurred during an attempt to initialize the File Facts dialog.

Explanation

The File Facts information cannot be opened. There may not be enough memory.

Action

Close and reopen the current dialog. If the problem persists, see Resolving Workstation Memory Problems in *Supervising the Network*.

1171: An error occurred during an attempt to save changes to the file attributes.

Explanation

Changes made to the File Attributes could not be saved. The file may be unavailable, or the new information may be corrupted.

Action

Close and reopen the current dialog; then reenter the information.

1172: An error occurred during an attempt to initialize the Bindery User and Group Selector dialog.

Explanation

The Bindery User and Group object information cannot be opened. There may not be enough memory.

Action

Close and reopen the current dialog. If the problem persists, see Resolving Workstation Memory Problems in *Supervising the Network*.

1173: An error occurred while sorting the salvageable file list.

Explanation

The list of salvageable files could not be sorted by the Sort option selected. There may not be enough memory available to complete the sort. The files should still appear in an unsorted list.

Action

See Resolving Workstation Memory Problems in *Supervising the Network*.

1174: An error occurred during an attempt to initialize the Salvage dialog.

Explanation

The Salvage dialog cannot be opened. There may not be enough memory.

Action

Try opening the dialog again. Exit and reenter the utility. See Resolving Workstation Memory Problems in *Supervising the Network*.

1175: An error occurred during an attempt to retrieve the salvageable file list.

Explanation

The list of files that can be salvaged from the selected directory could not be compiled. The volume may not be responding, or the request was corrupted.

Action

Close and reopen the Salvage dialog.

1176: An error occurred during an attempt to display the salvageable file list.

Explanation

The list of salvageable files was retrieved from the directory requested, but it cannot be displayed. Either the list was corrupted, or MS Windows cannot allocate enough memory to display the list.

Action

Close and reopen the current dialog. If the problem persists, see Resolving Workstation Memory Problems in *Supervising the Network*.

1177: An error occurred during an attempt to salvage files.

Explanation

The file or files that you tried to salvage could not be salvaged. The filenames sent to the volume may have been corrupted, or the volume may be unable to complete the operation.

Action

Close and reopen the current dialog.

1178: An error occurred during an attempt to purge files.

Explanation

The file or files that you tried to purge could not be purged. The filenames sent to the volume may have been corrupted, or the volume may be unable to complete the operation.

Action

Close and reopen the current dialog.

1322: A system error has occurred.

Explanation

An error has occurred with the system.

Action

Check the network connection, exit MS Windows, and restart the utility.

1329: An invalid name was entered.

Explanation

One of the following may explain this error

- The object name entered contains characters that are invalid.
- The object name entered refers to an object that does not exist or cannot be accessed at the moment.
- The workstation may have lost its connection to NetWare Directory Services.
- Requests may have been delayed, or access to the database may have been interrupted.

Action

Enter a different name or correct characters in the name. Make sure the workstation is connected to NetWare Directory Services.

1350: The object cannot be read. It may have been deleted from another workstation, or you may not have sufficient rights to read it.

Explanation

The specified object could not be located in the database. It may have been deleted at another workstation since the time that it appeared on the screen. Another possibility is that you can see the object but don't have rights to read its properties.

Action

Close and reopen the current dialog. If the object no longer appears, it must have been deleted at another station. If the object still appears, make sure the User object's effective rights to the object are appropriate.

1351: There is no such value.

Explanation

The requested value does not exist or cannot be found at the moment.

Action

Do the operation again. If it fails repeatedly, enter a different value.

1352: An object with that name already exists. Please try a different name.

Explanation

Objects within the same container must have unique names.

Action

Use a different name for this object, one that is not yet used in this container.

1353: A name was entered that is invalid in Directory Services. The maximum length is 256 characters.

Explanation

The name entered for this object was too long or used invalid characters.

Action

Reenter the name, being careful not to use invalid characters or to exceed the maximum length.

1356: A duplicate value has been entered.

Explanation

Duplicates are not allowed here.

Action

Enter a unique value.

1362: A duplicate value has been entered.

Explanation

Duplicate values are not allowed here.

Action

Enter a unique value.

1363: Access is not allowed.

Explanation

Access to this object or property is not allowed at this time. The User object may have inappropriate rights, or NetWare Directory Services may be currently processing a command (such as Delete or Move an object) that requires locking out certain other actions until it is completed.

Action

Wait until NetWare Directory Services has finished the previous operation; then do the operation again. Make sure the user has appropriate user access rights to the area.

1429: An error occurred during an attempt to load mvebb.dll.

Explanation

A file that was needed to complete a requested action is not available to the utility. One of the NetWare Administrator utility's files is missing or corrupted.

Action

Recopy the NetWare Administrator utility and its associated files to your work area (probably the PUBLIC directory) from the original NetWare CD-ROM or diskettes.

1430: An error occurred during an attempt to load muscroll.dll.

Explanation

A file that was needed to complete a requested action is not available to the utility. One of the NetWare Administrator's files is missing or corrupted.

Action

Recopy the NetWare Administrator and its associated files to your work area (probably the PUBLIC directory) from the original NetWare CD-ROM or diskettes.

1431: An error occurred during an attempt to call `CN can close.'

Explanation

The specified function call could not be completed. Data may have become corrupted during processing, or NetWare Directory Services did not provide or request enough information to complete the task. The value entered may not have been saved.

Action

Close and reopen the current dialog. Repeat the operation. Make sure the workstation is connected to the network. If the problem persists, contact your Novell Authorized Reseller.

1432: An error occurred during an attempt to call `Server can close.'

Explanation

The specified function call could not be completed. Data may have become corrupted during processing, or NetWare Directory Services did not provide or request enough information to complete the task. The value entered may not have been saved.

Action

Close and reopen the current dialog. Repeat the operation. Make sure the workstation is connected to the network. If the problem persists, contact your Novell Authorized Reseller.

1433: An error occurred during an attempt to call `Description can close.'

Explanation

The specified function call could not be completed. Data may have become corrupted during processing, or NetWare Directory Services did not provide or request enough information to complete the task. The value entered may not have been saved.

Action

Close and reopen the current dialog. Repeat the operation. Make sure the workstation is connected to the network. If the problem persists, contact your Novell Authorized Reseller.

1434: An error occurred during an attempt to call `Locality can close.'

Explanation

The specified function call could not be completed. Data may have become corrupted during processing, or NetWare Directory Services did not provide or request enough information to complete the task. The value entered may not have been saved.

Action

Close and reopen the current dialog. Repeat the operation. Make sure the workstation is connected to the network. If the problem persists, contact your Novell Authorized Reseller.

1435: An error occurred during an attempt to call `OU can close.'

Explanation

The specified function call could not be completed. Data may have become corrupted during processing, or NetWare Directory Services did not provide or request enough information to complete the task. The value entered may not have been saved.

Action

Close and reopen the current dialog. Repeat the operation. Make sure the workstation is connected to the network. If the problem persists, contact your Novell Authorized Reseller.

1436: An error occurred during an attempt to call `O can close.'

Explanation

The specified function call could not be completed. Data may have become corrupted during processing, or NetWare Directory Services did not provide or request enough information to complete the task. The value entered may not have been saved.

Action

Close and reopen the current dialog. Repeat the operation. Make sure the workstation is connected to the network. If the problem persists, contact your Novell Authorized Reseller.

1437: An error occurred during an attempt to call `Owner can close.'

Explanation

The specified function call could not be completed. Data may have become corrupted during processing, or NetWare Directory Services did not provide or request enough information to complete the task. The value entered may not have been saved.

Action

Close and reopen the current dialog. Repeat the operation. Make sure the workstation is connected to the network. If the problem persists, contact your Novell Authorized Reseller.

1438: An error occurred during an attempt to call `Serial Number can close.'

Explanation

The specified function call could not be completed. Data may have become corrupted during processing, or NetWare Directory Services did not provide or request enough information to complete the task. The value entered may not have been saved.

Action

Close and reopen the current dialog. Repeat the operation. Make sure the workstation is connected to the network. If the problem persists, contact your Novell Authorized Reseller.

1439: An error occurred during an attempt to load the flat browser dll.

Explanation

A file needed to complete the operation is not available or is corrupted.

Action

Make sure all necessary files are available to the utility. If any files are missing or corrupted, recopy them to your work area.

1440: An error occurred during an attempt to reference the transfer buffer.

Explanation

An internal memory area that was needed to complete an operation could not be accessed.

Action

There may be a memory conflict or an error in the requested operation. Close and reopen the current dialog. Repeat the operation. You may need to exit MS Windows if the problem persists.

1441: An error occurred during an attempt to create a new object.

Explanation

The new object could not be created because of a problem with the utility or with the NetWare Directory Services database. The User object may not have appropriate rights to create an object here, or the object you want to create may not be allowed within this container class.

Action

Create the object again. You may need to exit the utility first, and then reopen it. Make sure the workstation is connected to NetWare Directory Services. If the workstation connection is invalid, you cannot create a new object.

1442: An error occurred because the view pointer is invalid.

Explanation

A pointer needed to reference an area of the screen is invalid or could not be found. The display may be incorrect, even though the data has not been altered.

Action

Close all browsers and reopen them. You may need to close the utility and reopen it. If the problem persists, make sure the workstation is connected to the network and consider using replicas of this partition to correct any corrupted object data.

1443: An error occurred because the Windows object is invalid.

Explanation

The structure used to display information has become corrupted or cannot be found.

Action

Close the utility, and perhaps MS Windows, and reopen them. If the problem persists, contact your Novell Authorized Reseller.

1444: An error occurred because the model object is invalid.

Explanation

The needed information from the database about the selected object could not be found or understood.

Action

Close the dialog or browser and reopen it. If the problem persists, make sure the workstation is connected to the network and consider using replicas of this partition to correct any corrupted object data.

1445: An error occurred because the program was not able to get the browser handle.

Explanation

The information needed to correctly display the browser could not be found or understood. The information on the screen may appear garbled, even though the data has not been altered.

Action

Close the browser window, or perhaps the utility, and do the operation again.

1446: An error occurred during an attempt to call `fax can close.'

Explanation

The specified function call could not be completed. Data may have become corrupted during processing, or NetWare Directory Services did not provide or request sufficient information to complete the task. The value entered may not have been saved.

Action

Close the current dialog and reopen it. Repeat the operation. If the error occurs again, make sure the workstation is connected to the network. If the problem persists, contact your Novell Authorized Reseller.

1447: An error occurred during an attempt to call `email can close.'

Explanation

The specified function call could not be completed. Data may have become corrupted during processing, or NetWare Directory Services did not provide or request enough information to complete the task. The value entered may not have been saved.

Action

Close the current dialog and reopen it. Repeat the operation. If the error occurs again, make sure the workstation is connected to the network. If the problem persists, contact your Novell Authorized Reseller.

1448: An error occurred during an attempt to call `role occupant can close.'

Explanation

The specified function call could not be completed. Data may have become corrupted during processing, or NetWare Directory Services did not provide or request enough information to complete the task. The value entered may not have been saved.

Action

Close the current dialog and reopen it. Repeat the operation. If the error occurs again, make sure the workstation is connected to the network. If the problem persists, contact your Novell Authorized Reseller.

1449: An error occurred during an attempt to call `telephone number can close.'

Explanation

The specified function call could not be completed. Data may have become corrupted during processing, or NetWare Directory Services did not provide or request sufficient information to complete the task. The value entered may not have been saved.

Action

Close the current dialog and reopen it. Repeat the operation. If the error occurs again, check your network connection and contact your network supervisor. If the problem persists, contact your Novell Authorized Reseller.

1450: An error occurred during an attempt to call `host server can close.'

Explanation

The specified function call could not be completed. Data may have become corrupted during processing, or NetWare Directory Services did not provide or request enough information to complete the task. The value entered may not have been saved.

Action

Close the current dialog and reopen it. Repeat the operation. If the error occurs again, make sure the workstation is connected to the network. If the problem persists, contact your Novell Authorized Reseller.

1451: An error occurred during an attempt to call `aliased object name can close.'

Explanation

The specified function call could not be completed. Data may have become corrupted during processing, or NetWare Directory Services did not provide or request enough information to complete the task. The value entered may not have been saved.

Action

Close the current dialog and reopen it. Repeat the operation. If the error occurs again, make sure the workstation is connected to the network. If the problem persists, contact your Novell Authorized Reseller.

1452: An error occurred during an attempt to call `version can close.'

Explanation

The specified function call could not be completed. Data may have become corrupted during processing, or NetWare Directory Services did not provide or request enough information to complete the task. The value entered may not have been saved.

Action

Close the current dialog and reopen it. Repeat the operation. If the error occurs again, make sure the workstation is connected to the network. If the problem persists, contact your Novell Authorized Reseller.

1458: Due to an unknown error, the current operation may fail.

Explanation

Some information needed to complete this operation is unavailable or cannot be understood.

Action

Do the operation again. If the problem persists, exit the utility and make sure the workstation is connected to the network. If the workstation connection is invalid, you cannot create a new object. Also do the operation on other workstations to see if the problem is in the NetWare Directory Services database or with your workstation.

1459: An error occurred during an attempt to add an object. The operation may fail.

Explanation

The new object could not be created. One of the following may account for this error:

- A problem occurred with the utility or with the NetWare Directory Services database.
- The User object does not have appropriate rights to create an object here.
- The object you want to create may not be allowed within this container class.

Action

Create the object again. You may need to exit the utility and then reopen it. Make sure the workstation is connected to NetWare Directory Services.

1460: An error occurred during an attempt to read an object. The operation may fail.

Explanation

A problem may have occurred with the utility or with the NetWare Directory Services database. Another possibility is that the User object does not have appropriate rights to complete this operation. If the workstation connection is invalid, you cannot read an object.

Action

Read the object again. You may need to exit the utility first and then reopen it. Make sure the workstation is connected to NetWare Directory Services.

1461: An error occurred during an attempt to save changes. The operation may fail.

Explanation

The changes to the object could not be saved because of a problem with the utility or with the NetWare Directory Services database. Another possibility is that the User object does not have appropriate rights to modify this object. If the workstation connection is invalid, you cannot modify objects.

Action

Modify the object again and save the changes. You may need to exit the utility first and then reopen it. Make sure the workstation is connected to NetWare Directory Services.

1463: An error occurred during an attempt to rename an object. The operation may fail.

Explanation

A problem may have occurred with the utility or with the NetWare Directory Services database. Another possibility is that the User object does not have appropriate rights to complete this operation. If the workstation connection is invalid, you cannot rename an object.

Action

Rename the object again. You may need to exit the utility first and then reopen it. Make sure the workstation is connected to NetWare Directory Services.

1464: An error occurred. The current operation may fail.

Explanation

A problem may have occurred with the utility or with the NetWare Directory Services database. Another possibility is that the User object does not have appropriate rights to complete this operation.

Action

Do the operation again. You may need to exit the utility first and then reopen it. Make sure the workstation is connected to NetWare Directory Services.

1469: The new object could not be created.

Explanation

The new object could not be created. One of the following may account for this error:

- A problem occurred with the utility or with the NetWare Directory Services database.
- The User object does not have appropriate rights to create an object here.
- The object you want to create may not be allowed within this container class.
- The workstation has an invalid connection to NetWare Directory Services.

Action

Create the object again. You may need to exit the utility first and then reopen it. Make sure the workstation is connected to NetWare Directory Services.

1470: The object could not be read.

Explanation

The object could not be read because of a problem with the utility or with the NetWare Directory Services database. Another possibility is that the User object does not have appropriate rights to read this object. If the workstation connection is invalid, you cannot modify objects.

Action

Read the object again. You may need to exit the utility first and then reopen it. Make sure the workstation is connected to NetWare Directory Services.

1471: The object could not be modified.

Explanation

The changes to the object could not be saved because of a problem with the utility or with the NetWare Directory Services database. Another possibility is that the User object does not have appropriate rights to modify this object. If the workstation connection is invalid, you cannot modify objects.

Action

Modify the object again and save the changes. You may need to exit the utility first and then reopen it. Make sure the workstation is connected to NetWare Directory Services.

1472: The object could not be renamed.

Explanation

The object could not be renamed because of a problem with the utility or with the NetWare Directory Services database. Another possibility is that the User object does not have appropriate rights to rename this object. If the workstation connection is invalid, you cannot modify objects.

Action

Rename the object again. You may need to exit the utility first and then reopen it. Make sure the workstation is connected to NetWare Directory Services.

1473: An object key pair could not be generated.

Explanation

A property used during login could not be created properly. You may not be able to log in successfully or complete other operations requiring authentication.

Action

Do the operation again. If the problem persists, contact your Novell Authorized Reseller.

1479: A buffer could not be allocated. The current operation may fail.

Explanation

Space needed to complete this operation was not available. The operation may or may not be completed without that extra space.

Action

Close dialogs or browser windows if necessary to increase the available memory. See Resolving Workstation Memory Problems in *Supervising the Network*. If more available memory does not solve the problem, a problem may exist in MS Windows. Check the MS Windows settings. Exit MS Windows before repeating the operation.

1480: The user's login name could not be determined.

Explanation

The login name entered was unreadable, or the name of the user already logged in could not be found but is needed for the current operation.

Action

Do the operation again. The database may have been unavailable for a moment. Make sure the required username is a valid object name and exists in the database where expected.

1481: Effective rights could not be determined.

Explanation

The effective rights of the requested object cannot be found. NetWare Directory Services may not have responded to a request, or the name of the object may be corrupted.

Action

Close and reopen the current dialog.

1482: The name could not be mapped to an ID. The current operation may fail.

Explanation

The name entered was understood, but cannot be converted to an internal code needed for this operation. Without that code, the operation is likely to fail.

Action

Do the operation again. The database may have been unavailable for a moment. Make sure the entered username is a valid object name and exists in the database where expected.

1483 The model object could not be found. The current operation may fail.

Explanation

The needed information from the database about the selected object could not be found or understood.

Action

Close the dialog or browser and reopen it. If the problem persists, make sure the workstation is connected to the network and consider using replicas of this partition to correct any corrupted object data.

1484: The object could not be renamed.

Explanation

The object could not be renamed because of a problem with the utility or with the NetWare Directory Services database. Another possibility is that the User object does not have appropriate rights to rename this object.

Action

Rename the object again. You may need to exit the utility first and then reopen it. Make sure the workstation is connected to NetWare Directory Services.

1485: The password could not be changed.

Explanation

The password could not be changed because of a problem with the utility or with the NetWare Directory Services database. Another possibility is that the User object does not have appropriate rights to change the password. If the connection has become invalid, the User object is no longer authenticated and cannot change the password.

Action

Change the password again. You may need to exit the utility first and then reopen it. Make sure the workstation is connected to NetWare Directory Services.

1489: The login script file could not be opened.

Explanation

The file containing the login script property could not be successfully opened. The correct volume may be unavailable, or the User object may not have appropriate rights to the property.

Action

Make sure the user has appropriate user access rights to the login script property. Make sure the workstation is connected to the default server. If you still cannot open the login script, it may be corrupted. If this is the case, reenter the login script.

1490: The login script file could not be read.

Explanation

The file containing the login script property could not be read successfully. The correct volume may be unavailable, or the User object may not have appropriate rights to the property.

Action

Make sure the user has appropriate user access rights to the login script property. Make sure the workstation is connected to the default server. If you still cannot read the login script, it may be corrupted. If this is the case, exit the utility and reenter the changes to the login script. You can use the Clipboard with cut and paste in MS Windows to avoid retyping the login script.

1491: The login script file could not be written.

Explanation

The file containing the login script property could not be successfully written. The correct volume may be unavailable, even if it was available when you read the login script. Another possibility is that the User object does not have appropriate rights to the property.

Action

Write the changes again. Make sure the user has appropriate user access rights to the login script property. Make sure the workstation is connected to the default server. If you still cannot write the login script, it may be corrupted. Exit the utility and reenter the changes to the login script. You can use the Clipboard with cut and paste in MS Windows to avoid retyping the login script.

1492: The login script file could not be closed.

Explanation

The file containing the login script property could not be successfully closed. The correct volume may be unavailable, or the User object may not have appropriate rights to the property. If the file cannot be closed, any changes may be lost. If you have not changed the login script, no damage should occur.

Action

Make sure the user has appropriate user access rights to the login script property. Make sure the workstation is connected to the default server. If you still cannot close the login script, it may be corrupted. Exit and reenter the utility and look at the login script. Reenter any changes that were lost.

1493: The login script was not completely saved due to an unknown error.

Explanation

The file containing the login script property could not be successfully saved. The correct volume may be unavailable, even if it was available when you read the login script. Another possibility is that the User object does not have appropriate rights to the property.

Action

Save the changes again. Make sure the user has appropriate user access rights to the login script property. Make sure the workstation is connected to the default server. If you still cannot save the login script, it may be corrupted. Exit the utility and reenter the changes to the login script. You can use the Clipboard with cut and paste in MS Windows to avoid retyping the login script.

1494: The login script file could not be changed. The previous login script may not be deleted completely.

Explanation

The file containing the login script property could not be successfully updated. The correct volume may be unavailable, even if it was available when you read the login script. Another possibility is that the User object does not have appropriate rights to the property.

Action

Write the changes again. Make sure the user has appropriate user access rights to the login script property. Make sure the workstation is connected to the default server. If you still cannot update the login script, it may be corrupted. Exit the utility and reenter the changes to the login script. You can use the Clipboard with cut and paste in MS Windows to avoid retyping the login script. Check the login script again after making changes to be sure that the login script is complete and has not been corrupted.

1495: The login script could not be read because of insufficient memory.

Explanation

The utility has run out of memory and may not be able to continue.

Action

See Resolving Workstation Memory Problems in *Supervising the Network*.

1496: The login script could not be saved because of insufficient memory.

Explanation

The utility has run out of memory and may not be able to continue.

Action

See Resolving Workstation Memory Problems in *Supervising the Network*.

1499: This property requires valid Directory Services objects.

Explanation

The property requested must be associated with a NetWare Directory Services object, but none is specified or available.

Action

Specify a different property. Many NetWare Directory Services properties are similar to other properties, so be careful how you specify it.

1500 The following entries are invalid**Explanation**

Entries have been selected that the utility cannot process. The entry may be unavailable at the moment, or the operation may be invalid on certain classes of objects.

Action

Examine each invalid item to determine what caused it to be invalid. Remove invalid selections from the list of selections.

1501: You do not have sufficient rights to complete this operation.

Explanation

The User object's effective rights to this object, file, or directory, which are computed from trustee assignments, inheritance, and security equivalence, are not sufficient to complete this operation.

Action

Grant the User object more rights.

1675: A previous password cannot be used; enter a unique password.

Explanation

To increase network security, passwords must be unique. You cannot use a password that has been used.

Action

Enter a new password that has not been used.

1676 The password is too short.

Explanation

A minimum password length has been set for this user. The password selected must be at least that long.

Action

Enter a password that is at least as long as the minimum required length.

1677: The password is invalid.

Explanation

The password entered is not the correct one for the username entered. If intruder detection has been set and an incorrect password has been entered too many times, the account may be locked.

Action

Enter the correct password.

1678: The password has expired.

Explanation

Either the account or the password for this user account has expired and is no longer valid.

Action

If you have a grace login, use it to log in; then change the password. If there are no grace logins, or if the account has expired, access the account through the NetWare Administrator utility.

1679: Retype the new password.

Explanation

A new password must be entered twice to guard against typing errors. This ensures that the password has been changed to what it is supposed to be.

Action

Reenter the same new password just entered.

1685: Accounting could not be removed. (Delete property operation failed.)

Explanation

Accounting could not be removed from this server for one of the following reasons:

- The server was unavailable to receive the command.
- Other processes cannot be interrupted right now.

Action

Do the operation again. Make sure the workstation is connected to the network. Make sure the server is operating.

1686: Accounting could not be installed. (Create property operation failed.)

Explanation

Accounting could not be installed on this server for one of the following reasons:

- The server was unavailable to receive the command.
- Other processes cannot be interrupted right now.

Action

Do the operation again. Make sure the workstation is connected to the network. Make sure the server is operating.

1687: An error occurred during an attempt to install accounting.

Explanation

Accounting could not be installed on this server for one of the following reasons:

- The server was unavailable to receive the command.
- Other processes cannot be interrupted right now.

Action

Do the operation again. Make sure the workstation is connected to the network. Make sure the server is operating.

1688: An error occurred during an attempt to remove accounting.

Explanation

Accounting could not be removed from this server for one of the following reasons:

- The server was unavailable to receive the command.
- Other processes cannot be interrupted right now.

Action

Do the operation again. Make sure the workstation is connected to the network. Make sure the server is operating.

1689: An error occurred during an attempt to read a property value.

Explanation

A property value was requested to complete this operation, but none was returned. NetWare Directory Services may not have responded, or the request may have been invalid because of the object or property name used.

Action

Do the operation again. Close the utility. Make sure the workstation is connected to the network.

1690: An error occurred during an attempt to write a property value.

Explanation

The utility attempted to update a property value to complete this operation, but the new value was not accepted. NetWare Directory Services may not have responded, or the request may have been invalid because of the object or property name used.

Action

Do the operation again. Close the utility. Make sure the workstation is connected to the network.

1691: That is an invalid charge rate.

Explanation

The values entered for the multiplier and divisor form an invalid charge rate.

Action

See the help screens for instructions on using charge rates.

1692: A maximum of 20 different charge rates are allowed among all services.

Explanation

Only 20 different charge rates are allowed among all 5 resources that accounting tracks. For example, if you have 10 charge rates for disk storage and 10 for service requests, you cannot enter a charge rate for blocks read until you delete one of the other charge rates.

Action

Delete a charge rate from this resource or another resource to free one of the 20 charge rates available. Then reenter the new charge rate.

1694: No Charge cannot be deleted.

Explanation

The No Charge designation cannot be removed from the list.

Action

Do not try to delete No Charge.

1695: The selected charge rate cannot be deleted because it is still in use.

Explanation

You cannot delete a charge rate that is still in use in the day/time grid.

Action

Find all days and times that use this charge rate, and change those days and times to another charge rate. Then select the charge rate that you want to delete and choose Delete again.

1696: A charge rate must be selected to delete.

Explanation

You chose Delete, but did not select a charge rate to delete from the list.

Action

First select a charge rate from the list, then choose Delete again. You can only delete a charge rate that is not in use.

1697: The charge rate could not be added.

Explanation

The charge rate you entered could not be added. One of the following causes probably accounts for this error:

- You entered an invalid charge rate.
- The maximum number of charge rates has been exceeded. Only 20 different charge rates are allowed among all 5 resources that accounting tracks.
- The server has not accepted the new information.

Action

Do the operation again. Make sure the server is operating. Make sure that the charge rate is valid and that the maximum number of charge rates has not been exceeded.

1705: All fields must be filled in.

Explanation

To complete the requested operation, all of the fields displayed must be completed. They could be mandatory properties for this object class, or they could be incomplete.

Action

Fill in all the of the fields shown. See Help for information on each field.

1706: The entry contains invalid characters, or the value is too large.

Explanation

Either the value entered for this field is too large, or it included invalid characters that could not be understood and sent to NetWare Directory Services.

Action

Reenter a smaller value or an entry that does not include invalid characters. See Help for information about valid entries in this dialog.

1710: The server error log file could not be opened.

Explanation

The file containing the server error log could not be opened successfully. The correct volume may be unavailable, or the User object may not have rights to the server.

Action

Make sure the user has appropriate user access rights to the server. Make sure the workstation is connected to the default server. If you still cannot open the error log file, it may be corrupted.

1711: An error occurred during an attempt to close the server error log file.

Explanation

The file containing the server error log could not be closed successfully. The correct volume may be unavailable, or the User object may not have rights to the server. Because you can view but not change the error log, no damage should occur. This problem may indicate another problem, however, and you may want to check the server.

Action

Exit and reenter the utility and view the error log. Make sure the server is operating.

1712: The server error log file could not be read.

Explanation

The file containing the server error log could not be read successfully. The correct volume may be unavailable, or the User object may not have rights to the server.

Action

Make sure the user has appropriate user access rights to the server. Make sure the workstation is connected to the default server. If you still cannot read the error log file, it may be corrupted.

1713: The server error log file could not be cleared.

Explanation

The file containing the server error log could not be erased successfully. The correct volume may be unavailable, even if it was available when you read the error log; or the User object may not have rights to the server.

Action

Clear the error log again. Make sure the user has appropriate user access rights to the server. Make sure the workstation is connected to the default server. If you still cannot clear the error log, it may be corrupted. Exit the utility and reenter it to view the error log.

1714: The Alias of a country can only be named by two characters.

Explanation

Because the name of a Country object can only be two characters, an Alias to a Country also can be named only by two characters.

Action

Enter a new name for the Alias to a Country object, using only two characters.

1715: A Country object must be named by two characters.

Explanation

The name of a Country object must be only two characters long. Use the international two-character code for the country.

Action

Enter a new name for the Country object, using the correct two-character international code. Commonly used codes are found in Help.

1716: The home directory could not be created.

Explanation

A home directory for a user was specified, but cannot be created because of one of the following causes:

- The User object does not have appropriate rights.
- Access to the volume was not possible.
- A problem (such as too many directory entries) exists on the specified volume.
- A file or directory with the specified name already exists.

Action

Do the operation again. Make sure the user has appropriate user access rights to create a directory in the area you have selected. Make sure that there are no problems on the volume.

1720: The TCP/IP address is invalid. All fields must be between 0 and 255.

Explanation

The TCP/IP address entered is invalid because the values entered are not within ranges specified by the TCP/IP protocol.

Action

Enter correct values for each field. All values must be between 0 and 255.

1721 The Volume field must be filled in.

Explanation

In order to complete this operation, a volume must be specified. The volume provides an address to access the file system and its server. Use the Select Object dialog to select an object from the browser if you are not certain what volumes are available.

Action

Complete the volume field by entering a Volume object's name (or complete name, if it is in another context), or by selecting a volume from the Select Object dialog.

1732: You cannot delete a Server object using the NetWare Administrator. Use the Partition Manger.

Explanation

NetWare server objects can be deleted only by using the Partition Manager. Deleting NetWare Server objects using the browser in the NetWare Administrator could make portions of the Directory database inaccessible, because partition replicas could be on the deleted server. Partition Manager will not allow you to delete a server unless all parts of the Directory database are available from other servers.

Action

If you need to to delete NetWare Server objects, use the Partition Manager option .

1733: The server cannot be added. A server connection cannot be established.

Explanation

The utility needed to identify the server that it is receiving information from; however, it was not able to identify its connection ID to add it to the current list of server connections.

Action

Make sure the workstation is connected to the network. Make sure that the needed NetWare Directory Services server is operating. Do the operation again; exit and restart the utility, if necessary.

1736: The server cannot be added. The server's network address cannot be determined.

Explanation

To create a NetWare Server object, NetWare Directory Services must be able to locate the appropriate network address for the physical server.

Action

Specify the correct network address for this server. Make sure the server is operating and available on the network.

1737: The server cannot be added. The server's version cannot be determined.

Explanation

To create a NetWare Server object, NetWare Directory Services must be able to determine which version of NetWare is being used on the server.

Action

Make sure the server is operating and available on the network.

1741: The name of the Directory tree used by this server cannot be determined.

Explanation

The Directory tree used by this server cannot be determined.

Action

Make sure the workstation is connected to the network. Make sure that the needed NetWare Directory Services server is operating. Do the operation again; exit and restart the utility, if necessary.

1742: A preferred server connection cannot be established.

Explanation

The utility needed to identify the specified server as the preferred server, but was not able to identify its connection ID.

Action

Make sure the workstation is connected to the network. Make sure that the needed NetWare Directory Services server is operating. Do the operation again; exit and restart the utility, if necessary.

1743: The Error Log file is too big to display. Only the most recent portion is shown.

Explanation

The server error log file is too large to load entirely into memory for display. Only the most recently logged errors are displayed.

Action

After examining the server error log, clear the error log so that the file will not be too large to display in the future.

1752: You cannot delete a mandatory property.

Explanation

Certain properties must have values for this object to exist in NetWare Directory Services. You cannot remove all values from these mandatory properties.

Action

You can remove all but the last value of a mandatory property.

1850 Form numbers must be in the range 0 to 255.

Explanation

Form numbers must be between 0 and 255.

Action

Reenter a form number with a value from 0 to 255.

1851: The print server is not responding. Printer status failed.

Explanation

An attempt to get the status of the printer by reading properties of the print server failed because the print server did not respond to a request. NetWare Directory Services or the connection to a valid server may be broken.

Action

Make sure the workstation is connected to the the network. Do the operation again.

1852: No attachment has been made to the print server. Printer status failed.

Explanation

An attempt to get the status of the printer by reading properties of the print server failed. The print server did not respond to a request or could not be found. NetWare Directory Services or the connection to a valid server may be broken.

Action

Make sure the workstation is connected to the the network. Do the operation again.

1853: The user is not a print server operator. Printer status failed.

Explanation

In attempt to get the status of the printer by reading properties of the print server failed. The user requesting the status is not authorized to receive information from the print server.

Action

Make sure the user has appropriate user access rights to the print server to get the requested status information.

1854: A printer status error has occurred.

Explanation

An attempt to get the status of the printer by reading properties of the print server failed for an unknown reason. NetWare Directory Services or the connection to a valid server may be broken.

Action

Make sure the workstation is connected to the network. Do the operation again.

1855: The system timer cannot be read. The printer status will not be updated.

Explanation

An internal error has caused the system time to be unavailable. Because an incorrect system time can cause many problems, the printer status is left unchanged.

Action

Make sure that the workstation has a valid connection to a server and that the server is functioning as a time server. Do the operation again.

1856: The system timer cannot be read. The queue job list will not be updated.

Explanation

An internal error has caused the system time to be unavailable. Because an incorrect system time can cause many problems, the queue job list is left unchanged.

Action

Make sure that the workstation has a valid connection to a server and that the server is functioning as a time server. Do the operation again.

1857: You do not have sufficient rights to examine the queue job.

Explanation

The User object does not have appropriate rights to the printing-related objects of this part of the Directory tree to examine the print queue job.

Action

Make sure the user has appropriate user access rights.

1858: An error occurred during an attempt to read the queue job information.

Explanation

The print queue job information could not be read successfully. The correct object may be unavailable, or the User object may not have rights to the correct object.

Action

Make sure the user has appropriate user access rights to the object. Make sure the workstation is connected to the default server. If you still cannot read the queue job information, it may be corrupted.

16385: HCSS has encountered an internal system error.

Explanation

Generic error when none other fits.

16386: HCSS could not create a new directory.

Explanation

Due to spelling, memory constraints or other reasons, the user's request to make a directory was not completed by the server.

Action

Check your spelling.

16387: The directory name is incorrect.

Explanation

The directory name entered is not correct.

Action

Re-enter the correct directory name.

16388: The HCSS directory was not deleted.

Explanation

Directory could not be removed by server, or directory's DeleteInhibit flag could not be cleared.

16389: Choose a NetWare volume.

Explanation

The object class selected for the create operation is not a volume.

Action

Select volume in the Class of New Object list box.

16390: Select an HCSS directory.

Explanation

The directory selected for export could not be verified by the server as an HCSS directory, or the object to be exported is not a directory.

16391: HCSS could not format this media.

Explanation

The media could not be formatted, probably because the media labels entered by the user are unacceptable.

16392: The media label `media label' is invalid.

Explanation

The media label specified is indeed invalid.

Action

If at the Format dialog, spell the name(s) differently. If at the Media Management dialog, the disk must be reformatted.

16395: There are no HCSS subdirectories to export.

Explanation

If at the Export dialog, there are no media to export. If at the Assign dialog, there are no subdirectories available.

16396: Side 1 and Side 2 must have different labels.

Explanation

The names given to the two sides of the media are the same.

Action

Change one of the names.

16397: The HCSS directory name or media label is a duplicate - media label

Explanation

The HCSS domain directory name or the media label name of one of the two sides already exists. All HCSS domain directory names must be unique, and all media label must be unique whether the label is already being used in the same directory or in another.

Action

Change the non-unique name.

16398: The user has insufficient rights on volume. HCSS could not create a directory.

Explanation

The directory create rights have not been granted to the user.

Action

Ask the supervisor for the appropriate rights to be granted, or ask the supervisor to create the directory.

16400: HCSS could not import media.

Explanation

An unidentified error occurred while mounted the media after being inserted by the user into the jukebox. The error prohibits importing the data on the media.

Action

The media is possibly unuseable.

16405: The following directories are not valid: directory list

Explanation

During software inventory of the jukebox, one or more subdirectories existed on the HCSS volume under an HCSS domain directory. However, no media was found in the jukebox with matching media label names. A list of these directories follows the error message.

Action

Import media having labels corresponding to the directories in the list, or manually delete the subdirectories in the list being very careful not to delete a legitimate subdirectory.

16408: This operation can be done only on the HCSS volume. The current HCSS volume is `volume name'.º

Explanation

An attempt was made to create an HCSS domain directory on a volume different than the volume already containing HCSS domain directories, or an attempt was made to assign to a different volume as just stated.

Action

Select the correct volume and repeat the operation which failed.

16410: The optical disk is write-protected and has been ejected.

Explanation

Since HCSS is a dynamic system--data is migrated and demigrated often--the media in the jukebox may not be write-protected as has been detected.

Action

After disk will be ejected, remove the write-protection or import a different media.

16411: HCSS could not export media. Check system console.

Explanation

For reasons other than the media being full, HCSS could not export the media.

Action

Check system console screen on the server to see a more exact reason for this message.

16412: The jukebox is full.

Explanation

All slots in the jukebox are occupied.

Action

In order to import any more media, another media must first be exported.

16413: The selected HCSS directory is set for Don't Migrate.

Explanation

An attempt was made to export a media which has the Don't Migrate flag set. Non-migrated data must be migrated in order to export the media.

Action

Change the volume's Don't Migrate flag by selecting the volume. Then press enter or the right mouse button (and choose Details). Choose Attributes and toggle the state of the Don't Migrate check box.

16414: The media labeled `media label' is full. HCSS attempted to write number bytes of data in excess of the space available.

Explanation

During export, more data needs to be migrated to the media that will fit.

Action

Move (i.e. copy, then delete) enough files from one media-label subtree to another. The number of bytes that needs to be moved is in the message.

16417: HCSS NLMs are possibly not loaded on server.

Explanation

HCSS (at the server) is not responding to requests from the workstation; HCSS NLMs are probably not loaded.

Action

Load HCSS onto the server.

16418: NLMs are older than Snap-in DLLs--they do not support newer features of Parameters dialog.

Explanation

The older HCSS Snap-in to the NetWare Administrator had a Thresholds dialog for Upper/Lower thresholds and the Begin Migration Time. The newer Snap-in has a Parameters dialog which replaces the old Thresholds dialog. The Parameters has everything that the Thresholds dialog did, and much more, so the NLMs need to be current to support the newer features.

Action

Unload the old HCSS NLMs on the server, and load the new NLMs.

16419: HCSS could not create media label directory; it may already exist.

Explanation

In an attempt to create a media-label directory during an Assign, HCSS possibly found a directory/file by that name to already exist.

Action

There are several possible actions for this message. If a media-label directory already exists by that name, then export it. If a non-media-label directory already exists by that name, then delete it. If the data on the media being imported is not important, a last recourse is to reformat it.

16420: HCSS could not complete request due to lack of memory on server.

Explanation

Server memory was low during an Assign.

Action

Retry the operation later when processing is less memory intensive, or unload some NLMs to free up some memory.

16421: HCSS could not restore Netware attributes on some/all files.

Explanation

Some media problems occurred during an Assign, and left some files' NetWare attributes inconsistent between what is on the media and what is on the volume.

Action

Look into log file on server to see which files did not have their attributes properly set, and then do it manually.

16423: HCSS is initializing and cannot respond to your request.

Explanation

HCSS is busy--probably doing an inventory.

Action

Retry within minutes.

16640: One or more of the parameter changes was invalid. See server console screen.

Explanation

When the user attempted to set some HCSS parameters from the client, one or more of those parameters was incorrect and rejected by the server. The valid parameters will have been set.

Action

See the server console screen for information on which parameters failed.

