

## DS Table

1	dsBusError - bus error
2	dsAddressErr - address error
3	dsIllInstErr - illegal instruction error
4	dsZeroDivErr - zero divide error
5	dsChkErr - check trap error
6	dsOvflowErr - overflow trap error
7	dsPrivErr - privilege violation error
8	dsTraceErr - trace mode error
9	dsLineAErr - line 1010 trap error
10	dsLineFErr - line 1111 trap error
11	dsMiscErr - miscellaneous hardware exception error
12	dsCoreErr - unimplemented core routine error
13	dsIrqErr - uninstalled interrupt error
14	dsIOCoreErr - IO Core Error
15	dsLoadErr - Segment Loader Error
16	dsFPerr - Floating point error
17	dsNoPackErr - package 0 not present [List Manager]
18	dsNoPk1 - package 1 not present [Reserved by Apple]
19	dsNoPk2 - package 2 not present [Disk Initialization]
20	dsNoPk3 - package 3 not present [Standard File]
21	dsNoPk4 - package 4 not present [Floating-Point Arithmetic]
22	dsNoPk5 - package 5 not present [Transcendental Functions]
23	dsNoPk6 - package 6 not present [International Utilities]
24	dsNoPk7 - package 7 not present [Binary/Decimal Conversion]
25	dsMemFullErr - out of memory!
26	dsBadLaunch - can't launch file
27	dsFSerr - file system map has been trashed
28	dsStknHeap - stack has moved into application heap
30	dsReinsert - request user to reinsert off-line volume
31	dsNotThe1 - not the disk I wanted (obsolete)
33	negZcbFreeErr - ZcbFree has gone negative
40	dsGreeting - welcome to Macintosh greeting
41	dsFinderErr - can't load the Finder error
42	dsBadStartupDisk - unable to mount boot volume (obsolete)
43	dsSystemFileErr - can't find System file to open (obsolete)
51	dsBadSlotInt - unserviceable slot interrupt
81	dsBadSANEopcode - bad opcode given to SANE Pack4
83	dsBadPatchHeader - SetTrapAddress saw the "come-from" header
84	menuPrgErr - happens when a menu is purged
85	dsMBarNFnd - SysErr -- cannot find MBDF
86	dsHMenuFindErr - SysErr -- recursively defined HMenus
87	dsWDEFnFnd - Could not load WDEF
88	dsCDEFnFnd - Could not load CDEF
89	dsMDEFnFnd - Could not load MDEF
90	dsNoFPU - FPU instruction executed, but machine has no FPU
98	dsNoPatch - Can't patch for particular Model Mac
99	dsBadPatch - Can't load patch resource
101	dsParityErr - memory parity error
102	dsOldSystem - System is too old for this ROM
103	ds32BitMode - booting in 32-bit on a 24-bit sys
104	dsNeedToWriteBootBlocks - need to write new boot blocks
105	dsNotEnoughRAMToBoot - need at least 1.5MB of RAM to boot 7.0
20000	dsShutDownOrRestart - user choice between ShutDown and Restart
20001	dsSwitchOffOrRestart - user choice between Switch off or Restart
20002	dsForcedQuit - allow the user to ExitToShell, return if Cancel
32767	dsSysErr - general system error (catch-all used in DSAT)

## General System (VBL Mgr, Queue, Etc.)

0 noErr - 0 for success

- 1 qErr - queue element not found during deletion
- 2 vTypErr - invalid queue element
- 3 corErr - core routine number out of range
- 4 unimpErr - unimplemented core routine
- 5 SlpTypeErr - invalid queue element
- 8 seNoDB - no debugger installed to handle debugger command

## Color Manager

- 9 iTabPurgErr - from Color2Index/ITabMatch
- 10 noColMatch
- 11 qAllocErr - from MakeTable
- 12 tblAllocErr
- 13 overRun
- 14 noRoomErr
- 15 seOutOfRange - from SetEntry
- 16 seProtErr
- 17 i2CRangeErr
- 18 gdBadDev
- 19 reRangeErr
- 20 selnvRequest
- 21 seNoMemErr

## I/O System

- 17 controlErr - Driver can't respond to Control call
- 18 statusErr - Driver can't respond to Status call
- 19 readErr - Driver can't respond to Read call
- 20 writErr - Driver can't respond to Write call
- 21 badUnitErr - Driver ref num doesn't match unit table
- 22 unitEmptyErr - Driver ref num specifies NIL handle in unit table
- 23 openErr - Requested read/write permission doesn't match driver's  
open permission, or Attempt to open RAM SerD failed
- 24 closErr - Close failed
- 25 dRemovErr - tried to remove an open driver
- 26 dlnstErr - DrvrInstall couldn't find driver in resources
- 27 abortErr - IO call aborted by KillIO
- 27 iIOabortErr - IO abort error (Printing Manager)
- 28 notOpenErr - Couldn't rd/wr/ctl/sts cause driver not opened
- 29 unitTblFullErr - unit table has no more entries
- 30 dceExtErr - dce extension error

## File System

- 33 dirFulErr - Directory full
- 34 dskFulErr - disk full
- 35 nsvErr - no such volume
- 36 ioErr - I/O error (bummers)
- 37 bdNamErr - there may be no bad names in the final system!
- 38 fnOpnErr - File not open
- 39 eofErr - End of file
- 40 posErr - tried to position to before start of file (r/w)
- 41 mFulErr - memory full (open) or file won't fit (load)
- 42 tmfoErr - too many files open
- 43 fnfErr - File not found
- 44 wPrErr - diskette is write protected
- 45 fLckdErr - file is locked
- 46 vLckdErr - volume is locked
- 47 fBsyErr - File is busy (delete)
- 48 dupFNerr - duplicate filename (rename)
- 49 opWrErr - file already open with with write permission
- 50 paramErr - error in user parameter list

- 51 rfNumErr - refnum error
- 52 gfpErr - get file position error
- 53 volOffLinErr - volume not on line error (was Ejected)
- 54 permErr - permissions error (on file open)
- 55 volOnLinErr - drive volume already on-line at MountVol
- 56 nsDrvErr - no such drive (tried to mount a bad drive num)
- 57 noMacDskErr - not a mac diskette (sig bytes are wrong)
- 58 extFSErr - volume in question belongs to an external fs
- 59 fsRnErr - file system internal error: during rename the old  
entry was deleted but could not be restored...
- 60 badMDBErr - bad master directory block
- 61 wrPermErr - write permissions error

## Font Manager

- 64 fontDecError - error during font declaration
- 65 fontNotDeclared - font not declared
- 66 fontSubErr - font substitution occurred

## Disk

- 64 lastDskErr
- 64 noDriveErr - drive not installed
- 65 offLinErr - r/w requested for an off-line drive
- 66 noNybErr - couldn't find 5 nybbles in 200 tries
- 67 noAdrMkErr - couldn't find valid addr mark
- 68 dataVerErr - read verify compare failed
- 69 badCksmErr - addr mark checksum didn't check
- 70 badBtSlpErr - bad addr mark bit slip nibbles
- 71 noDtaMkErr - couldn't find a data mark header
- 72 badDCksum - bad data mark checksum
- 73 badDBtSlp - bad data mark bit slip nibbles
- 74 wrUnderrun - write underrun occurred
- 75 cantStepErr - step handshake failed
- 76 tk0BadErr - track 0 detect doesn't change
- 77 initIWMErr - unable to initialize IWM
- 78 twoSideErr - tried to read 2nd side on a 1-sided drive
- 79 spdAdjErr - unable to correctly adjust disk speed
- 80 seekErr - track number wrong on address mark
- 81 sectNFErr - sector number never found on a track
- 82 fmt1Err - can't find sector 0 after track format
- 83 fmt2Err - can't get enough sync
- 84 verErr - track failed to verify
- 84 firstDskErr

## Serial Ports, PRAM/Clock

- 85 clkRdErr - unable to read same clock value twice
- 86 clkWrErr - time written did not verify
- 87 prWrErr - parameter ram written didn't read-verify
- 88 prInitErr - InitUtil found the parameter ram uninitialized
- 89 rcvrErr - SCC receiver error (framing, parity, OR)
- 90 breakRecd - Break received (SCC)

## AppleTalk

- 91 ddpSktErr - error in socket number
- 92 ddpLenErr - data length too big
- 93 noBridgeErr - no network bridge for non-local send
- 94 lapProtErr - error in attaching/detaching protocol
- 95 excessCollsns - excessive collisions on write
- 97 portInUse - driver Open error code (port is in use)
- 98 portNotCf - driver Open error code (parameter RAM not configured)

for this connection)

## Memory Manager

- 99 memROZErr - hard error in ROZ
- 99 memROZError - hard error in ROZ
- 99 memROZWarn - soft error in ROZ

## Scrap Manager

- 100 noScrapErr - No scrap exists error
- 102 noTypeErr - No object of that type in scrap

## Memory Manager

- 108 memFullErr - Not enough room in heap zone
- 109 nilHandleErr - Handle was NIL in HandleZone or other
- 110 memAdrErr - address was odd, or out of range
- 111 memWZErr - WhichZone failed (applied to free block)
- 112 memPurErr - trying to purge a locked or non-purgeable block
- 113 memAZErr - Address in zone check failed
- 114 memPCErr - Pointer Check failed
- 115 memBCErr - Block Check failed
- 116 memSCErr - Size Check failed
- 117 memLockedErr - trying to move a locked block (MoveHHi)

## HFS

- 120 dirNFErr - Directory not found
- 121 tmwdoErr - No free WDCB available
- 122 badMovErr - Move into offspring error
- 123 wrgVolTypErr - Wrong volume type error: not supported for MFS
- 124 volGoneErr - Server volume has been disconnected.
- 125 updPixMemErr - insufficient memory to update a pixmap
- 127 fsDSIntErr - Internal file system error

## Menu Manager

- 126 dsMBarNFnd - system error code for MBDF not found
- 127 dsHMenuFindErr - could not find HMenu's parent in MenuKey
- 128 userCanceledErr - user canceled the operation status

## HFS FileID

- 130 fidNotFound - no file thread exists
- 131 fidNotAFile - directory specified
- 132 fidExists - file id already exists

## Color Quickdraw & Color Manager

- 145 noMemForPictPlaybackErr
- 147 rgnTooBigError - Region accumulation failed, rgn may be corrupt
- 148 pixMapTooBigErr - passed pixmap is too large
- 149 nsStackErr - not enough stack space for the necessary buffers
- 150 cMatchErr - Color2Index failed to find an index
- 151 cTempMemErr - failed to allocate memory for temporary structures
- 152 cNoMemErr - failed to allocate memory for structure
- 153 cRangeErr - range error on colorTable request
- 154 cProtectErr - colorTable entry protection violation
- 155 cDevErr - invalid type of graphics device
- 156 cResErr - invalid resolution for MakeTable
- 157 cDepthErr - invalid pixel depth
- 158 cParmErr - invalid parameter

## Resource Manager

- 185 badExtResource - extended resource has a bad format.
- 186 CantDecompress - resource bent ("the bends")  
can't decompress a compressed resource
- 192 resNotFound - Resource not found
- 193 resFNotFound - Resource file not found
- 194 addResFailed - AddResource failed
- 195 addRefFailed - AddReference failed
- 196 rmvResFailed - RmveResource failed
- 197 rmvRefFailed - RmveReference failed
- 198 resAttrErr - attribute inconsistent with operation
- 199 mapReadErr - map inconsistent with operation

## Sound Manager

- 200 noHardware - No hardware support for the specified synthesizer
- 201 notEnoughHardware - No more channels for the specified synth
- 203 queueFull - No more room in queue
- 204 resProblem - Problem loading resource
- 205 badChannel - Invalid channel queue length
- 206 badFormat - Handle to 'snd ' resource was invalid
- 207 notEnoughBufferSpace - could not allocate enough memory
  
- 208 badFileFormat - was not type AIFF or was of bad format,corrupt
  
- 209 channelBusy - the Channel is being used for a PFD already
  
- 210 buffersTooSmall - can not operate in the memory allowed
  
- 211 channelNotBusy
- 212 noMoreRealTime - not enough CPU cycles left to add another task
- 220 siNoSoundInHardware
- 221 siBadSoundInDevice - invalid index, SoundInGetIndexedDevice
- 222 siNoBufferSpecified - nil buffer passed to synchronous SPBRecord
- 223 siInvalidCompression - invalid compression type
- 224 siHardDriveTooSlow - hard drive too slow to record to disk
- 225 siInvalidSampleRate - invalid sample rate
- 226 siInvalidSampleSize - invalid sample size
- 227 siDeviceBusyErr - input device already in use
- 228 siBadDeviceName - input device could not be opened
- 229 siBadRefNum - invalid input device reference number
- 230 siInputDeviceErr - input device hardware failure
- 231 siUnknownInfoType - driver returned invalid info type selector
- 232 siUnknownQuality - invalid quality selector returned by driver

## MIDI Manager

- 250 midiNoClientErr - no client with that ID found
- 251 midiNoPortErr - no port with that ID found
- 252 midiTooManyPortsErr - too many ports already installed in system
- 253 midiTooManyConsErr - too many connections made

- 254 midiVConnectErr - pending virtual connection created
- 255 midiVConnectMade - pending virtual connection resolved
- 256 midiVConnectRmvd - pending virtual connection removed
- 257 midiNoConErr - no connection exists between specified ports
- 258 midiWriteErr - couldn't write to all connected ports
- 259 midiNameLenErr - name supplied is longer than 31 characters
- 260 midiDupIDErr - duplicate client ID
- 261 midiInvalidCmdErr - command not supported for port type

## Notification Manager

- 299 nmTypErr - Wrong queue type

## Start Manager

- 290 smSDMInitErr - SDM could not be initialized
- 291 smSRTInitErr - Slot Resource Table could not be initialized
- 292 smPRAMInitErr - Slot Resource Table could not be initialized
- 293 smPriInitErr - Cards could not be initialized
- 300 smEmptySlot - No card in slot
- 301 smCRCFail - CRC check failed for declaration data
- 302 smFormatErr - FHeader Format is not Apple's
- 303 smRevisionErr - Wrong revision level
- 304 smNoDir - Directory offset is Nil
- 305 smDisabledSlot - This Slot is disabled
- 306 smNosInfoArray - No sInfoArray. Memory Mgr error
- 307 smResrvErr - Fatal reserved error. Reserved field <> 0
- 308 smUnExBusErr - Unexpected BusError
- 309 smBLFieldBad - ByteLanes field was bad.
- 310 smFHBlockRdErr - Error occurred during \_sGetFHeader
- 311 smFHBlkDispErr - Error occurred during \_sDisposePtr (Dispose of FHeader block).
- 312 smDisposePErr - \_DisposePointer error
- 313 smNoBoardsRsrc - No Board sResource
- 314 smGetPRErr - Error occurred during \_sGetPRAMRec (See SIMStatus)
- 315 smNoBoardId - No Board Id
- 316 smIntStatVErr - The InitStatusV field was negative after primary or secondary init
- 317 smIntTbIVerr - An error occurred while trying to initialize the Slot Resource Table
- 318 smNoJmpTbl - SDM jump table could not be created
- 319 smBadBoardId - BoardId was wrong, re-init the PRAM record
- 320 smBusErrTO - BusError time out
- 330 smBadRefId - Reference Id not found in List
- 331 smBadList - Bad sList: Id1<Id2<Id3 ... format is not followed
- 332 smReservedErr - Reserved field not zero
- 333 smCodeRevErr - Code revision is wrong
- 334 smCPUErr - Code revision is wrong
- 335 smsPointerNil - LPointer is nil From sOffsetData. If this error occurs, check sInfo rec for more information.
- 336 smNilsBlockErr - Nil sBlock error Don't allocate and try to use a nil sBlock
- 337 smSlotOOBErr - Slot out of bounds error
- 338 smSelOOBErr - Selector out of bounds error
- 339 smNewPErr - \_NewPtr error
- 340 smBlkMoveErr - \_BlockMove error
- 341 smCkStatusErr - Status of slot = fail
- 342 smGetDrvrNamErr - Error occurred during \_sGetDrvrName
- 343 smDisDrvrNamErr - Error occurred during \_sDisDrvrName
- 344 smNoMoresRsrcs - No more sResources
- 345 smsGetDrvrErr - Error occurred during \_sGetDriver.
- 346 smBadsPtrErr - Bad pointer was passed to sCalcsPointer

- 347 smByteLanesErr - NumByteLanes was determined to be zero.
- 348 smOffsetErr - Offset was too big (temporary, should be fixed)
- 349 smNoGoodOpens - No opens were successful in the loop
- 350 smSRTOvrFlErr - SRT over flow
- 351 smRecNotFnd - Record not found in the SRT

## Device Manager Slot Support

- 360 slotNumErr - invalid slot # error
- 400 gcrOnMFMErr - gcr format on high density media error

## Edition Manager

- 450 editionMgrInitErr - edition manager not init'd by this app
- 451 badSectionErr - not a valid SectionRecord
- 452 notRegisteredSectionErr - not a registered SectionRecord
- 453 badEditionFileErr - edition file is corrupt
- 454 badSubPartErr - can not use sub parts in this release
- 460 multiplePublisherWrn - Pub already registered for container
- 461 containerNotFoundWrn - couldn't find editionContainer now
- 462 containerAlreadyOpenWrn - container is open by this section
- 463 notThePublisherWrn - different pub last wrote that container

## SCSI Manager

- 470 scsiBadPBErr - invalid field(s) in the parameter block
- 471 scsiOverrunErr - attempted to transfer too many bytes
- 472 scsiTransferErr - write flag conflicts with data transfer phase
- 473 scsiBusTOErr - bus error during transfer
- 474 scsiSelectTOErr - scsiSelTO exceeded (selection failed)
- 475 scsiTimeOutErr - scsiReqTO exceeded
- 476 scsiBusResetErr - the bus was reset, so your request was aborted
- 477 scsiBadStatus - non-zero (not "Good") status returned
- 478 scsiNoStatusErr - device did not go through a status phase
- 479 scsiLinkFailErr - linked command never executed
- 489 scsiUnimpVctErr - unimplemented routine was called

## SysErrs used instead of inline \$A9FF & \$ABFF

- 490 userBreak - user debugger break
- 491 strUserBreak - user debugger break - display string on stack
- 492 exUserBreak - user debugger break - execute commands on stack

## QuickDraw

- 500 rgnTooBigErr - region too big error

## Text Edit

- 501 teScrapSizeErr - scrap item too big for text edit record

## O/S

- 502 hwParamrErr - bad selector for \_HWPriv

## Process Manager

- 600 procNotFound - no eligible process with specified descriptor
- 601 memFragErr - not enough room to launch app w/spec requirements
- 602 appModeErr - memory mode is 32-bit, but app not 32-bit clean
- 603 protocolErr - app made module calls in improper order
- 604 hardwareConfigErr - hardware configuration not correct for call
- 605 appMemFullErr - application SIZE not big enough for launch
- 606 appsDaemon - app is BG-only, and launch flags disallow this

## Memory Dispatch

- 620 notEnoughMemoryErr - insufficient physical memory
- 621 notHeldErr - specified range of memory is not held
- 622 cannotMakeContiguousErr - cannot make specified range contiguous
- 623 notLockedErr - specified range of memory is not locked
- 624 interruptsMaskedErr - don't call with interrupts masked
- 625 cannotDeferErr - unable to defer additional functions

## DatabaseAccess (Pack 13)

- 800 rcDBNull
- 801 rcDBValue
- 802 rcDBError
- 803 rcDBBadType
- 804 rcDBBadCol
- 805 rcDBBreak
- 806 rcDBExec
- 807 rcDBBadSessID
- 808 rcDBBadSessNum
- 809 rcDBBadDDEV
- 810 rcDBCcancel
- 811 rcDBAsyncNotSupp
- 812 rcDBBadAsyncPB
- 813 rcDBNoHandler
- 814 rcDBWrongVersion
- 815 rcDBPackNotInited
- 816 rcDBStatusCancel

## Help Manager

- 850 hmHelpDisabled - Show Balloons mode off, call to routine ignored
- 851 hmResNotFound
- 852 hmMemFullErr
- 853 hmBalloonAborted - Mouse was moving/wasn't in window port rect
- 854 hmBadHelpData - HMShowMenuBalloon menu & item same as last time
- 855 hmHelpManagerNotInited HMGetHelpMenuHandle help menu not setup
- 856 hmBadSelector
- 857 hmSkippedBalloon - Helpmsg specified a skip balloon
- 858 hmWrongVersion - Help mgr resource was the wrong version
- 859 hmUnknownHelpType - Help msg record contained a bad type
- 860 hmCouldNotLoadPackage
- 861 hmOperationUnsupported - Bad method passed to HMShowBalloon
- 862 hmNoBalloonUp - No balloon visible when HMRemoveBalloon called
- 863 hmCloseViewActive - CloseView active when HMRemoveBalloon called

## PPC Toolbox

- 900 notInitedErr - PPCToolBox not initialized
- 902 nameTypeErr - Invalid locationKindSelector in locationName
- 903 noPortErr - Unable to open port or bad portRefNum
- 904 noGlobalsErr - The system is hosed, better re-boot
- 905 localOnlyErr - Network activity is currently disabled
- 906 destPortErr - Port does not exist at destination
- 907 sessTableErr - Out of session tables, try again later
- 908 noSessionErr - Invalid session reference number
- 909 badReqErr - bad parameter or invalid state for operation
- 910 portNameExistsErr - port is already open (perhaps another app)
- 911 noUserNameErr - user name unknown on destination machine
- 912 userRejectErr - Destination rejected the session request
- 913 noMachineNameErr - user hasn't named his Macintosh
- 914 noToolboxNameErr - A system resource is missing, not too likely



- 915 noResponseErr - unable to contact destination
- 916 portClosedErr - port was closed
- 917 sessClosedErr - session was closed
- 919 badPortNameErr - PPCPortRec malformed
- 922 noDefaultUserErr - user hasn't typed in owners name
- 923 notLoggedInErr - The default userRefNum does not yet exist
- 924 noUserRefErr - unable to create a new userRefNum
- 925 networkErr - An error has ocured in the network, not too likely
- 926 noInformErr - PPCStart failed: dest didn't have inform pending
- 927 authFailErr - unable to authenticate user at destination
- 928 noUserRecErr - Invalid user reference number
- 930 badServiceMethodErr - illegal service type, or not supported
- 931 badLocNameErr - location name malformed
- 932 guestNotAllowedErr - destination port requires authentication

### AppleTalk - NBP

- 1024 nbpBuffOvr - Buffer overflow in LookupName
- 1025 nbpNoConfirm - Name not confirmed on ConfirmName
- 1026 nbpConfDiff - Name confirmed at different socket
- 1027 nbpDuplicate - Duplicate name exists already
- 1028 nbpNotFound - Name not found on remove
- 1029 nbpNISErr - Error trying to open the NIS

### AppleTalk - ASP (XPP driver)

- 1066 aspBadVersNum - Server cannot support this ASP version
- 1067 aspBufTooSmall - Buffer too small
- 1068 aspNoMoreSess - No more sessions on server
- 1069 aspNoServers - No servers at that address
- 1070 aspParamErr - Parameter error
- 1071 aspServerBusy - Server cannot open another session
- 1072 aspSessClosed - Session closed
- 1073 aspSizeErr - Command block too big
- 1074 aspTooMany - Too many clients (server error)
- 1075 aspNoAck - No ack on attention request (server err)

### AppleTalk - ATP

- 1096 reqFailed - SendRequest failed: retry count exceeded
- 1097 tooManyReqs - Too many concurrent requests
- 1098 tooManySkts - Too many concurrent responding-sockets
- 1099 badATPSkt - Bad ATP-responding socket
- 1100 badBuffNum - Bad response buffer number specified
- 1101 noRelErr - No release received
- 1102 cbNotFound - Control Block (TCB or RspCB) not found
- 1103 noSendResp - AddResponse issued without SendResponse
- 1104 noDataArea - No data area for request to MPP
- 1105 reqAborted - SendRequest aborted by RelTCB

### Data Stream Protocol - DSP driver

- 1273 errOpenDenied - open connection request was denied
- 1274 errDSPQueueSize - send or receive queue is too small
- 1275 errFwdReset - read terminated by forward reset
- 1276 errAttention - attention message too long
- 1277 errOpening - open connection request was denied
- 1278 errState - bad connection state for this operation
- 1279 errAborted - control call was aborted
- 1280 errRefNum - bad connection refNum

### HFS

- 1300 fidNotFound - no file thread exists
- 1301 fidExists - file id already exists
- 1302 notAFileErr - directory specified
- 1303 diffVolErr - files on different volumes
- 1304 catChangedErr - catalog has been modified
- 1305 desktopDamagedErr - desktop database files are corrupted
- 1306 sameFileErr - can't exchange a file with itself
- 1307 badFidErr - file id is dangling or doesn't match file number
- 1308 notARemountErr - if \_Mount allows only remounts & doesn't get 1

### AppleTalk - ATP

- 3101 buf2SmallErr - Buffer too small error
- 3102 noMPPErr - No MPP error
- 3103 ckSumErr - Check sum error
- 3104 extractErr - Extraction error
- 3105 readQErr - Read queue error
- 3106 atpLenErr - ATP length error
- 3107 atpBadRsp - ATP bad response error
- 3108 recNotFnd - Record not found
- 3109 sktClosedErr - Socket closed error

### Print Manager w/LaserWriter

- 4096 ??? - No free Connect Control Blocks available
- 4097 ??? - Bad connection reference number
- 4098 ??? - Request already active
- 4099 ??? - Write request too big
- 4100 ??? - Connection just closed
- 4101 ??? - Printer not found, or closed

### File Manager Extensions

- 5000 accessDenied - Incorrect access for this file/folder
- 5006 DenyConflict - Permission/Deny mode conflicts with the current mode in which this fork is already open
- 5015 NoMoreLocks - Byte range locking failure from Server
- 5020 RangeNotLocked - Attempt to unlock an already unlocked range
- 5021 RangeOverlap - Attempt to lock some of an already locked range

### AppleTalk - AFP (XPP driver)

- 5000 afpAccessDenied - AFP access denied
- 5001 afpAuthContinue - AFP authorization continue
- 5002 afpBadUAM - AFP bad UAM
- 5003 afpBadVersNum - AFP bad version number
- 5004 afpBitmapErr - AFP bit map error
- 5005 afpCantMove - AFP can't move error
- 5006 afpDenyConflict - AFP deny conflict
- 5007 afpDirNotEmpty - AFP dir not empty
- 5008 afpDiskFull - AFP disk full
- 5009 afpEofError - AFP End-of-File error
- 5010 afpFileBusy - AFP file busy
- 5011 afpFlatVo - AFP flat volume
- 5012 afpItemNotFound - AFP item not found
- 5013 afpLockErr - AFP lock error
- 5014 afpMiscErr - AFP misc error
- 5015 afpNoMoreLocks - AFP no more locks
- 5016 afpNoServer - AFP no server
- 5017 afpObjectExists - AFP object already exists
- 5018 afpObjectNotFound - AFP object not found
- 5019 afpParmErr - AFP parm error
- 5020 afpRangeNotLocked - AFP range not locked

- 5021 afpRangeOverlap - AFP range overlap
- 5022 afpSessClosed - AFP session closed
- 5023 afpUserNotAuth - AFP user not authorized
- 5024 afpCallNotSupported - AFP call not supported
- 5025 afpObjectTypeErr - AFP object type error
- 5026 afpTooManyFilesOpen - AFP too many files open
- 5027 afpServerGoingDown - AFP server going down
- 5028 afpCantRename - AFP can't rename
- 5029 afpDirNotFound - AFP directory not found
- 5030 afpIconTypeError - AFP icon type error
- 5031 afpVolLocked - Volume is Read-Only
- 5032 afpObjectLocked - Object is M/R/D/W inhibited
- 5033 afpContainsSharedErr - folder being shared has a shared folder
- 5034 afpIDNotFound
- 5035 afpIDExists
- 5036 afpDiffVolErr
- 5037 afpCatalogChanged
- 5038 afpSameObjectErr
- 5039 afpBadIDErr
- 5040 afpPwdSameErr - same password on a mandatory password change
- 5041 afpPwdTooShortErr - password being set is too short
- 5042 afpPwdExpiredErr - password being used is too old
- 5043 afpInsideSharedErr - folder being shared is in a shared folder
- 5044 afpInsideTrashErr - folder being shared is in the trash folder

## SysEnviron

- 5500 envNotPresent - SysEnviron trap not present - returned by glue.
- 5501 envBadVers - Version non-positive
- 5502 envVersTooBig - Version bigger than call can handle

## Gestalt

- 5550 gestaltUnknownErr - Gestalt doesn't know the answer
- 5551 gestaltUndefSelectorErr - Undefined code was passed to Gestalt
- 5552 gestaltDupSelectorErr - Tried to add entry that already existed
- 5553 gestaltLocationErr - Gestalt function ptr wasn't in sysheap

## LaserWriter Driver

- 8132 ???? - Manual Feed time out
- 8133 ???? - General PostScript Error
- 8150 ???? - No LaserWriter chosen
- 8151 ???? - Version mismatch between LaserPrep dictionaries
- 8150 ???? - No LaserPrep dictionary installed
- 8160 ???? - Zoom scale factor out of range

## Picture Utilities

- 11000 pictInfoVersionErr - wrong version of the PictInfo structure
- 11001 pictInfoIDErr - internal consistency check is wrong
- 11002 pictInfoVerbErr - the passed verb was invalid
- 11003 cantLoadPickMethodErr - unable to load the custom pick proc
- 11004 colorsRequestedErr - the number of colors requested was illegal
- 11005 pictureDataErr - the picture data was invalid

## Power Manager

- 13000 pmBusyErr - Pmgr never ready to start handshake
- 13001 pmReplyTOErr - Timed out waiting for reply
- 13002 pmSendStartErr - During send, pmgr did not start hs
- 13003 pmSendEndErr - During send, pmgr did not finish hs
- 13004 pmRecvStartErr - During receive, pmgr did not start hs

-13005 pmRecvEndErr - During receive, pmgr did not finish hs

## Mac TCP

-23000 ipBadLapErr - Bad network configuration  
-23001 ipBadCnfgErr - Bad IP configuration error  
-23002 ipNoCnfgErr - Missing IP or LAP configuration error  
-23003 ipLoadErr - Error in MacTCP load  
-23004 ipBadAddr - Error in getting address  
-23005 connectionClosing - Connection in closing  
-23006 invalidLength  
-23007 connectionExists - Request conflicts with existing connection  
-23008 connectionDoesntExist - Connection does not exist  
-23009 insufficientResources - Insufficient rsrcs to perform request  
-23010 invalidStreamPtr  
-23011 streamAlreadyOpen  
-23012 connectionTerminated  
-23013 invalidBufPtr  
-23014 invalidRDS  
-23014 invalidWDS  
-23015 openFailed  
-23016 commandTimeout  
-23017 duplicateSocket  
-23030 ipOpenProtErr - Can't open new protocol, table full  
-23031 ipCloseProtErr - Can't find protocol to close  
-23032 ipDontFragErr - Packet too large to send w/o fragmenting  
-23033 ipDestDeadErr - Destination not responding  
-23034 ipBadWDSerr - Error in WDS format  
-23035 icmpEchoTimeoutErr - ICMP echo timed-out  
-23036 ipNoFragMemErr - No memory to send fragmented pkt  
-23037 ipRouteErr - Can't route packet off-net  
-23041 nameSyntaxErr  
-23042 cacheFault  
-23043 noResultProc  
-23044 noNameServer  
-23045 authNameErr  
-23046 noAnsErr  
-23047 dnrErr  
-23048 outOfMemory

## Font Manager

-32615 fontNotOutlineErr - bitmap passed, routine does outlines only

## Primary or Secondary Init Code

-32768 svTempDisable - Temporarily disable card but run primary init  
-32640 svDisabled - Reserve -32640 to -32768 for Apple temp disables

..... Slightly Obscure Errors...

## Internal File System

1 chNoBuf - no free cache buffers (all in use)  
2 chInUse - requested block in use  
3 chnotfound - requested block not found  
4 chNotInUse - block being released was not in use  
16 fxRangeErr - file position beyond mapped range  
17 fxOvFlErr - extents file overflow  
32 bnotfound - record not found  
33 btexists - record already exists  
34 btnospace - no available space  
35 btnoFit - record doesn't fit in node

36 btbadNode - bad node detected  
37 btbadHdr - bad BTree header record detected  
48 cmnotfound - CNode not found  
49 cmexists - CNode already exists  
50 cmnotempty - directory CNode not empty (valence = 0)  
51 cmRootCN - invalid reference to root CNode  
52 cmbadnews - detected bad catalog structure  
53 cmFThdDirErr - thread belongs to a directory not a file  
54 cmFThdGone - file thread doesn't exist  
64 dsBadRotate - bad BTree rotate

## Slot Declaration ROM Manager

1 silnitSDTblErr - slot int dispatch table couldn't be initialized  
2 silnitVBLQsErr - VBLqueues for all slots couldn't be initialized  
3 silnitSPTblErr - slot priority table could not be initialized  
10 sdmJTInitErr - SDM Jump Table could not be initialized  
11 sdmInitErr - SDM could not be initialized  
12 sdmSRTInitErr - Slot Resource Table could not be initialized  
13 sdmPRAMInitErr - Slot PRAM could not be initialized  
14 sdmPriInitErr - Cards could not be initialized

## HD20 Driver

16 wrtHsLw - HSHK low before starting  
17 wrtHSLwTO - Time out waiting for HSHK to go low  
19 wrtHSHighTO - Time out waiting for HSHK to go high  
32 rdHsHi - HSHK high before starting  
33 rdSyncTO - Time out waiting for sync (\$AA) bye  
34 rdGroupTO - Time out waiting for group  
36 rdHoffSyncTO - Time out waiting for sync after holdoff  
37 rdHsHiTO - Time out waiting for HSHK high  
38 rdChksumErr - Checksum error on response packet  
48 invalidResp - First byte in response packet was wrong  
49 sqncNumErr - Sequence number in response packet was wrong  
50 dNumberErr - Drive number in response packet was wrong  
64 noResp - No response packet ever received

## SCSI Manager

2 scCommErr - Communications error (operations timeout)  
3 scArbNBErr - Arbitration failed during SCSIGet - Bus busy  
4 scBadparmsErr - Bad parameter or TIB opcode  
5 scPhaseErr - SCSI bus not in correct phase for operation  
6 scCompareErr - SCSI Manager busy with another operation when  
SCSIGet was called  
7 scMgrBusyErr - SCSI Manager busy with another operation when  
SCSIGet was called  
8 scSequenceErr - Attempted operation is out of sequence - e.g.,  
calling SCSISelect before doing SCSIGet  
9 scBusTOErr - Bus timeout before data ready on SCIRBlind and  
SCSIWBlind  
10 scComplPhaseErr - SCSIComplete failed - bus not in Status phase

## Connection Manager

0 cmNoErr  
1 cmRejected  
2 cmFailed  
3 cmTimeOut  
4 cmNotOpen  
5 cmNotClosed  
6 cmNoRequestPending

7 cmNotSupported  
8 cmNoTools  
9 cmUserCancel  
11 cmUnknownError  
-1 cmGenericError

### File Transfer Manager

0 ftNoErr  
1 ftRejected  
2 ftFailed  
3 ftTimeOut  
4 ftTooManyRetry  
5 ftNotEnoughDspace  
6 ftRemoteCancel  
7 ftWrongFormat  
8 ftNoTools  
9 ftUserCancel  
10 ftNotSupported  
11 ftUnknownError  
-1 ftGenericError

### Terminal Manager

0 tmNoErr  
1 tmNotSent  
2 tmEnvironsChanged  
7 tmNotSupported  
8 tmNoTools  
11 tmUnknownError  
-1 tmGenericError

This list maintained with MPW SysErr.a  
Last change - Version 3.1 - Wednesday, June 12, 1991