



Negative Error Codes (0 to -99)

General System Errors (VBL Mgr, Queue)

- 0 noErr 0 for success "OR"
- 0 smNotTruncated No truncation necessary
- 1 qErr queue element not found during deletion "OR"
- 1 smTruncErr Truncation indicator alone is wider than the specified width
- 2 vTypErr invalid queue element
- 3 corErr core routine number out of range
- 4 unimpErr unimplemented core routine
- 5 SlpTypeErr invalid queue element
- 8 seNoDB no debugger installed to handle debugger command

Color Manager Errors

- 9 iTabPurgErr from Color2Index/ITabMatch
- 10 noColMatch from Color2Index/ITabMatch
- 11 qAllocErr from MakeITable
- 12 tblAllocErr from MakeITable
- 13 overRun from MakeITable
- 14 noRoomErr from MakeITable
- 15 seOutOfRange from SetEntry
- 16 seProtErr from SetEntry
- 17 i2CRangeErr from SetEntry
- 18 gdBadDev from SetEntry
- 19 reRangeErr from SetEntry
- 20 seInvRequest from SetEntry
- 21 seNoMemErr from SetEntry

I/O System Errors

- 17 controlErr Driver can't respond to Control call
- 18 statusErr Driver can't respond to Status call
- 19 readErr Driver can't respond to Read call
- 20 writErr Driver can't respond to Write call
- 21 badUnitErr Driver ref num doesn't match unit table
- 22 unitEmptyErr Driver ref num specifies NIL handle in unit table
- 23 openErr Requested read/write permission doesn't match driver's open permission, or Attempt to open RAM serial Driver failed
- 24 closErr Close failed; Permission to close .MPP driver was denied
- 25 dRemovErr tried to remove an open driver
- 26 dInstErr DrvrInstall couldn't find driver in resources
- 27 abortErr IO call aborted by KillIO; Publisher has written a new edition "OR"
- 27 iIOAbortErr IO abort error (Printing Manager)
- 28 notOpenErr Couldn't rd/wr/ctl/sts cause driver not opened
- 29 unitTblFullErr Unit table has no more entries
- 30 dceExtErr dce extension error

File System Errors

- 33 dirFulErr Directory full
- 34 dskFulErr Disk full
- 35 nsvErr No such volume; volume not found
- 36 ioErr I/O error
- 37 bdNamErr Bad file name; there may be no bad names in the final system!
- 38 fnOpnErr File not open
- 39 eofErr End of file; no additional data in the format
- 40 posErr Tried to position to before start of file (r/w)
- 41 mFulErr Memory full (open) or file won't fit (load)
- 42 tmfoErr too many files open
- 43 fnfErr File not found; Folder not found; Edition container not found; Target not found
- 44 wPrErr Disk is write-protected; Volume is locked through hardware
- 45 fLckdErr File is locked
- 45 vLckdErr Publisher writing to an edition
- 46 vLckdErr Volume is locked through software
- 47 fBsyErr File is busy (delete); Section doing I/O
- 48 dupFNerr Duplicate filename (rename); File found instead of folder
- 49 opWrErr File already open with write permission
- 50 paramErr Error in user parameter list
- 51 rfNumErr Reference number invalid
- 52 gfpErr Get file position error
- 53 volOffLinErr Volume is off line
- 54 permErr Software lock on file; Not a subscriber [permissions error on file open]
- 55 volOnLinErr drive volume already on-line at MountVol
- 56 nsDrvErr no such drive (tried to mount a bad drive num)
- 57 noMacDskErr not a Macintosh disk (sig bytes are wrong)
- 58 extFSErr External file system __ file system identifier is nonzero
- 59 fsRnErr file system internal error: during rename the old entry was deleted but could not be restored.
- 60 badMDBErr bad master directory block
- 61 wrPermErr Write permissions error; Not a publisher

Font Manager Errors

- 64 fontDecError error during font declaration
- 65 fontNotDeclared font not declared
- 66 fontSubErr font substitution occurred

Disk, Serial Ports, Clock Specific Errors

- 64 lastDskErr
- 64 noDriveErr drive not installed
- 65 offLinErr r/w requested for an off-line drive
- 66 noNybErr couldn't find 5 nybbles in 200 tries
- 67 noAdrMkErr couldn't find valid addr mark
- 68 dataVerErr read verify compare failed
- 69 badCksmErr addr mark checksum didn't check
- 70 badBtSlpErr bad addr mark bit slip nibbles
- 71 noDtaMkErr couldn't find a data mark header
- 72 badDCksm bad data mark checksum
- 73 badDBtSlp bad data mark bit slip nibbles
- 74 wrUnderrun write underrun occurred
- 75 cantStepErr step handshake failed
- 76 tk0BadErr track 0 detect doesn't change

- 77 initIWMErr unable to initialize IWM
- 78 twoSideErr tried to read 2nd side on a 1-sided drive
- 79 spdAdjErr unable to correctly adjust disk speed
- 80 seekErr track number wrong on address mark
- 81 sectNFErr sector number never found on a track
- 82 fmt1Err can't find sector 0 after track format
- 83 fmt2Err can't get enough sync
- 84 verErr track failed to verify
- 84 firstDskErr
- 85 clkRdErr unable to read same clock value twice
- 86 clkWrErr time written did not verify
- 87 prWrErr parameter RAM written didn't read-verify
- 88 prInitErr InitUtil found the parameter RAM uninitialized
- 89 rcvrErr SCC receiver error (framing, parity, OR)
- 90 breakRecd Break received (SCC)

AppleTalk Errors

- 91 ddpSktErr Error opening socket "OR"
- 91 eMultiErr Invalid address or table is full
- 92 ddpLenErr Data length too big "OR"
- 92 eLenErr Packet too large or first entry of the write-data structure didn't contain the full 14-byte header
- 93 noBridgeErr No router available [for non-local send]
- 94 lapProtErr error in attaching/detaching protocol "OR"
- 94 LAPPProtErr Protocol handler is already attached, node's protocol table is full, protocol not attached, or protocol handler pointer was not 0
- 95 excessCollsns Hardware error [excessive collisions on write]
- 97 portInUse driver Open error code (port is in use)
- 98 portNotCf driver Open error code (parameter RAM not configured for this connection)
- 99 memROZErr hard error in ROZ
- 99 memROZError hard error in ROZ
- 99 memROZWarn soft error in ROZ