



Negative Error Codes (-200 to -261)

Sound Manager Errors

- 200 noHardware Required sound hardware not available [no hardware support for the specified synthesizer]
- 201 notEnoughHardware Insufficient hardware available [no more channels for the specified synthesizer]
- 203 queueFull No room in the queue
- 204 resProblem Problem loading the resource
- 205 badChannel Channel is corrupt or unusable [invalid channel queue length]
- 206 badFormat Resource is corrupt or unusable [handle to 'snd ' resource was invalid]
- 207 notEnoughBufferSpace Insufficient memory available
- 208 badFileFormat File is corrupt or unusable, or not AIFF or AIFF-C
- 209 channel Channel is busy
- 210 buffersTooSmall Buffer is too small
- 211 channelNotBusy Channel not currently used
- 212 noMoreRealTime Not enough CPU time available
- 213 badParam A parameter is incorrect
- 220 siNoSoundInHardware No sound input hardware available
- 221 siBadSoundInDevice Invalid sound input device
- 222 siNoBufferSpecified No buffer specified
- 223 siInvalidCompression Invalid compression type
- 224 siHardDiskTooSlow Hard drive too slow to record
- 225 siInvalidSampleRate Invalid sample rate
- 226 siInvalidSampleSize Invalid sample size
- 227 siDeviceBusyErr Sound input device is busy
- 228 siBadDeviceName Invalid device name
- 229 siBadRefNum Invalid reference number
- 230 siInputDeviceErr Input device hardware failure
- 231 siUnknownInfoType Unknown type of information
- 232 siUnknownQuality Unknown quality

MIDI Manager Errors

- 250 midiNoClientErr no client with that ID found
- 251 midiNoPortErr no port with that ID found
- 252 midiTooManyPortsErr too many ports already installed in the system
- 253 midiTooManyConsErr too many connections made
- 254 midiVConnectErr pending virtual connection created
- 255 midiVConnectMade pending virtual connection resolved
- 256 midiVConnectRmvd pending virtual connection removed
- 257 midiNoConErr no connection exists between specified ports
- 258 midiWriteErr couldn't write to all connected ports
- 259 midiNameLenErr name supplied is longer than 31 characters
- 260 midiDupIDErr duplicate client ID
- 261 midiInvalidCmdErr command not supported for port type

Article Created: 19 February 1986
Article Reviewed/Updated: 20 November 1995

This article is one of many available through the Apple Fax center. For a complete list of available Fax documents, search the Tech Info Library for Apple Fax Document Index or call the Apple Fax line at 1-800-505-0171 and select document number 20000 (Apple Fax - Document Index - Product Support Literature). The Apple Fax center is available free of charge 24 hours a day, 7 days a week.

Article Change History:

20 Nov 1995 - Added new keyword and reviewed article for technical accuracy.
19 Oct 1994 - Added negative error codes.
12 Oct 1994 - Added keyword, description, and troubleshooting tips.
30 Nov 1993 - Reviewed and reorganized.

Support Information Services
Copyright 1986-94, Apple Computer, Inc.
01749: TIL