



## Negative Error Codes (-299 to -5553)

### Notification Manager Error

-299 nmTypErr Invalid qType- must be ORD(nmType)

### Start Manager Errors

- 290 smSDMInitErr SDM could not be initialized.
- 291 smSRTInitErr Slot Resource Table could not be initialized.
- 292 smPRAMInitErr Slot Resource Table could not be initialized.
- 293 smPriInitErr Cards could not be initialized.
- 300 smEmptySlot No card in slot
- 301 smCRCFail CRC check failed for declaration data
- 302 smFormatErr FHeader Format is not Apple's
- 303 smRevisionErr Wrong revision level
- 304 smNoDir Directory offset is Nil
- 305 smLWTstBad Long Word test field \$5A932BC7.
- 306 smNosInfoArray No sInfoArray. Memory Mgr error.
- 307 smResrvErr Fatal reserved error. Reserved field 0.
- 308 smUnExBusErr Unexpected Bus Error
- 309 smBLFieldBad ByteLanes field was bad.
- 310 smFHBlockRdErr Error occurred during \_sGetFHeader.
- 311 smFHBlkDispErr Error occurred during \_sDisposePtr (Dispose of FHeader block).
- 312 smDisposePErr \_DisposePointer error
- 313 smNoBoardsRsrc No Board sResource.
- 314 smGetPErr Error occurred during \_sGetPRAMRec (See SIMStatus).
- 315 smNoBoardId No Board Id.
- 316 smIntStatVErr The InitStatusV field was negative after primary or secondary init.
- 317 smIntTblVErr An error occurred while trying to initialize the Slot Resource Table.
- 318 smNoJmpTbl SDM jump table could not be created.
- 319 smBadBoardId BoardId was wrong, re-init the PRAM record.
- 320 smBusErrTO BusError time out.
- 330 smBadRefId Reference Id not found in list
- 331 smBadList Bad sResource [sList] structure:Id1
- 332 smReservedErr Reserved field not zero
- 333 smCodeRevErr Code revision is wrong
- 334 smCPUErr Code revision is wrong
- 335 smsPointerNil LPointer is nil From sOffsetData. Check sInfo rec for more information.
- 336 smNilsBlockErr Nil sBlock error Don't allocate and try to use a nil sBlock
- 337 smSlotOOBErr Slot out of bounds error
- 338 smSelOOBErr Selector out of bounds error; function not implemented
- 339 smNewPErr \_NewPtr error
- 340 smBlkMoveErr \_BlockMove error
- 341 smCkStatusErr Status of slot = fail.
- 342 smGetDrvrNamErr Error occurred during \_sGetDrvrName.
- 343 smDisDrvrNamErr Error occurred during \_sDisDrvrName.
- 344 smNoMoresRsrcs No more sResources \*OR\*
- 344 smNoMoresResources Specified sResource data structure not found
- 345 smsGetDrvrErr Error occurred during \_sGetDriver.
- 346 smBadSPtrErr Bad pointer was passed to sCaldSPointer function
- 347 smByteLanesErr ByteLanes field in card's format block was determined to be zero

- 348 smOffsetErr Offset was too big (temporary, should be fixed)
- 349 smNoGoodOpens No opens were successful in the loop.
- 350 smSRTOvrFlErr SRT over flow.
- 351 smRecNotFnd Record not found in the SRT. Device Manager Slot Support Errors
- 360 slotNumErr invalid slot # error
- 400 gcrOnMFMErr gcr format on high density media error

## Edition Manager Errors

- 450 editionMgrInitErr Manager not initialized or could not load package
- 451 badSectionErr Not a valid section type
- 452 notRegisteredSectionErr Not registered
- 454 badSubPartErr Bad edition container spec or invalid edition container
- 460 multiplePublisherWrn Already is a publisher
- 461 containerNotFoundWrn Alias was not resolved
- 463 notThePublisherWrn Not the publisher SCSI Manager Errors
- 470 scsiBadPBErr invalid field(s) in the parameter block
- 471 scsiOverrunErr attempted to transfer too many bytes
- 472 scsiTransferErr write flag conflicts with data transfer phase
- 473 scsiBusTOErr bus error during transfer
- 474 scsiSelectTOErr scsiSelTO exceeded (selection failed)
- 475 scsiTimeOutErr scsiReqTO exceeded
- 476 scsiBusResetErr the bus was reset, so your request was aborted
- 477 scsiBadStatus non-zero (not "Good") status returned
- 478 scsiNoStatusErr device did not go through a status phase
- 479 scsiLinkFailErr linked command never executed
- 489 scsiUnimpVctErr unimplemented routine was called SysErrs used instead of inline \$A9FF & \$ABFF
- 490 userBreak user debugger break
- 491 strUserBreak user debugger break - display string on stack
- 492 exUserBreak user debugger break - execute commands on stack

## QuickDraw Error

- 500 rgnTooBigErr Bitmap would convert into a region greater than 64 KB

## Text Edit Error

- 501 teScrapSizeErr scrap item too big for text edit record

## O/S Error

- 502 hwParamrErr bad selector for \_HWPriv

## Processes Errors

- 600 procNotFound No eligible process with specified process serial number
- 601 memFragErr Not enough room to launch application with special requirements
- 602 appModeErr Memory mode is 32-bit, but application is not 32-bit clean
- 603 protocolErr app made module calls in improper order
- 604 hardwareConfigErr hardware configuration not correct for call
- 605 appMemFullErr Partition size specified in 'SIZE' resource is not big enough for launch
- 606 applsDaemon Application is background-only
- 607 bufferIsSmall Buffer is too small
- 608 noOutstandingHLE No outstanding high-level event
- 609 connectionInvalid Connection is invalid
- 610 noUserInteractionAllowed Attempted PostHighLevelEvent from background and no session yet

#### established Memory Dispatch Errors

- 620 notEnoughMemoryErr Insufficient physical memory
- 621 notHeldErr Specified range of memory is not held
- 622 cannotMakeContiguousErr Cannot make specified range contiguous
- 623 notLockedErr Specified range of memory is not locked
- 624 interruptsMaskedErr Called with interrupts masked
- 625 cannotDeferErr Unable to defer additional user functions

#### DatabaseAccess (Pack 13) Errors

- 800 rcDBNull The data item was NULL
- 801 rcDBValue Data available or successfully retrieved
- 802 rcDBError Error executing function
- 803 rcDBBadType Next data item not of requested data type
- 804 rcDBBreak Function timed out
- 805 rcDBExec Query currently executing
- 806 reDBBadSessID Session ID is invalid
- 807 rcDBBadSessNum Invalid session number
- 808 rcDBBadDDEV Couldn't find the specified database extension, or error occurred in opening database extension
- 809 rcDBAsyncNotSupp The database extension does not support asynchronous calls
- 810 rcDBBadAsyncPB Invalid parameter block specified
- 811 rcDBNoHandler There is no handler for this data type installed for the current application
- 812 rcDBWrongVersion Wrong version number
- 813 rcDBPackNotInited The InitDBPack function has not yet been called

#### Help Manager Errors

- 850 hmHelpDisabled Help balloons are not enabled
- 851 hmResNotFound ????
- 852 hmMemFullErr ????
- 853 hmBalloonAborted Because of constant cursor movement, the help balloon wasn't displayed
- 854 hmSameAsLastBalloon Menu and item are same as previous menu and item
- 855 hmHelpManagerNotInited Help menu not set up
- 856 hmBadSelector ????
- 857 hmSkippedBalloon No balloon content to fill in
- 858 hmWrongVersion Wrong version of Help Manager resource
- 859 hmUnknownHelpType Help message record contained a bad type
- 860 hmCouldNotLoadPackage ????
- 861 hmOperationUnsupported Bad method parameter
- 862 hmNoBalloonUp No balloon showing
- 863 hmCloseViewActive User using CloseView won't let you remove balloon

#### AppleTalk - PPC Toolbox Errors

- 900 notInitedErr PPC Toolbox has not been initialized yet
- 902 nameTypeErr Invalid or inappropriate locationKindSelector in location name
- 903 noPortErr Invalid port name; Unable to open port or bad port reference number
- 904 noGlobalsErr System unable to allocate memory, critical error
- 905 localOnlyErr Network activity is currently disabled
- 906 destPortErr Port does not exist at destination
- 907 sessTableErr PPC Toolbox is unable to create a session
- 908 noSessionErr Invalid session reference number
- 909 badReqErr Bad parameter or invalid state for this operation
- 910 portNameExistsErr Another port is already open with this name
- 911 noUserNameErr User name unknown on destination machine
- 912 userRejectErr Destination rejected the session request
- 915 noResponseErr Unable to contact application

- 916 portClosedErr The port was closed
- 917 sessClosedErr The session has closed
- 919 badPortNameErr PPC port record is invalid
- 922 noDefaultUserErr User has not specified owner name in Sharing Setup control panel
- 923 notLoggedInErr Default user reference number does not yet exist
- 924 noUserRefErr Unable to create a new user reference number
- 925 networkErr An error has occurred in the network
- 926 noInformErr PPCStart failed because target application did not have an inform pending
- 927 authFailErr User's password is wrong
- 928 noUserRecErr Invalid user reference number
- 930 badServiceMethodErr Service method is other than ppcServiceRealTime
- 931 badLocNameErr Location name is invalid
- 932 guestNotAllowedErr Destination port requires authentication

## AppleTalk - NBP Errors

- 1024 nbpBuffOvr Buffer overflow in LookupName
- 1025 nbpNoConfirm Name not confirmed on ConfirmName
- 1026 nbpConfDiff Name confirmed at different socket
- 1027 nbpDuplicate Duplicate name exists already
- 1028 nbpNotFound Name not found on remove
- 1029 nbpNISErr Error trying to open the NIS

## ASP Errors (XPP driver)

- 1066 aspBadVersNum Server cannot support this ASP version
- 1067 aspBufTooSmall Buffer too small
- 1068 aspNoMoreSess No more sessions on server
- 1069 aspNoServers No servers at that address
- 1070 aspParamErr Parameter error
- 1071 aspServerBusy Server cannot open another session
- 1072 aspSessClosed Session closed
- 1073 aspSizeErr Command block too big
- 1074 aspTooMany Too many clients (server error)
- 1075 aspNoAck No ack on attention request (server err)

## AppleTalk - ATP Errors

- 1096 reqFailed Request to contact router failed: retry count exceeded
- 1097 tooManyReqs Too many concurrent requests
- 1098 tooManySkts Too many concurrent responding-sockets
- 1099 badATPSkt Bad ATP-responding socket
- 1100 badBuffNum Bad response buffer number specified
- 1101 noRelErr No release received
- 1102 cbNotFound Control Block not found; no pending asynchronous calls
- 1103 noSendResp AddResponse issued without SendResponse
- 1104 noDataArea No data area for request to MPP
- 1105 reqAborted ERdCancel function called for this ERead [SendRequest aborted by RelTCB]

## Data Stream Protocol - DSP driver Errors

- 1273 errOpenDenied Open request denied by recipient
- 1274 errDSPQueueSize Send or receive queue is too small
- 1275 errFwdReset Read terminated by forward reset
- 1276 errAttention Attention message too long
- 1277 errOpening Attempt to open connection failed
- 1278 errState Bad connection state for this operation

- 1279 errAborted Request aborted by dspRemove or dspClose function
- 1280 errRefNum Bad connection reference number

## HFS Errors

- 1300 fidNotFound File ID not found [No file thread exists]
- 1301 fidExists File id already exists
- 1302 notAFileErr Specified file is a directory
- 1303 diffVolErr Files on different volumes
- 1304 catChangedErr Catalog has changed and CatPosition may be invalid
- 1305 desktopDamagedErr The desktop database has become corrupted - the Finder will fix this, but if your application is not running with the Finder, use DTRreset or DTDelete

## AppleEvent Errors

- 1700 errAECOercionFail Data could not be coerced to the requested descriptor type
- 1701 errAEDescNotFound Descriptor record was not found
- 1702 errAECorruptData Data in an Apple event could not be read
- 1703 errAEWrongDataType Wrong descriptor type
- 1704 errAENotAEDesc Not a valid descriptor record
- 1705 errAEBadListItem Operation involving a list item failed
- 1706 errAENewerVersion Need a newer version of the Apple Event Manager
- 1707 errAENotAppleEvent Event is not an Apple event
- 1708 errAEEventNotHandled Event wasn't handled by an Apple event handler
- 1709 errAEReplyNotValid AEResetTimer was passed an invalid reply
- 1710 errAEUnknownSendMode Invalid sending mode was passed
- 1711 errAEWaitCanceled User canceled out of wait loop for reply or receipt
- 1712 errAETimeout Apple event timed out
- 1713 errAENoUserInteraction No user interaction allowed
- 1714 errAENotASpecialFunction Wrong keyword for a special function
- 1715 errAEParamMissed Handler did not get all required parameters
- 1716 errAEUnknownAddressType Unknown Apple event address type
- 1717 errAEHandlerNotFound No handler found for an Apple event or a coercion
- 1718 errAEReplyNotArrived Reply has not yet arrived
- 1719 errAEIllegalIndex Not a valid list index

## AppleTalk - ATP Errors

- 3101 buf2SmallErr Packet too large for buffer; partial data returned
- 3102 noMPPerr No MPP error
- 3103 ckSumErr Check sum error
- 3104 extractErr Extraction error
- 3105 readQErr Read queue error
- 3106 atpLenErr ATP length error
- 3107 atpBadRsp ATP bad response error
- 3108 recNotFnd Record not found
- 3109 sktClosedErr Socket closed error

## Print Manager w/LaserWriter Errors

- 4096 ??? No free Connect Control Blocks available
- 4097 ??? Bad connection reference number
- 4098 ??? Request already active
- 4099 ??? Write request too big
- 4100 ??? Connection just closed
- 4101 ??? Printer not found, or closed

## File Manager Extensions Errors

- 5000 accessDenied Incorrect access for this file/folder
- 5006 DenyConflict Permission/Deny mode conflicts with the current mode in which this fork is already open
- 5015 NoMoreLocks Byte range locking failure from Server
- 5020 RangeNotLocked Attempt to unlock an already unlocked range
- 5021 RangeOverlap Attempt to lock some of an already locked range

## AFP Errors (XPP driver)

- 5000 afpAccessDenied AFP Access denied
- 5001 afpAuthContinue AFP Authorization continue
- 5002 afpBadUAM AFP Bad UAM
- 5003 afpBadVersNum AFP Bad version number
- 5004 afpBitmapErr AFP Bit map error
- 5005 afpCantMove AFP Can't move error
- 5006 afpDenyConflict AFP Deny conflict
- 5007 afpDirNotEmpty AFP Dir not empty
- 5008 afpDiskFull AFP Disk full
- 5009 afpEofError AFP End-of-File error
- 5010 afpFileBusy AFP File busy
- 5011 afpFlatVo AFP Flat volume
- 5012 afpItemNotFound AFP Information not found
- 5013 afpLockErr AFP Lock error
- 5014 afpMiscErr AFP Misc error
- 5015 afpNoMoreLocks AFP No more locks
- 5016 afpNoServer AFP No server
- 5017 afpObjectExists AFP Object already exists
- 5018 afpObjectNotFound AFP Object not found
- 5019 afpParmErr AFP Parm error
- 5020 afpRangeNotLocked AFP Range not locked
- 5021 afpRangeOverlap AFP Range overlap
- 5022 afpSessClosed AFP Session closed
- 5023 afpUserNotAuth AFP User not authorized
- 5024 afpCallNotSupported AFP Call not supported
- 5025 afpObjectTypeErr AFP Object type error
- 5026 afpTooManyFilesOpen AFP Too many files open
- 5027 afpServerGoingDown AFP Server going down
- 5028 afpCantRename AFP Can't rename
- 5029 afpDirNotFound AFP Directory not found
- 5030 afpIconTypeError Size of new icon and one it replaces don't match
- 5031 afpVolLocked Volume is Read-Only
- 5032 afpObjectLocked Object is M/R/D/W inhibited

## SysEnviron Errors

- 5500 envNotPresent SysEnviron trap not present - returned by glue.
- 5501 envBadVers Version non-positive
- 5502 envVersTooBig Version bigger than call can handle

## Gestalt Errors

- 5550 gestaltUnknownErr Could not obtain the response
- 5551 gestaltUndefSelectorErr Undefined selector
- 5552 gestaltDupSelectorErr Selector already exists
- 5553 gestaltLocationErr Function not in system heap

Article Change History:

29 Nov 1995 - Corrected minor typo.

07 Dec 1994 - Corrected spelling.

25 Sep 1992 - Reviewed for technical accuracy.

Support Information Services

Copyright 1992-95, Apple Computer, Inc.

Keywords: sys7, ktopil