<u>Supported Systems Software: 7.5.3</u> <u>SCSI: DB-25</u> <u>Serial Ports: 2</u> <u>Sound Output: 16-bit stereo 44.1 KHz sample rate</u> <u>ADB: 1, plus additional port for PS/2 keyboard</u> <u>Ethernet: Add-in card</u> <u>Machine Gestalt ID: ???</u>

Minutiae:

Improve performance by installing a Newer Technology level-2 cache DIMM, part # 7CC512C.

<u>APS MoPower 604e240 can take only EDO DIMMs. It does not</u> <u>support interleaved memory. The three DIMM sockets are NOT</u> <u>identical. The first socket, which comes stock with a 16 MB DIMM</u> <u>installed, can only accept up to 32 MB DIMMs. The other two</u> <u>sockets can accept up to 64 MB DIMMs. The maximum memory is</u> <u>therefore 160 MB.</u>

<u>APS M°Power 604e240 has a socketed CPU daughter card which can be upgraded. No specifics on upgrades or upgradability for APS M°Power 604e240 are available at this time.</u>

<u>Manufactured by:</u> <u>APS Technologies</u> <u>1-800-568-2891</u> <u>http://www.apstech.com/</u>