<u>Supported System Software: 7.5.2 or greater</u> <u>SCSI: DB-25</u> <u>Serial Ports: 2</u> <u>Sound Output: stereo 16 bit.</u> <u>ADB: 1</u> <u>Ethernet: AAUI, 10baseT</u> <u>Machine Gestalt ID: 68</u>

<u>Minutiae:</u>

## <u>Alternate 128 MB DIMM part # 7DM128M/64B-60A. Contact your</u> <u>Newer sales rep for details.</u>

## Upgraded with one DIMM at a time.

<u>This DayStar machine has four 132MHz processors on a 7500</u> motherboard.

Accelerate performance through the addition of a Newer Technology 256KB Cache DIMM, part # 7CC256B or 1MB Cache DIMM, part # 7CC1MB.

<u>Can interleave memory for approximately 10-30% faster RAM</u> access. For the fastest speed, sockets A1 & B1, A2 & B2...A4 & B4 should contain identical capacity DIMMs.

<u>Serial Port with the phone icon supports synchronous modems, with</u> <u>handshaking on both output and input supported.</u>

Has 4MB ROM and a 1.44MB SuperDrive.

<u>Manufactured by DayStar Digital, Inc.</u> <u>Technical support at 1-770-967-2077</u> <u>Email support at Support@DayStar.com</u>