

ysEnviron Errors

-5500

envNotPresent

 SysEnviron trap not present - returned
 by glue.
-5501

envBadVers

 Version non-positive
-5502

envVersTooBig

Version bigger than call can handle

Gestalt Errors

-5550

gestaltUnknownErr Could not obtain the response
-5551

gestaltUndefSelectorErr Undefined selector
-5552

gestaltDupSelectorErr Selector already exists
-5553

gestaltLocationErr Function not in system heap

-6220	kDMGenErr	Unexpected Error
-6221	kDMMirroringOnAlready	Returned by all calls that need mirroring to be off to do their thing
-6222	kDMWrongNumberOfDisplays	Can only handle 2 displays for now
-6223	kDMMirroringBlocked	DMBlockMirroring() has been called
-6224	kDMCantBlock	Mirroring is already on, can't Block now (call DMUnMirror() first)
-6225	kDMMirroringNotOn	Returned by all calls that need mirroring to be on to do their thing
-6226	kSysSWTooOld	Missing critical pieces of System Software
-6227	kDMSWNotInitializedErr	Required software not initialized (eg windowmanager or display mgr)
-6228	kDMDriverNotDisplayMgrAwareErr	Video Driver does not support display manager
-6229	kDMDisplayNotFoundErr	Could not find item
-6230	kDMDisplayAlreadyInstalledErr	Attempt to add an already installed display
-6231	kDMNoDeviceTableclothErr	DMGetGDeviceTablecloth with no tablecloth installed

LaserWriter Driver Errors

-8132

????

Manual Feed time out
-8133

????

General PostScript Error
-8150

????

No LaserWriter chosen
-8151

????

Version mismatch between LaserPrep

dictionaries
-8150

????

No LaserPrep dictionary installed
-8160

????

Zoom scale factor out of range

-8960	codecErr	unknown
-8961	noCodecErr	unknown
-8962	codecUnimpErr	unknown
-8963	codecSizeErr	unknown
-8964	codecScreenBufErr	unknown
-8965	codecImageBufErr	unknown
-8966	codecSpoolErr	unknown
-8967	codecAbortErr	unknown
-8968	codecWouldOffscreenErr	unknown
-8969	codecBadDataErr	unknown
-8970	codecDataVersErr	unknown
-8971	codecExtensionNotFoundErr	unknown
-8972	codecConditionErr	unknown
-8973	codecOpenErr	unknown
-8974	codecCantWhenErr	unknown
-8975	codecCantQueueErr	unknown
-8976	codecNothingToBlitErr	unknown
-9400	noDeviceForChannel	unknown
-9401	grabTimeComplete	unknown
-9402	cantDoThatInCurrentMode	unknown
-9403	notEnoughMemoryToGrab	unknown
-9404	notEnoughDiskSpaceToGrab	unknown
-9405	couldntGetRequiredComponent	unknown
-9406	badSGChannel	unknown
-9407	seqGrabInfoNotAvailable	unknown
-9408	deviceCantMeetRequest	unknown
-9994	badControllerHeight	unknown
-9995	editingNotAllowed	unknown

-9996	controllerBoundsNotExact	unknown
-9997	cannotSetWidthOfAttachedControler	unknown
-9998	controllerHasFixedHeight	unknown
-9999	cannotMoveAttachedController	unknown
-10000	errAEEEventFailed	unknown
-10001	telBadTermErr	Invalid TELHandle or handle not found
-10002	telBadDNErr	TELDNHandle not found or invalid
-10003	telBadCAErr	TELCAHandle not found or invalid
-10004	telBadHandErr	Bad handle specified
-10005	telBadProcErr	Bad msgProc specified
-10006	telCAUnavail	A CA is not available
-10007	telNoMemErr	No memory to allocate handle
-10008	telNoOpenErr	Unable to open terminal
-10009	errAECantSupplyType	unknown
-10010	telBadHTypeErr	Bad hook type specified
-10011	telHTypeNotSupp	Hook type not supported by this tool
-10012	telBadLevelErr	Bad volume level setting
-10013	telBadVTypeErr	Bad volume type error
-10014	telVTypeNotSupp	Volume type not supported by this too
-10015	telBadAPattErr	Bad alerting pattern specified
-10016	telAPattNotSupp	Alerting pattern not supported by too
-10017	telBadIndex	Bad index specified
-10018	telIndexNotSupp	Index not supported by this tool
-10019	telBadStateErr	Bad device state specified
-10020	telStateNotSupp	Device state not supported by tool
-10021	telBadIntExt	Bad internal external error
-10022	telIntExtNotSupp	Internal external type not supported by this tool
-10023	telBadDNDType	Bad DND type specified
-10024	telDNDTypeNotSupp	DND type is not supported by this tool
-10030	telFeatNotSub	Feature not subscribed
-10031	telFeatNotAvail	Feature subscribed but not available\
-10032	telFeatActive	Feature already active
-10033	telFeatNotSupp	Feature program call not supported by this tool
-10040	telConfLimitErr	Limit specified is too high for this configuration
-10041	telConfNoLimit	No limit was specified but required
-10042	telConfErr	Conference was not prepared
-10043	telConfRej	Conference request was rejected
-10044	telTransferErr	Transfer not prepared
-10045	telTransferRej	Transfer request rejected
-10046	telCBErr	Call back feature not set previously
-10047	telConfLimitExceeded	Attempt to exceed switch conference limits
-10050	telBadDNType	DN type invalid
-10051	telBadPageID	Bad page ID specified
-10052	telBadIntercomID	Bad intercom ID specified
-10053	telBadFeatureID	Bad feature ID specified
-10054	telBadFwdType	Bad fwdType specified
-10055	telBadPickupGroupID	Bad pickup group ID specified
-10056	telBadParkID	Bad park id specified
-10057	telBadSelect	Unable to select or deselect DN
-10058	telBadBearerType	Bad bearerType specified
-10059	telBadRate	Bad rate specified

-10060	telDNTypeNotSupp	DN type not supported by tool
-10061	telFwdTypeNotSupp	Forward type not supported by tool
-10062	telBadDisplayMode	Bad display mode specified
-10063	telDisplayModeNotSupp	Display mode not supported by tool
-10064	telNoCallbackRef	No call back reference was specified, but is required
-10070	telAlreadyOpen	Terminal already open
-10071	telStillNeeded	Terminal driver still needed by someone else
-10072	telTermNotOpen	Terminal not opened via TElOpenTerm
-10080	telCANotAcceptable	CA not "acceptable"
-10081	telCANotRejectable	CA not "rejectable"
-10082	telCANotDeflectable	CA not "deflectable"
-10090	telPBErr	Parameter block error, bad format
-10091	telBadFunction	Bad msgCode specified
-10101	telNoTools	Unable to find any telephone tools
-10102	telNoSuchTool	Unable to find tool with name specified
-10103	telUnknownErr	Unable to set config
-10106	telNoCommFolder	Communications/Extensions f not found
-10107	telInitFailed	Initialization failed
-10108	telBadCodeResource	Code resource not found
-10109	telDeviceNotFound	CrmTelephoneDevice not found
-10110	telBadProcID	Invalid procID
-10111	telValidateFailed	TelValidate failed
-10112	telAutoAnsNotOn	AutoAnswer in not turned on
-10113	telDTMFDetAlreadyOn	dtmf detection is already turned on

PictInfo Errors

-11000

pictInfoVersionErr Version number not zero
-11001

pictInfoIDErr Invalid PictInfo ID
-11002

pictInfoVerbErr Invalid verb combination specified
-11003

cantLoadPickMethodErr Custom pick method not in resource

chain
-11004

colorsRequestedErr Number out of range or greater than

passed to NewPictInfo
-11005

pictureDataErr Invalid picture data

Power Manager Errors

-13000

pmBusyErr

Power Manager IC stuck busy
-13001

pmReplyTOErr

Timed out waiting to begin reply

handshake
-13002

pmSendStartErr

Power Manager IC did not start handshake
-13003

pmSendEndErr

During send, Power Manager did not
finish handshake
-13004

pmRecvStartErr

During receive, Power Manager did not

start handshake
-13005

pmRecvEndErr

During receive, Power Manager did not

finish handshake
MacTCP Errors

-23000

ipBadLapErr Bad network configuration
-23001

ipBadCnfgErr Bad IP configuration error
-23002

ipNoCnfgErr Missing IP or LAP configuration error
-23003

ipLoadErr Error in MacTCP load
-23004

ipBadAddr Error in getting address
-23005

connectionClosing Connection in closing
-23006

invalidLength
-23007

connectionExists Request conflicts with existing

connection
-23008

connectionDoesntExist Connection does not exist
-23009

insufficientResources Insufficient resources to perform

request -23010	
invalidStreamPtr -23011	unknown
streamAlreadyOpen -23012	unknown
connectionTerminated -23013	unknown
invalidBufPtr -23014	unknown
invalidRDS -23014	unknown
invalidWDS -23015	unknown
openFailed -23016	unknown
commandTimeout -23017	unknown
duplicateSocket -23030	unknown
ipOpenProtErr -23031	Can't open new protocol, table full
ipCloseProtErr -23032	Can't find protocol to close
ipDontFragErr -23033	Packet too large to send w/o fragmenting
ipDestDeadErr -23034	Destination not responding
ipBadWDSerr -23035	Error in WDS format
icmpEchoTimeoutErr	ICMP echo timed-out

disablesInternal