

0012

COLLABORATORS

	<i>TITLE :</i> 0012		
<i>ACTION</i>	<i>NAME</i>	<i>DATE</i>	<i>SIGNATURE</i>
WRITTEN BY		August 8, 2022	

REVISION HISTORY

NUMBER	DATE	DESCRIPTION	NAME

Contents

1	0012	1
1.1	Personal Fonts Maker - F. Selection of Amiga Printer Drivers	1

Chapter 1

0012

1.1 Personal Fonts Maker - F. Selection of Amiga Printer Drivers

F. Selection of Amiga Printer Drivers

The following is a partial list of printers and some of the printer drivers which can be used in combination with those printers. Many drivers have been updated several times through the different versions of the Amiga operating system. Where the standard printer drivers provided with the Amiga operating system are not sufficient, at Cloanto we recommend alternate systems such as Studio and TurboPrint. Section 14.2 has more information on printers.

Manufacturer	Printer	Driver	Note
Alphacom	Alphapro 101	Alphacom_Alphapro_101	
Apple	Imagewriter	ImagewriterII	
Apple	Imagewriter II	ImagewriterII	
Brother	HR_15XL	Brother_HR-15XL	
Brother	xx09 and xx18 Series	EpsonX[CBM_MPS-1250]	(2)
Brother	xx24 Series	EpsonQ	(1)
Bull	Compuprint Series	EpsonX[CBM_MPS-1250]	(14)
CalComp	ColorMaster	CalComp_ColorMaster or CalComp_ColorMaster2	(10)
Canon	PJ-1080A	Canon PJ-1080A	
Canon	Bubble Jet Printers	CanonBJ10 or CanonBJC	(13) (12)
CBM	MPS 1000	CBM_MPS1000	
CBM	MPS 1224	Nec_Pinwriter	(3)
CBM	MPS 1250	EpsonX[CBM_MPS-1250]	
CBM	MPS 1500 C	EpsonX[CBM_MPS-1250] or CBM_MPS1000	(9) (8)
CBM	6400	Diablo_630	(7)
CIE	CI-3500	CBM_MPS1000	(8)
CIE	L:ips 10	EpsonX[CBM_MPS-1250]	(9)
Citizen	MSP Series	EpsonX[CBM_MPS-1250]	(2)
Citizen	Premier 35	Diablo_630	
Citizen	Swift Series	EpsonQ or Nec_Pinwriter	(1) (15)
Comrex	CR II and III	Brother_HR-15XL	

Diablo	630	Diablo_630	
Diablo	Advantage D25	Diablo_Advantage_D25	
Diablo	C-150	Diablo_C-150	
Dynax		Brother_HR-15XL	
Epson	LQ Series	EpsonQ	(1)
Epson	DX-20	Diablo_630	
Epson	EX,FX,JX,LX,MX,RX Series	EpsonX[CBM_MPS-1250]	(2)
Facit	x50 Series	EpsonX[CBM_MPS-1250]	(9)
Facit	x80 and x90 Series	EpsonQ	(1)
Fujitsu	DL Series	FujitsuDL	(12)
Fujitsu	Breeze Series	HP_DeskJet	(16)
Gemini	10X	EpsonXOld	
Hewlett-Packard	DeskJet, Black and White	HP_DeskJet	(16)
Hewlett-Packard	DeskJet, Color	HP_DeskJet550C	(16)
Hewlett-Packard	LaserJet, All Series	HP_LaserJet	
Hewlett-Packard	PaintJet	HP_PaintJet	
Hewlett-Packard	ThinkJet	HP_ThinkJet	
Howtek	Pixelmaster	Howtek_Pixelmaster	
IBM	Proprinter	CBM_MPS1000	
Juki	5510	EpsonX[CBM_MPS-1250]	(2)
Juki	6000	Diablo_630	
Juki	6100	Diablo_630	
Juki	6300	Diablo_630	
Mannesmann Tally	MT Series	EpsonQ	(1)
NEC	CP2 and CP3	EpsonX[CBM_MPS-1250]	(2)
NEC	P5,P6,P7,P9,CP6,CP7	Nec_Pinwriter	(3)
NEC	P2, P6 and P7 Plus	Nec_Pinwriter	(3)
NEC	P2200, P60, P70	Nec_Pinwriter	(3)
Oki	ML/Microline Series	EpsonQ	(1)
Okidata	192 and 193	CBM_MPS1000	(8)
Okidata	92	Okidata_92	
Okidata	292 and 293	Okidata_293I	(4)
Okidata	Okimate 20	Okimate_20	
Panasonic	KX-P 3131 and 3151	Diablo_630	
Panasonic	KX-P xx23 and xx24 Series	EpsonQ	(1)
Panasonic	1080, 1091, 1092, 1592	EpsonX[CBM_MPS-1250]	(2)
Philips	PP 40x Series	EpsonQ	(1)
Quadram	QuadJet	Quadram_QuadJet	
Qume	LetterPro 20	Qume_LetterPro_20	
Qume	Sprint2	Diablo_630	
Samsung	SP-24xx Series	EpsonQ	(1)
Seiko	5301, 5303 and 5312	Seiko_5300	(11)
Seikosha	BP, SBP, SP and SL 532	EpsonX[CBM_MPS-1250]	(2)
Seikosha	SL and LT Series	EpsonQ	(1)
Star	NL, NX, ND, NR	EpsonXOld or CBM_MPS1000	(9) (8)
Star	LC-10, FR-10	EpsonX[CBM_MPS-1250]	(2)
Star	NB24, LC24, XB24	EpsonQ	(1)
TEC	F10	Diablo_630	
Tektronix	4696	Tektronix_4696	(12)
Tektronix	4693D	Tektronix_4693D	(12)
Toshiba	P351 C, 341 and 1340	Toshiba_P351C	(5)
Toshiba	P351 SX	Toshiba_P351SX	(6)
Toshiba	P321 SL and SLC	Toshiba_P351SX	(6)
Toshiba	P341 SL and SLC	Toshiba_P351SX	(6)
Triumph Adler	TA MPR Series	EpsonQ	(1)
Xerox	4020	Xerox_4020	

Notes:

- (1) For Epson 24/48-pin printers and compatibles (360 by 360 dpi graphics). Compatible printers must be set in the Epson LQ or ESC/P2 emulation mode. Also works well in text mode on 8/9-pin printers.
 - (2) For Epson 8/9-pin printers and compatibles. Compatible printers must be set in the Epson X emulation mode. Better results in both text and graphics mode may be obtained using the EpsonXOld driver. The EpsonQ driver should be used for 24-pin printers.
 - (3) For NEC Pinwriter 24-pin printers and compatibles. Compatible printers must be set in the NEC Pinwriter emulation mode.
 - (4) The IBM interface module is required.
 - (5) Drives all Toshiba P351 C and compatibles.
 - (6) Drives all Toshiba P351 SX and compatibles.
 - (7) The Centronics option is required.
 - (8) The printer must be in IBM mode to use the CBM_MPS1000 driver. Some functions may not be activated.
 - (9) To use the EpsonX driver, the printer must be in Epson mode. Some features may not be supported. Note (2) also applies.
 - (10) The CalComp_ColorMaster driver should be used on systems with less than 1 Mbyte of RAM. The CalComp_ColorMaster2 driver is faster, but uses more memory. Both drivers also work with the CalComp ColorView printer.
 - (11) The Seiko_5300a driver is also available. The Seiko_5300a is faster than the standard Seiko_5300, but it requires more memory. Note (12) also applies.
 - (12) These drivers are not included on the Workbench and Extras disks. They may be available from the printer manufacturer, in Amiga disk collections (e.g. Fish Disk) and electronic networks (e.g. Internet/Aminet, CompuServe, BIX).
 - (13) New drivers introduced with version 2.1 of the Amiga operating system.
 - (14) Tests have shown that 9-pin Epson drivers may yield better printouts than IBM and EpsonQ drivers even on 24-pin printers. Note 9 may also apply.
 - (15) The improved Print Manager Amiga drivers are available from Citizen. Note 3 also applies.
 - (16) New drivers developed by Commodore and Cloanto.
-