

Assembled By Steve Maller (415)621-3904 or E-mail 70436,1745

Type
<shift>
<PrtSc>
for a
printout
of
directions

Sheet1

Menu of Print Options for Lotus 1-2-3 Worksheet Printer Codes Written For Epson FX-80/100

Directions For Implementation:

- (1) Do a File Retrieve to load worksheet into which you plan to insert this plan.
- (2) **Important!**
worksheet (must have at least 40 rows X 6 columns).
- (3) Perform a File/Combine/Copy/Named Range, using this worksheet and the Range named "POM".
- (4) Once entered in your worksheet, perform a Range Name Create on the upper left cell, the one which says "/xmP.O.M.-", and call it "\P" or whatever your preference is for it's Macro Name. Then type <alt>-P and see what happens.

FX-80/100

Find an open area of your

/xmP.O.M.~

Config. 1

Print in normal mode

/ppcar.{?}~aq

/xmNORMAL~

Print Header/Footer Sub-menu

Header

Enter Text of Header (type in "@" for date in title)

/ppohr{esc}{?}~qq

/xmP.O.M.~

Normal

No enhancements

/xmP.O.M.~

Print Options Menu

Config. 2

Print in Tiny print mode

```
/ppca  
oou  
sr{esc}  
\027\083\048\015\0273\013~q  
ar.{?}~q  
/xmP.O.M.~
```

Config. 3

Print with condensed print and 1/8" line spacing

```
/ppcaos  
\015\0270~  
p88~mr128~  
qr.{?}~q  
/xmP.O.M.~
```

Footer

Enter Text of Footer (type in "p #" for page count)

```
/ppofr{ESC}{?}~qq  
/xmP.O.M.~
```

Print Normal Sub-menu

Emphasized

Emphasized character font

```
/ppos\027\069~qq  
/xmP.O.M.~
```

| Header/Footer | Begin | Quit |
|-----------------------|---------------------|---------------------------------|
| Enter header & footer | Begin Printing | Quit this menu without Printing |
| /xmPOM_S.M.~ | /ppgcarblank_space~ | |
| /xmP.O.M.~ | os\027\064~ouqgq | |