

The fourth sequence on top is set for a 150 dpi resolution.
 This should print the 30 column wide arrow 0.20 inches wide
 which is 30 dots divided by 150 dots per inch resolution.

```

X
←E←&l10C←*p600x600Y←*t150R←*r1A
←*b4W⊙ ⊙←*b4W⊙⊙0⊙←*b4W⊙⊙8⊙←*b4W⊙⊙<⊙
←*b4W⊙⊙>⊙←*b4W⊙⊙?⊙←*b4W   Ç←*b4W   L
←*b4W   α←*b4W   ≡←*b4W   °←*b4W   n
←*b4W   °←*b4W   ≡←*b4W   α←*b4W   L
←*b4W   Ç←*b4W⊙⊙?⊙←*b4W⊙⊙>⊙←*b4W⊙⊙<⊙
←*b4W⊙⊙8⊙←*b4W⊙⊙0⊙←*b4W⊙⊙ ⊙
←*rB←E                                     X
  
```

Set TMC system variable "zz" to the device name of your
 printer by key-in:
 TMC> zz lpt1
 Execute "wrt" with a left mouse button click on the menu bar
 followed with left mouse button clicks at the spots
 indicated with the X's above.

Below are shown the images for all four possible degrees of
 resolution. This group of images can be produced by stacking
 four sets of the above data and editing the X and Y
 coordinate values and the resolution values in their
 respective escape sequences in each set. Also the first and
 second sequence on top is only needed in the first set of
 data and the second sequence on the bottom is only needed
 in the last set of data. Then using TMC command "wrt" the
 entire group can be sent to the printer at once by doing
 left mouse button clicks at two diagonally opposite corners
 of the group.

