

ATTENUATOR DESIGN DATA

Design data for symmetrical Pi or T attenuators:-

Impedance	50 Ohms	
Attenuation	10 dB	
Resistors:-	R1	R2 š
Pi-attenuator	96.25	71.15 Ohms
T-attenuator	25.97	35.14 Ohms

Design data for unbalanced Pi or T attenuators:-

Attenuation	10 dB		
Input impedance	50 Ohms		
Output impedance	50 Ohms		
Resistors:	R1	R2	R3 š
Pi-attenuator	96.25	96.25	71.15 Ohms
T-attenuator	25.97	25.97	35.14 Ohms