# Kalman Ancilla 1.51 Call Tree Diagram
## Incoming Caller Options

Welcome Message 10

- Setup as Telephone Answering Machine (TAM) only
- Press [1-7] for designated Mailbox
- Enter Directory Number
- For Mailbox List Press #
- For Help Press 9
- For Operator Press 0
- To Terminate Call Press *
- Personal Options 8

Record Message at the tone

Mailbox Number Confirmed

Enter name using TT keys

Not in directory, return to main menu

Enter Mailbox Number

TO: User Setup Options

Access messages remotely during TAM greeting

Pressing 8 will place you at the voice mail tree, where you can retrieve your messages

Leave Voice Message 1

Leave Fax Message 2

Request Fax 3

User Setup 8

TO: User Setup Options

Press Start to send fax

Return to message options

Press # to receive this session

Enter fax number

Check for blocked number

Number Confirmed

Number Correct 1
Re-enter number 2
Hear number 3

Enter 1-digit fax request

Number rejected, try again

Enter another digit

Press # to end fax request

Fax(es) sent then disconnect

Message: Fax will be sent ASAP or press * to go back to main menu