

Modem Options

The Modem Options dialog box allows you to change the modem settings for PhoneWatcher.

- Using the popup menu at the top, choose the port that your modem is connected to.
- When using modems from various manufacturers, you may need to set the modem initialization and caller ID activation strings for your particular modem.
In most cases, the initialization string can be left alone at "AT&F1", which is the default. You can use the popup box to choose the brand of modem you are using to enter the Caller ID activation string for you.

NOTE: If you are utilizing the paging feature of PhoneWatcher, you should include "E0" (that's a zero) in your initialization string to make sure the pages go through.
If you have voice messaging on your telephone, you may want to include "X1" in your initialization string in order to allow PhoneWatcher to dial out properly.