# **OPL3 Synth**

Use the OPL3 Synth option to configure the operation of your internal MIDI synthesis device. Choose one of the following options for information about the dialog box:

See Also About FM Synthesis Patch Options Channel Options
Voice Modes

# **Patches**

▶ Choose the Patches button to display the Patch Sets dialog. Use the Patch Sets dialog to change a patch set used by the synthesis driver.

The Patches button is only displayed when extra patch sets are available.

# **Channel Config**

oose the Channel Config button to display the channel options. ne operation of each MIDI channel.	Use the Channel options to

# **Enable Stereo**

The synthesis driver can be configured to play in stereo or mono.

Choose the Channel Config button to enable/disable stereo operation.

When stereo operation is disabled the connection setting in the channel options is ignored.

# **Voice Mode**

The synthesis driver can be configured to play in one of 8 modes. Each mode selects a different number of voices available to a MIDI application.

Change the voice mode by selecting a mode from the drop down list box.

# **About FM Synthesis**

The OPL3 synthesizer is an FM synthesis module which provides a great amount of flexibility in the synthesis of MIDI music. The synthesizer can operate in a number of modes combining, 4 Operator, 2 Operator, and Drum synthesis. 4 Operator synthesis typically provides a "richer" sounding instrument over 2 Operator synthesis.

# **Patch Options**

The Patch Options dialogs allows you to select a new patch set for one of the three types of patches. Choosing Default for a patch set, will reset the patches for that set to the default patches stored in the OPL3 synthesis driver.

# To change a patch set:

- 1) Select a new patch set from one of the drop down list boxes.
- 2) Press the OK button to allow your changes to take effect.

The Patches options are displayed only when extra patch sets are available.

# **Channel Options**

The Channel Options allow you to specify how each MIDI channel will produce sound. The MIDI channel options are:

### Connect:

Specifies whether notes on the specified MIDI channel will sound from the left speaker, right speaker, or both (Center Channel).

## Polyphony:

Specifies the maximum number of notes that can be on at one time for the specified channel.

### 2 Operator Enable:

Specifies whether 2 operator voices will be used on the specified channel.

## 4 Operator Enable:

Specifies whether 4 operator voices will be used on the specified channel.

# To change a MIDI channel option:

- 1) Select the channel to configure from the Channel drop down list box.
- 2) Change the option either via a drop down list box or a check box.
- 3) Channel changes take effect when the OK button is pressed.

### **Voice Modes**

The OPL3 synthesizer allows you to configure the synthesizer in 8 different modes. Each mode has a different number of voices consisting of 2 operator, 4 operator, and drum sounds. Typically 4 operator sounds will sound "fuller" than 2 operator sounds, however each 4 operator note takes up two 2 operator notes.

There are two drum generation methods for the voice modes, **Standard Drums** and **Melodic Drums**. Standard drums allows for 5 simultaneous drum sounds using only 3 2operator voices. This allows for a large drum polyphony but also leads to a "thinner" drum sound. Melodic drums uses 1 2 operator voice for each drum sound allowing less polyphony but a more realist sounding drum kit.

Typically the two best modes for synthesis are the **6-4Op 6-2Op Melodic Drums** mode and the **18-2Op Melodic Drums** mode.

The voice modes are as follows:

### 9-2Op Melodic Drums

9 2 operator voices are available for melodic notes. Drum kit sounds are generated using 2 op melodic voices.

### 6-2Op Standard Drums

6 2 operator voices are available for melodic notes. Drum kits sounds are generated using 1 op percussive voices.

## 18-2Op Melodic Drums

18 2 operator voices are available for melodic notes. Drum kit sounds are generated using 2 op melodic voices. This mode allows the greatest polyphony along with the more realistic drum sounds.

## 15-20p Standard Drums

15 2 operator voices are available for melodic notes. Drum kits sounds are generated using 1 op percussive voices. This mode offers the most notes on at one time (15 melodic notes + 5 percussive notes)..

### 3-4Op 9-2Op Melodic Drums

3 4 operator voices and 9 2 operator voices are available for melodic notes. Drum kit sounds are generated using 2 op melodic voices.

#### 3-40p 12-20p Standard Drums

3 4 operator voices and 9 2 operator voices are available for melodic notes. Drum kits sounds are generated using 1 op percussive voices.

## 6-40p 3-20p Standard Drums

9 2 operator voices are available for melodic notes. Drum kits sounds are generated using 1 op percussive voices.

### 6-4Op 6-2Op Melodic Drums

6 4 operator voices and 9 2 operator voices are available for melodic notes. Drum kit sounds are generated using 2 op melodic voices. This mode offers the most notes while also providing the richness of 4 operator sound and realistic drum generation.