

Supported Systems Software: 7.5.3

SCSI: DB-25

Serial Ports: 2

Sound Output: 16-bit stereo 44.1 KHz sample rate

ADB: 1, plus additional port for PS/2 keyboard

Ethernet: Add-in card

Machine Gestalt ID: ???

Minutiae:

StarMax can take only EDO DIMMs. It does not support interleaved memory. The three DIMM sockets are NOT identical. The first socket, which comes stock with a 32 MB DIMM installed, can only accept up to 32 MB DIMMs. The other two sockets can accept up to 64 MB DIMMs. The maximum memory is therefore 160 MB.

Each StarMax system comes with 32 MB RAM, a 1.2GB IDE hard drive, 8x CD-ROM, 2 MB IDO DRAM for graphics, and a 256K Level-2 Cache.

Manufactured by:

Motorola Computer Group

1-800-759-1107

<http://www.mot.com/computer/starmax>