

Modem Options

(NeXT System 2 & System 3)

Most of the selections in this option view are self explanatory. A brief summary of each is given below:

1. The *If no answer, retry* pop-up determines the number of times the modem will retry in the event a dialed number is busy or goes unanswered.
2. The *Answer calls after* pop-up determines the number of times the modem will allow the phone to ring before answering. If you do not want the modem to answer any incoming calls, choose No Answer.
3. The *Speaker on* pop-up determines what period of time the modem speaker remains on during an outgoing call. You can choose to have it on at all times, or turn it off after dialing is complete. To turn the speaker off completely, set the volume slider to a value of zero.
4. The *Speaker Volume* slider controls the speaker volume. Volume controls are limited to the range offered by the modem manufacturer. The maximum value of ten does not necessarily imply that there are ten different volume settings available for a given modem. A value of zero turns the speaker off during all operations.
5. The *Dialing* pop-up determines whether tone or pulse dialing is used for outgoing calls. If your telephone service does not offer tone dialing, you must

select the pulse option before the modem can successfully dial out.

6. The *Modem's Number* field will pass a maximum of twenty characters (the *subscriber ID*) to a remote fax machine or modem whenever a fax connection occurs. It is recommended that you use this space to enter the telephone number of your fax modem (although the field can be used for any string of characters which might identify the connection).