

SP Voice reset (reference) -> err

reference	integer	specifys the channel you want to reset. Use the reference number obtained from the SP Open Voice function.
err	integer	returns the error which occurred. A value of zero indicates no error occurred. See below for a list of possible errors.

Resets the specified speech channel to the default settings.

This function resets all values to the default state, as if you just opened the voice and haven't changed the rate or pitch. It also resets the input mode and other settings you may have changed using embedded speech commands.

Example:

```
$err := SP Voice reset ($speechref)
```

Possible errors:

- 0 No Error
- 4 Speech Pack can not be used (Speech Mgr not available)
- 50 Parameter error (inside external, not necessarily the parameters you pass)
- 231 Feature not implemented on synthesizer
- 3000 Invalid SpeechChannel parameter, probably invalid reference number