on color borders. It spreads pixels that have a Value between selected thresholds, in selected directions. Options Propagate Mode The examples will be about the following image (zomm x8): More White: Pixels will be propagated from upper Value pixels towards lower Value pixels. So bright areas will enlarge. More Black: Pixels will be propagated from lower Value pixels towards upper Value pixels. So dark areas will enlarge. Middle Value to Peaks: On a border between the selected thresholds, it blends the two colors. Foregound to Peaks: The propagated areas will be filled with the foreground color of the toolbox. Only Foreground: Only areas with the Foreground color will propagate. Only Background: Only areas with the Background color will propagate. More Opaque and More Tranparent: These commands work like More White and More Black. Propagated areas will be more opaque or more transparent. These commands need an image with an Alpha channel. Parameters Settings Lower Threshold and Upper Threshold: These commands allow you to set the Value range that will be concerned by Propagate. Propagating Rate: That's the propagating amount. The higher it will be the more colored the propagation will be. Propagating Direction: You can select one or more directions. Prev Up Next 10.12. Video Home 10.14. Waves