

**Supported System Software:** 7.5.2 or greater

**SCSI:** DB-25

**Serial Ports:** 2

**Sound Output:** stereo 16 bit.

**ADB:** 1

**Ethernet:** AAUI, 10baseT

**Machine Gestalt ID:** 69

**Minutiae:**

**Alternate 128 MB DIMM part # 7DM128M/64B-60A. Contact your Newer sales rep for details.**

**Upgraded with one DIMM at a time.**

**This DayStar machine has four 200MHz processors on a 9500 motherboard.**

**Can interleave memory for approximately 10-30% faster RAM access. For the fastest speed, sockets A1 & B1, A2 & B2...A4 & B4 should contain identical capacity DIMMs.**

**Serial Port with the phone icon supports synchronous modems, with handshaking on both output and input supported.**

**Has 4MB ROM and a 1.44MB SuperDrive.**

**Manufactured by DayStar Digital, Inc.**

**Technical support at 1-770-967-2077**

**Email support at Support@DayStar.com**