

# Miscellaneous Keys

More: [Keyboard Shortcuts](#), [Color Keys](#), [Waveform Keys](#)

## Oscillator Speeds

The number keys (0-9) can be used to set all of the oscillators to a given speed. Zero is a speed of zero, so colors will not blend.

- = slower speeds
- \_ = much slower speeds
- = = faster speeds
- + = much faster speeds
- Option-shift-e = random speeds

## Oscillator Ranges

- Option-d = darker ranges
- Option-l = lighter ranges
- Option-f = full ranges
- Option-w = wider ranges
- Option-shift-n = narrower ranges
- / = random ranges

## Miscellaneous Keys

- Comma = start/stop color animation
- Space = random color
- ; = repeat last random color
- [ = reverse directions
- Escape = avoid resetting oscillators

- Option-s = HSL color model
  - Option-r = RGB color model
  - Option-v = HSV color model
  - Option-m = next color model
- The color models are RGB, HSV, and HSL.  
RGB stands for Red/Green/Blue.  
HSV stands for Hue/Saturation/Value.  
HSL stands for Hue/Saturation/Lightness.

[Table of Contents](#)